

VMware Deliverable Release Notes

This document does not apply to HPE Superdome servers. For information on HPE Superdome, see the following links:

[HPE Integrity Superdome X](#)
[HPE Superdome Flex](#)

Information on HPE Synergy supported VMware ESXi OS releases, HPE ESXi Custom Images and HPE Synergy Custom SPPs is available at:

[OS Support Tool for HPE Synergy](#)

Information on HPE Synergy Software Releases is available at:

[HPE Synergy Software Releases - Overview](#)

Gen10 SPP 2026.07.00.00 Release Notes for VMware ESXi 8.0 U3

[BIOS - System ROM](#)
[Driver - Lights-Out Management](#)
[Driver - Network](#)
[Driver - Storage Controller](#)
[Firmware - Management](#)
[Firmware - Network](#)
[Firmware - Storage Controller](#)
[Firmware - Storage Fibre Channel](#)
[Software - Management](#)
[Software - Storage Controller](#)
[Software - Storage Fibre Channel](#)
[Software - System Management](#)

BIOS - System ROM

[Top](#)

ROM Flash Firmware Package - HPE Apollo 4200 Gen10/HPE ProLiant XL420 Gen10 (U39) Servers
Version: 3.66_04-01-2026 **(Optional)**
Filename: U39_3.66_04_01_2026.fwpkg

Important Note!

Important Notes:

This version of the System ROM should be paired with Server Platform Services (SPS) Firmware 04.01.05.201.

Details about reported security vulnerabilities and their mitigation can be found at the following link [Security Bulletin Library | HPE Support](#).

Deliverable Name:

HPE Apollo 4200 Gen10/ProLiant XL420 Gen10 System ROM - U39

Release Version:

3.66_04-01-2026

Last Recommended or Critical Revision:

3.64_02-05-2026

Previous Revision:

3.64_02-05-2026

Firmware Dependencies:

None

Enhancements/New Features:

Updated HPE branding logos across all boot screens (early POST, late POST, System Utility, and BGRT) to reflect the new HPE corporate identity.

Enabled "BIOS log to AHS every boot" by default after a ROM update; users can disable via RBSU.

Problems Fixed:

None

Known Issues:

None

Enhancements

Important Notes:

This version of the System ROM should be paired with Server Platform Services (SPS) Firmware 04.01.05.201.

Details about reported security vulnerabilities and their mitigation can be found at the following link [Security Bulletin Library | HPE Support](#).

Firmware Dependencies:

None

Enhancements/New Features:

Updated HPE branding logos across all boot screens (early POST, late POST, System Utility, and BGRT) to reflect the new HPE corporate identity.

Enabled "BIOS log to AHS every boot" by default after a ROM update; users can disable via RBSU.

Known Issues:

None

ROM Flash Firmware Package - HPE Apollo 4510 Gen10/HPE ProLiant XL450 Gen10 (U40) Servers
Version: 3.66_04-01-2026 **(Optional)**
Filename: U40_3.66_04_01_2026.fwpkg

Important Note!

Important Notes:

This version of the System ROM should be paired with Server Platform Services (SPS) Firmware 04.01.05.201.

Details about reported security vulnerabilities and their mitigation can be found at the following link [Security Bulletin Library | HPE Support](#).

Deliverable Name:

HPE Apollo 4510 Gen10/HPE ProLiant XL450 Gen10 System ROM - U40

Release Version:

3.66_04-01-2026

Last Recommended or Critical Revision:

3.64_02-05-2026

Previous Revision:

3.64_02-05-2026

Firmware Dependencies:

None

Enhancements/New Features:

Updated HPE branding logos across all boot screens (early POST, late POST, System Utility, and BGRT) to reflect the new HPE corporate identity.

Enabled "BIOS log to AHS every boot" by default after a ROM update; users can disable via RBSU.

Problems Fixed:

None

Known Issues:

None

Enhancements

Important Notes:

This version of the System ROM should be paired with Server Platform Services (SPS) Firmware 04.01.05.201.

Details about reported security vulnerabilities and their mitigation can be found at the following link [Security Bulletin Library | HPE Support](#).

Firmware Dependencies:

None

Enhancements/New Features:

Updated HPE branding logos across all boot screens (early POST, late POST, System Utility, and BGRT) to reflect the new HPE corporate identity.

Enabled "BIOS log to AHS every boot" by default after a ROM update; users can disable via RBSU.

Known Issues:

None

ROM Flash Firmware Package - HPE ProLiant DL160 Gen10/DL180 Gen10 (U31) Servers

Version: 3.66_04-01-2026 (**Optional**)

Filename: U31_3.66_04_01_2026.fwpkg

Important Note!

Important Notes:

This version of the System ROM should be paired with Server Platform Services (SPS) Firmware 04.01.05.201.

Details about reported security vulnerabilities and their mitigation can be found at the following link [Security Bulletin Library | HPE Support](#).

Deliverable Name:

HPE ProLiant DL160 Gen10/DL180 Gen10 System ROM - U31

Release Version:

3.66_04-01-2026

Last Recommended or Critical Revision:

3.64_02-05-2026

Previous Revision:

3.64_02-05-2026

Firmware Dependencies:

None

Enhancements/New Features:

Updated HPE branding logos across all boot screens (early POST, late POST, System Utility, and BGRT) to reflect the new HPE corporate identity.

Enabled "BIOS log to AHS every boot" by default after a ROM update; users can disable via RBSU.

Problems Fixed:

None

Known Issues:

None

Enhancements

Important Notes:

This version of the System ROM should be paired with Server Platform Services (SPS) Firmware 04.01.05.201.

Details about reported security vulnerabilities and their mitigation can be found at the following link [Security Bulletin Library | HPE Support](#).

Firmware Dependencies:

None

Enhancements/New Features:

Updated HPE branding logos across all boot screens (early POST, late POST, System Utility, and BGRT) to reflect the new HPE corporate identity.

Enabled "BIOS log to AHS every boot" by default after a ROM update; users can disable via RBSU.

Known Issues:

None

ROM Flash Firmware Package - HPE ProLiant DL20 Gen10 (U43) Servers

Version: 3.76_05-28-2026 **(Optional)**

Filename: U43_3.76_05_28_2026.fwpkg

Fixes

Important Notes:

This version of the System ROM should be paired with Server Platform Services (SPS) Firmware 05.01.05.103.

Details about reported security vulnerabilities and their mitigation can be found at the following link [Security Bulletin Library | HPE Support](#).

Firmware Dependencies:

None

Problems Fixed:

Resolved a security vulnerability where a NULL pointer dereference could cause a system crash during boot if an internal memory allocation failed during the ExitBootServices or boot option launch sequence.

Addressed an issue where the Minimum Processor Idle Power Core C-State and Minimum Processor Idle Power Package C-State options were not appearing in System Configuration (RBSU) under Power and Performance Options on ML30 Gen10 and DL20 Gen10 platforms.

Known Issues:

None

Enhancements

Improved BIOS debug log diagnostics by including POST code events, boot target OS information, and RTC timestamps for enhanced triage support.

Enabled medium-level debug message logging for shared memory and CHIF methods, aligning Gen10 Active Health System (AHS) log collection with Gen10 Plus and later platforms.

ROM Flash Firmware Package - HPE ProLiant DL20 Gen10 Plus Servers

Version: 2.64_04-01-2026 **(Recommended)**

Filename: U60_2.64_04_01_2026.fwpkg

Important Note!

Important Notes:

None

Details about reported security vulnerabilities and their mitigation can be found at the following link [Security Bulletin Library | HPE Support](#).

Deliverable Name:

HPE System ROM - U60

Release Version:

2.64_04-01-2026

Last Recommended or Critical Revision:

2.62_03-05-2026

Previous Revision:

2.62_03-05-2026

Firmware Dependencies:

None

Enhancements/New Features:

Updated HPE branding logos across all boot screens (early POST, late POST, System Utility, and BGRT) to reflect the new HPE corporate identity.

Added multi-language translation support for Chinese and Japanese in RBSU setup menus.

Problems Fixed:

Addressed an issue where ESKM (Enterprise Secure Key Manager) server keys could be generated with invalid bytes, potentially causing Self-Encrypting Drive (SED) unlock failures. Keys are now validated upon generation and corrected during drive unlock operations if previously affected.

Known Issues:

None

Fixes

Important Notes:

None

Details about reported security vulnerabilities and their mitigation can be found at the following link [Security Bulletin Library | HPE Support](#).

Firmware Dependencies:

None

Problems Fixed:

Addressed an issue where ESKM (Enterprise Secure Key Manager) server keys could be generated with invalid bytes, potentially causing Self-Encrypting Drive (SED) unlock failures. Keys are now validated upon generation and corrected during drive unlock operations if previously affected.

Known Issues:

None

Enhancements

Updated HPE branding logos across all boot screens (early POST, late POST, System Utility, and BGRT) to reflect the new HPE corporate identity.

Added multi-language translation support for Chinese and Japanese in RBSU setup menus.

ROM Flash Firmware Package - HPE ProLiant DL325 Gen10 (A41) Servers

Version: 3.80_05-28-2026 (**Optional**)

Filename: A41_3.80_05_28_2026.fwpkg

Important Note!

Important Notes:

This revision of the System ROM includes AMD reference code RomePI 1.0.0.Q for AMD 2nd Generation EPYC processors. This revision of the System ROM includes AMD reference code NaplesPI 1.0.0.T for AMD 1st Generation EPYC processors.

Details about reported security vulnerabilities and their mitigation can be found at the following link [Security Bulletin Library | HPE Support](#).

Deliverable Name:

HPE ProLiant DL325 Gen10 System ROM - A41

Release Version:

3.80_05-28-2026

Last Recommended or Critical Revision:

3.72_04-01-2026

Previous Revision:

3.72_04-01-2026

Firmware Dependencies:

None

Enhancements/New Features:

This revision of the System ROM includes AMD reference code RomePI 1.0.0.Q for AMD 2nd Generation EPYC processors.

This revision of the System ROM includes AMD reference code NaplesPI 1.0.0.T for AMD 1st Generation EPYC processors.

Problems Fixed:

Resolved potential system stability issues related to buffer validation in hardware error handling routines during System Management Mode operations on different-socket (Rome) configurations.

Known Issues:

None

Fixes

Important Notes:

This revision of the System ROM includes AMD reference code RomePI 1.0.0.Q for AMD 2nd Generation EPYC processors. This revision of the System ROM includes AMD reference code NaplesPI 1.0.0.T for AMD 1st Generation EPYC processors.

Details about reported security vulnerabilities and their mitigation can be found at the following link [Security Bulletin Library | HPE Support](#).

Firmware Dependencies:

None

Problems Fixed:

Resolved potential system stability issues related to buffer validation in hardware error handling routines during System Management Mode operations on different-socket (Rome) configurations.

Known Issues:

None

Enhancements

This revision of the System ROM includes AMD reference code RomePI 1.0.0.Q for AMD 2nd Generation EPYC processors.

This revision of the System ROM includes AMD reference code NaplesPI 1.0.0.T for AMD 1st Generation EPYC processors.

ROM Flash Firmware Package - HPE ProLiant DL360 Gen10 (U32) Servers

Version: 3.66_04-01-2026 **(Optional)**

Filename: U32_3.66_04_01_2026.fwpkg

Important Note!

Important Notes:

This version of the System ROM should be paired with Server Platform Services (SPS) Firmware 04.01.05.201.

Details about reported security vulnerabilities and their mitigation can be found at the following link [Security Bulletin Library | HPE Support](#).

Deliverable Name:

HPE ProLiant DL360 Gen10 System ROM - U32

Release Version:

3.66_04-01-2026

Last Recommended or Critical Revision:

3.64_02-05-2026

Previous Revision:

3.64_02-05-2026

Firmware Dependencies:

None

Enhancements/New Features:

Updated HPE branding logos across all boot screens (early POST, late POST, System Utility, and BGRT) to reflect the new HPE corporate identity.

Enabled "BIOS log to AHS every boot" by default after a ROM update; users can disable via RBSU.

Problems Fixed:

None

Known Issues:

None

Enhancements

Important Notes:

This version of the System ROM should be paired with Server Platform Services (SPS) Firmware 04.01.05.201.

Details about reported security vulnerabilities and their mitigation can be found at the following link [Security Bulletin Library | HPE Support](#).

Firmware Dependencies:

None

Enhancements/New Features:

Updated HPE branding logos across all boot screens (early POST, late POST, System Utility, and BGRT) to reflect the new HPE corporate identity.

Enabled "BIOS log to AHS every boot" by default after a ROM update; users can disable via RBSU.

Known Issues:

None

ROM Flash Firmware Package - HPE ProLiant DL380 Gen10 (U30) Servers
Version: 3.66_04-01-2026 **(Optional)**
Filename: U30_3.66_04_01_2026.fwpkg

Important Note!

Important Notes:

This version of the System ROM should be paired with Server Platform Services (SPS) Firmware 04.01.05.201.

Details about reported security vulnerabilities and their mitigation can be found at the following link [Security Bulletin Library | HPE Support](#).

Deliverable Name:

HPE System ROM - U30

Release Version:

3.66_04-01-2026

Last Recommended or Critical Revision:

3.64_02-05-2026

Previous Revision:

3.64_02-05-2026

Firmware Dependencies:

None

Enhancements/New Features:

Updated HPE branding logos across all boot screens (early POST, late POST, System Utility, and BGRT) to reflect the new HPE corporate identity.

Enabled "BIOS log to AHS every boot" by default after a ROM update; users can disable via RBSU.

Problems Fixed:

None

Known Issues:

None

Enhancements

Important Notes:

This version of the System ROM should be paired with Server Platform Services (SPS) Firmware 04.01.05.201.

Details about reported security vulnerabilities and their mitigation can be found at the following link [Security Bulletin Library | HPE Support](#).

Firmware Dependencies:

None

Enhancements/New Features:

Updated HPE branding logos across all boot screens (early POST, late POST, System Utility, and BGRT) to reflect the new HPE corporate identity.

Enabled "BIOS log to AHS every boot" by default after a ROM update; users can disable via RBSU.

Known Issues:

None

ROM Flash Firmware Package - HPE ProLiant DL385 Gen10 (A40) Servers
Version: 3.80_05-28-2026 **(Optional)**
Filename: A40_3.80_05_28_2026.fwpkg

Important Note!

Important Notes:

This revision of the System ROM includes AMD reference code RomePI 1.0.0.Q for AMD 2nd Generation EPYC processors. This revision of the System ROM includes AMD reference code NaplesPI 1.0.0.T for AMD 1st Generation EPYC processors.

Details about reported security vulnerabilities and their mitigation can be found at the following link [Security Bulletin Library | HPE Support](#).

Deliverable Name:

HPE System ROM - A40

Release Version:

3.80_05-28-2026

Last Recommended or Critical Revision:

3.72_04-01-2026

Previous Revision:

3.72_04-01-2026

Firmware Dependencies:

None

Enhancements/New Features:

This revision of the System ROM includes AMD reference code RomePI 1.0.0.Q for AMD 2nd Generation EPYC processors.

This revision of the System ROM includes AMD reference code NaplesPI 1.0.0.T for AMD 1st Generation EPYC processors.

Problems Fixed:

Resolved potential system stability issues related to buffer validation in hardware error handling routines during System Management Mode operations on different-socket (Rome) configurations.

Known Issues:

None

Fixes

Important Notes:

This revision of the System ROM includes AMD reference code RomePI 1.0.0.Q for AMD 2nd Generation EPYC processors. This revision of the System ROM includes AMD reference code NaplesPI 1.0.0.T for AMD 1st Generation EPYC processors.

Details about reported security vulnerabilities and their mitigation can be found at the following link [Security Bulletin Library | HPE Support](#).

Firmware Dependencies:

None

Problems Fixed:

Resolved potential system stability issues related to buffer validation in hardware error handling routines during System Management Mode operations on different-socket (Rome) configurations.

Known Issues:

None

Enhancements

This revision of the System ROM includes AMD reference code RomePI 1.0.0.Q for AMD 2nd Generation EPYC processors.

This revision of the System ROM includes AMD reference code NaplesPI 1.0.0.T for AMD 1st Generation EPYC processors.

ROM Flash Firmware Package - HPE ProLiant DL560 Gen10/DL580 Gen10 (U34) Servers

Version: 3.66_04-01-2026 **(Optional)**

Filename: U34_3.66_04_01_2026.fwpkg

Important Note!

Important Notes:

This version of the System ROM should be paired with Server Platform Services (SPS) Firmware 04.01.05.201.

Details about reported security vulnerabilities and their mitigation can be found at the following link [Security Bulletin Library | HPE Support](#).

Deliverable Name:

HPE ProLiant DL560 Gen10/DL580 Gen10 System ROM - U34

Release Version:

3.66_04-01-2026

Last Recommended or Critical Revision:

3.64_02-05-2026

Previous Revision:

3.64_02-05-2026

Firmware Dependencies:

None

Enhancements/New Features:

Updated HPE branding logos across all boot screens (early POST, late POST, System Utility, and BGRT) to reflect the new HPE corporate identity.

Enabled "BIOS log to AHS every boot" by default after a ROM update; users can disable via RBSU.

Problems Fixed:

None

Known Issues:

None

Enhancements

Important Notes:

This version of the System ROM should be paired with Server Platform Services (SPS) Firmware 04.01.05.201.

Details about reported security vulnerabilities and their mitigation can be found at the following link [Security Bulletin Library | HPE Support](#).

Firmware Dependencies:

None

Enhancements/New Features:

Updated HPE branding logos across all boot screens (early POST, late POST, System Utility, and BGRT) to reflect the new HPE corporate identity.

Enabled "BIOS log to AHS every boot" by default after a ROM update; users can disable via RBSU.

Known Issues:

None

ROM Flash Firmware Package - HPE ProLiant MicroServer Gen10 Plus v2 (U64) Servers

Version: 2.64_04-01-2026 (**Recommended**)

Filename: U64_2.64_04_01_2026.fwpkg

Important Note!

Important Notes:

None

Details about reported security vulnerabilities and their mitigation can be found at the following link [Security Bulletin Library | HPE Support](#).

Deliverable Name:

HPE ProLiant MicroServer Gen10 Plus v2 System ROM - U64

Release Version:

2.64_04-01-2026

Last Recommended or Critical Revision:

2.62_03-05-2026

Previous Revision:

2.62_03-05-2026

Firmware Dependencies:

None

Enhancements/New Features:

Updated HPE branding logos across all boot screens (early POST, late POST, System Utility, and BGRT) to reflect the new HPE corporate identity.

Added multi-language translation support for Chinese and Japanese in RBSU setup menus.

Problems Fixed:

Addressed an issue where ESKM (Enterprise Secure Key Manager) server keys could be generated with invalid bytes, potentially causing Self-Encrypting Drive (SED) unlock failures. Keys are now validated upon generation and corrected during drive unlock operations if previously affected.

Known Issues:

None

Fixes

Important Notes:

None

Details about reported security vulnerabilities and their mitigation can be found at the following link [Security Bulletin Library | HPE Support](#).

Firmware Dependencies:

None

Problems Fixed:

Addressed an issue where ESKM (Enterprise Secure Key Manager) server keys could be generated with invalid bytes, potentially causing Self-Encrypting Drive (SED) unlock failures. Keys are now validated upon generation and corrected during drive unlock operations if previously affected.

Known Issues:

None

Enhancements

Updated HPE branding logos across all boot screens (early POST, late POST, System Utility, and BGRT) to reflect the new HPE corporate identity.

Added multi-language translation support for Chinese and Japanese in RBSU setup menus.

ROM Flash Firmware Package - HPE ProLiant ML110 Gen10 (U33) Servers

Version: 3.66_04-01-2026 (**Optional**)

Filename: U33_3.66_04_01_2026.fwpkg

Important Note!

Important Notes:

This version of the System ROM should be paired with Server Platform Services (SPS) Firmware 04.01.05.201.

Details about reported security vulnerabilities and their mitigation can be found at the following link [Security Bulletin Library | HPE Support](#).

Deliverable Name:

HPE ProLiant ML110 Gen10 System ROM - U33

Release Version:

3.66_04-01-2026

Last Recommended or Critical Revision:

3.64_02-05-2026

Previous Revision:

3.64_02-05-2026

Firmware Dependencies:

None

Enhancements/New Features:

Updated HPE branding logos across all boot screens (early POST, late POST, System Utility, and BGRT) to reflect the new HPE corporate identity.

Enabled "BIOS log to AHS every boot" by default after a ROM update; users can disable via RBSU.

Problems Fixed:

None

Known Issues:

None

Enhancements**Important Notes:**

This version of the System ROM should be paired with Server Platform Services (SPS) Firmware 04.01.05.201.

Details about reported security vulnerabilities and their mitigation can be found at the following link [Security Bulletin Library | HPE Support](#).

Firmware Dependencies:

None

Enhancements/New Features:

Updated HPE branding logos across all boot screens (early POST, late POST, System Utility, and BGRT) to reflect the new HPE corporate identity.

Enabled "BIOS log to AHS every boot" by default after a ROM update; users can disable via RBSU.

Known Issues:

None

ROM Flash Firmware Package - HPE ProLiant ML30 Gen10 (U44) Servers

Version: 3.76_05-28-2026 (**Optional**)

Filename: U44_3.76_05_28_2026.fwpkg

Important Note!**Important Notes:**

This version of the System ROM should be paired with Server Platform Services (SPS) Firmware 05.01.05.103.

Details about reported security vulnerabilities and their mitigation can be found at the following link [Security Bulletin Library | HPE Support](#).

Deliverable Name:

HPE ProLiant ML30 Gen10 System ROM - U44

Release Version:

3.76_05-28-2026

Last Recommended or Critical Revision:

3.74_04-01-2026

Previous Revision:

3.74_04-01-2026

Firmware Dependencies:

None

Enhancements/New Features:

Improved BIOS debug log diagnostics by including POST code events, boot target OS information, and RTC timestamps for enhanced triage support.

Enabled medium-level debug message logging for shared memory and CHIF methods, aligning Gen10 Active Health System (AHS) log collection with Gen10 Plus and later platforms.

Problems Fixed:

Resolved a security vulnerability where a NULL pointer dereference could cause a system crash during boot if an internal memory allocation failed during the ExitBootServices or boot option launch sequence.

Addressed an issue where the Minimum Processor Idle Power Core C-State and Minimum Processor Idle Power Package C-State options were not appearing in System Configuration (RBSU) under Power and Performance Options on ML30 Gen10 and DL20 Gen10 platforms.

Known Issues:

None

Fixes

Important Notes:

This version of the System ROM should be paired with Server Platform Services (SPS) Firmware 05.01.05.103.

Details about reported security vulnerabilities and their mitigation can be found at the following link [Security Bulletin Library | HPE Support](#).

Firmware Dependencies:

None

Problems Fixed:

Resolved a security vulnerability where a NULL pointer dereference could cause a system crash during boot if an internal memory allocation failed during the ExitBootServices or boot option launch sequence.

Addressed an issue where the Minimum Processor Idle Power Core C-State and Minimum Processor Idle Power Package C-State options were not appearing in System Configuration (RBSU) under Power and Performance Options on ML30 Gen10 and DL20 Gen10 platforms.

Known Issues:

None

Enhancements

Improved BIOS debug log diagnostics by including POST code events, boot target OS information, and RTC timestamps for enhanced triage support.

Enabled medium-level debug message logging for shared memory and CHIF methods, aligning Gen10 Active Health System (AHS) log collection with Gen10 Plus and later platforms.

ROM Flash Firmware Package - HPE ProLiant ML30 Gen10 Plus Servers

Version: 2.64_04-01-2026 (**Recommended**)

Filename: U61_2.64_04_01_2026.fwpkg

Important Note!

Important Notes:

None

Details about reported security vulnerabilities and their mitigation can be found at the following link [Security Bulletin Library | HPE Support](#).

Deliverable Name:

HPE ProLiant ML30 Gen10 Plus System ROM - U61

Release Version:

2.64_04-01-2026

Last Recommended or Critical Revision:

2.62_03-05-2026

Previous Revision:

2.62_03-05-2026

Firmware Dependencies:

None

Enhancements/New Features:

Updated HPE branding logos across all boot screens (early POST, late POST, System Utility, and BGRT) to reflect the new HPE corporate identity.

Added multi-language translation support for Chinese and Japanese in RBSU setup menus.

Problems Fixed:

Addressed an issue where ESKM (Enterprise Secure Key Manager) server keys could be generated with invalid bytes, potentially causing Self-Encrypting Drive (SED) unlock failures. Keys are now validated upon generation and corrected during drive unlock operations if previously affected.

Known Issues:

None

Fixes

Important Notes:

None

Details about reported security vulnerabilities and their mitigation can be found at the following link [Security Bulletin Library | HPE Support](#).

Firmware Dependencies:

None

Problems Fixed:

Addressed an issue where ESKM (Enterprise Secure Key Manager) server keys could be generated with invalid bytes, potentially causing Self-Encrypting Drive (SED) unlock failures. Keys are now validated upon generation and corrected during drive unlock operations if previously affected.

Known Issues:

None

Enhancements

Updated HPE branding logos across all boot screens (early POST, late POST, System Utility, and BGRT) to reflect the new HPE corporate identity.

Added multi-language translation support for Chinese and Japanese in RBSU setup menus.

ROM Flash Firmware Package - HPE ProLiant ML350 Gen10 (U41) Servers

Version: 3.66_04-01-2026 (**Optional**)

Filename: U41_3.66_04_01_2026.fwpkg

Important Note!

Important Notes:

This version of the System ROM should be paired with Server Platform Services (SPS) Firmware 04.01.05.201.

Details about reported security vulnerabilities and their mitigation can be found at the following link [Security Bulletin Library | HPE Support](#).

Deliverable Name:

HPE ProLiant ML350 Gen10 System ROM - U41

Release Version:

3.66_04-01-2026

Last Recommended or Critical Revision:

3.64_02-05-2026

Previous Revision:

3.64_02-05-2026

Firmware Dependencies:

None

Enhancements/New Features:

Updated HPE branding logos across all boot screens (early POST, late POST, System Utility, and BGRT) to reflect the new HPE corporate identity.

Enabled "BIOS log to AHS every boot" by default after a ROM update; users can disable via RBSU.

Problems Fixed:

None

Known Issues:

None

Enhancements

Important Notes:

This version of the System ROM should be paired with Server Platform Services (SPS) Firmware 04.01.05.201.

Details about reported security vulnerabilities and their mitigation can be found at the following link [Security Bulletin Library | HPE Support](#).

Firmware Dependencies:

None

Enhancements/New Features:

Updated HPE branding logos across all boot screens (early POST, late POST, System Utility, and BGRT) to reflect the new HPE corporate identity.

Enabled "BIOS log to AHS every boot" by default after a ROM update; users can disable via RBSU.

Known Issues:

None

ROM Flash Universal Firmware Package - HPE ProLiant DL325/DL325 v2/DL345 Gen10 Plus (A43) Servers

Version: 4.04_04-02-2026 (**Recommended**)

Filename: A43_4.04_04_02_2026.fwpkg

Important Note!

Important Notes:

This revision of the System ROM includes AMD reference code MilanPI 1.0.0.J for AMD 3rd Generation EPYC processors. This revision of the System ROM includes AMD reference code RomePI 1.0.0.P for AMD 2nd Generation EPYC processors.

Details about reported security vulnerabilities and their mitigation can be found at the following link [Security Bulletin Library | HPE Support](#).

Deliverable Name:

HPE ProLiant DL325/DL325 v2/DL345 Gen10 Plus System ROM - A43

Release Version:

4.04_04-02-2026

Last Recommended or Critical Revision:

4.04_04-02-2026

Previous Revision:

4.02_03-05-2026

Firmware Dependencies:

None

Enhancements/New Features:

Updated HPE branding logos across all boot screens (early POST, late POST, System Utility GUI and text modes, and BGRT) to reflect the new HPE corporate identity. AMD ABL binaries updated to display the new logo in quiet mode.

Added multi-language support (Chinese and Japanese) for RBSU setup menus and System Utility.

Enabled "BIOS log to AHS every boot" by default after a ROM update; users can disable this setting through RBSU if desired. The setting is also re-enabled when loading system defaults.

Problems Fixed:

Addressed an issue where ESKM (Enterprise Secure Key Manager) server keys could be generated with invalid bytes, potentially causing Self-Encrypting Drive (SED) unlock failures. Keys are now validated upon generation and corrected during drive unlock operations if previously affected.

Known Issues:

None

Fixes

Important Notes:

This revision of the System ROM includes AMD reference code MilanPI 1.0.0.J for AMD 3rd Generation EPYC processors. This revision of the System ROM includes AMD reference code RomePI 1.0.0.P for AMD 2nd Generation EPYC processors.

Details about reported security vulnerabilities and their mitigation can be found at the following link [Security Bulletin Library | HPE Support](#).

Firmware Dependencies:

None

Problems Fixed:

Addressed an issue where ESKM (Enterprise Secure Key Manager) server keys could be generated with invalid bytes, potentially causing Self-Encrypting Drive (SED) unlock failures. Keys are now validated upon generation and corrected during drive unlock operations if previously affected.

Known Issues:

None

Enhancements

Updated HPE branding logos across all boot screens (early POST, late POST, System Utility GUI and text modes, and BGRT) to reflect the new HPE corporate identity. AMD ABL binaries updated to display the new logo in quiet mode.

Added multi-language support (Chinese and Japanese) for RBSU setup menus and System Utility.

Enabled "BIOS log to AHS every boot" by default after a ROM update; users can disable this setting through RBSU if desired. The setting is also re-enabled when loading system defaults.

ROM Flash Universal Firmware Package - HPE ProLiant DL360/DL380 Gen10 Plus (U46) Servers

Version: 2.64_04-01-2026 (**Optional**)

Filename: U46_2.64_04_01_2026.fwpkg

Important Note!

Important Notes:

This version of the System ROM should be paired with Server Platform Services (SPS) Firmware 04.04.04.925 (2.60_12_05_2025).

Details about reported security vulnerabilities and their mitigation can be found at the following link [Security Bulletin Library | HPE Support](#).

Deliverable Name:

HPE ProLiant DL360/DL380 Gen10 Plus System ROM - U46

Release Version:

2.64_04-01-2026

Last Recommended or Critical Revision:

2.62_03-05-2026

Previous Revision:

2.62_03-05-2026

Firmware Dependencies:

None

Enhancements/New Features:

Updated HPE branding logos across all boot screens (early POST, late POST, System Utility, and BGRT) to reflect the new HPE corporate identity.

Added multi-language translation support for Chinese and Japanese in RBSU setup menus and Factory Options.

Enabled BIOS log to AHS every boot by default after a ROM update. Users can disable this setting through RBSU if desired.

Problems Fixed:

Addressed an issue where ESKM (Enterprise Secure Key Manager) server keys could be generated with invalid bytes, potentially causing Self-Encrypting Drive (SED) unlock failures. Keys are now validated upon generation and corrected during drive unlock operations if previously affected.

Known Issues:

None

Fixes

Important Notes:

This version of the System ROM should be paired with Server Platform Services (SPS) Firmware 04.04.04.925 (2.60_12_05_2025).

Details about reported security vulnerabilities and their mitigation can be found at the following link [Security Bulletin Library | HPE Support](#).

Firmware Dependencies:

None

Problems Fixed:

Addressed an issue where ESKM (Enterprise Secure Key Manager) server keys could be generated with invalid bytes, potentially causing Self-Encrypting Drive (SED) unlock failures. Keys are now validated upon generation and corrected during drive unlock operations if previously affected.

Known Issues:

None

Enhancements

Updated HPE branding logos across all boot screens (early POST, late POST, System Utility, and BGRT) to reflect the new HPE corporate identity.

Added multi-language translation support for Chinese and Japanese in RBSU setup menus and Factory Options.

Enabled BIOS log to AHS every boot by default after a ROM update. Users can disable this setting through RBSU if desired.

ROM Flash Universal Firmware Package - HPE ProLiant DL365/DL385/DL385 v2 Gen10 Plus (A42) Servers

Version: 4.04_04-02-2026 (**Recommended**)

Filename: A42_4.04_04_02_2026.fwpkg

Important Note!

Important Notes:

This revision of the System ROM includes AMD reference code MilanPI 1.0.0.J for AMD 3rd Generation EPYC processors. This revision of the System ROM includes AMD reference code RomePI 1.0.0.P for AMD 2nd Generation EPYC processors.

Details about reported security vulnerabilities and their mitigation can be found at the following link [Security Bulletin Library | HPE Support](#).

Deliverable Name:

HPE System ROM - A42

Release Version:

4.04_04-02-2026

Last Recommended or Critical Revision:

4.04_04-02-2026

Previous Revision:

4.02_03-05-2026

Firmware Dependencies:

None

Enhancements/New Features:

Updated HPE branding logos across all boot screens (early POST, late POST, System Utility GUI and text modes, and BGRT) to reflect the new HPE corporate identity. AMD ABL binaries updated to display the new logo in quiet mode.

Added multi-language support (Chinese and Japanese) for RBSU setup menus and System Utility.

Enabled "BIOS log to AHS every boot" by default after a ROM update; users can disable this setting through RBSU if desired. The setting is also re-enabled when loading system defaults.

Problems Fixed:

Addressed an issue where ESKM (Enterprise Secure Key Manager) server keys could be generated with invalid bytes, potentially causing Self-Encrypting Drive (SED) unlock failures. Keys are now validated upon generation and corrected during drive unlock operations if previously affected.

Known Issues:

None

Fixes

Important Notes:

This revision of the System ROM includes AMD reference code MilanPI 1.0.0.J for AMD 3rd Generation EPYC processors. This revision of the System ROM includes AMD reference code RomePI 1.0.0.P for AMD 2nd Generation EPYC processors.

Details about reported security vulnerabilities and their mitigation can be found at the following link [Security Bulletin Library | HPE Support](#).

Firmware Dependencies:

None

Problems Fixed:

Addressed an issue where ESKM (Enterprise Secure Key Manager) server keys could be generated with invalid bytes, potentially causing Self-Encrypting Drive (SED) unlock failures. Keys are now validated upon generation and corrected during drive unlock operations if previously affected.

Known Issues:

None

Enhancements

Updated HPE branding logos across all boot screens (early POST, late POST, System Utility GUI and text modes, and BGRT) to reflect the new HPE corporate identity. AMD ABL binaries updated to display the new logo in quiet mode.

Added multi-language support (Chinese and Japanese) for RBSU setup menus and System Utility.

Enabled "BIOS log to AHS every boot" by default after a ROM update; users can disable this setting through RBSU if desired. The setting is also re-enabled when loading system defaults.

Driver - Lights-Out Management

[Top](#)

HPE iLO Native Driver for ESXi 8.0 and ESXi 9.0

Version: 10.9.1 (**Recommended**)

Filename: ilo-driver_800.10.9.1.4-10EM.800.1.0.20613240.zip

Fixes

Implement MSI interrupt in the ilo driver to fix PSOD due to interrupt storm and to fix snmpwalk delays.

Driver - Network

[Top](#)

HPE Broadcom NetXtreme-E Drivers for VMware vSphere 8.0

Version: 2026.05.00 (**Recommended**)

Filename: cp071478.compsig; cp071478.zip

Important Note!

- This component is intended to be used by HPE applications. It is a zip file that contains the same driver deliverable available from the vmware.com and the HPE vibsdepot.hpe.com webpages, plus an HPE specific CP0xxxxx.xml file.
- HPE recommends the *HPE Broadcom NetXtreme-E Firmware Version, 237.1.148000* or later, for use with this driver.

Fixes

- This product fixes the issue where RDMA resource configuration for VFs may be incorrectly handled when VF RDMA is disabled in BIOS.
- This product fixes the issue where the RoCE traffic priority may be incorrectly updated during RoCE connection handling.

Enhancements

- This product enhances the driver to report a warning in the kernel logs when the module temperature reaches the threshold.

Supported Devices and Features

This product supports the following network adapters:

- HPE Ethernet 10Gb 2-port 535FLR-T Adapter
- HPE Ethernet 10Gb 2-port 535T Adapter
- HPE Ethernet 10Gb 2-port 537SFP+ Adapter
- HPE Ethernet 10Gb 2-port 537SFP+ FLR Adapter
- HPE Ethernet 10/25Gb 2-port 631FLR-SFP28 Adapter
- HPE Ethernet 10/25Gb 2-port 631SFP28 Adapter
- HPE Ethernet 10Gb 2-port SFP+ BCM57412 OCP3 Adapter

- o HPE Ethernet 10Gb 2-port SFP+ BCM57412 Adapter
- o HPE Ethernet 10Gb 2-port BaseT BCM57416 OCP3 Adapter
- o HPE Ethernet 10Gb 2-port BaseT BCM57416 Adapter
- o HPE Ethernet 10/25Gb 2-port SFP28 BCM57414 OCP3 Adapter
- o HPE Ethernet 10/25Gb 2-port SFP28 BCM57414 Adapter
- o Broadcom BCM57504 Ethernet 10/25Gb 4-port SFP28 Adapter for HPE
- o Broadcom BCM57504 Ethernet 10/25Gb 4-port SFP28 OCP3 Adapter for HPE
- o Broadcom BCM57608 Ethernet 100Gb 2-port QSFP112 Adapter for HPE
- o Broadcom BCM57608 Ethernet 100Gb 2-port QSFP112 OCP3 Adapter for HPE

HPE Intel i40en Driver for VMware vSphere 8.0

Version: 2025.11.00 **(Recommended)**

Filename: cp068940.compsig; cp068940.zip

Important Note!

This component is intended to be used by HPE applications. It is a zip file that contains the same driver deliverable available from the vmware.com and the HPE vibsddepot.hpe.com webpages, plus an HPE specific CP0xxxxx.xml file.

HPE recommends the firmware provided in *HPE Intel Online Firmware Upgrade Utility for VMware*, version 3.25.0 or later, for use with this driver.

Enhancements

- o This product added Requested FEC display in vmkernel.log.
- o This product added info message in vmkernel.log.

Supported Devices and Features

This product supports the following network adapters:

- o HPE Ethernet 1Gb 2-port 368FLR-MMT Adapter
- o HPE Ethernet 1Gb 2-port 368i Adapter
- o HPE Ethernet 1Gb 4-port 369i Adapter
- o HPE Ethernet 10Gb 2-port 562FLR-SFP+ Adapter
- o HPE Ethernet 10Gb 2-port 562SFP+ Adapter
- o HPE Ethernet 10Gb 2-port 563i Adapter
- o HPE Ethernet 10Gb 2-port 568FLR-MMSFP+ Adapter
- o HPE Ethernet 10Gb 2-port 568FLR-MMT Adapter
- o HPE Ethernet 10Gb 2-port 568i Adapter
- o HPE Ethernet 10Gb 2-port SFP+ OCP3 X710-DA2 Adapter
- o HPE Ethernet 10Gb 2-port SFP+ X710-DA2 Adapter

HPE Intel igbn Driver for VMware vSphere 8.0

Version: 2025.05.00 **(Recommended)**

Filename: cp066052.compsig; cp066052.zip

Important Note!

This component is intended to be used by HPE applications. It is a zip file that contains the same driver deliverable available from the vmware.com and the HPE vibsddepot.hpe.com webpages, plus an HPE specific CP0xxxxx.xml file.

HPE recommends the firmware provided in *HPE Intel Online Firmware Upgrade Utility for VMware*, version 3.26.1 or later, for use with this driver.

Enhancements

This product enhanced the compatibility with firmware.

Supported Devices and Features

These drivers support the following network adapters:

- o HPE Ethernet 1Gb 2-port 361T Adapter
- o HPE Ethernet 1Gb 2-port 361i Adapter
- o HPE Ethernet 1Gb 2-port 363i Adapter
- o HPE Ethernet 1Gb 4-port 366FLR Adapter
- o HPE Ethernet 1Gb 4-port 366T Adapter
- o HPE Ethernet 1Gb 4-port 366i Adapter
- o HPE Ethernet 1Gb 4-port 366i Communication Board
- o Intel I350-T4 Ethernet 1Gb 4-port BASE-T Adapter for HPE
- o Intel I350-T4 Ethernet 1Gb 4-port BASE-T OCP3 Adapter for HPE
- o Intel(R) I350 Gigabit Network Connection

HPE Intel ixgben Driver for VMware vSphere 8.0

Version: 2026.03.00 **(Recommended)**

Filename: cp070243.compsig; cp070243.zip

Important Note!

This component is intended to be used by HPE applications. It is a zip file that contains the same driver deliverable available from the vmware.com and the HPE vibsddepot.hpe.com webpages, plus an HPE specific CP0xxxxx.xml file.

- o HPE recommends the firmware provided in *HPE Intel Online Firmware Upgrade Utility for VMware*, version 3.27.0 or later, for use with this driver.
- o HPE recommends the firmware provided in *Intel Firmware Package For E610-IT4 Ethernet 1Gb 4-port BASE-T OCP3 Adapter*, version 1.22 or later, for use with this driver

Fixes

- o This product fixed warning logs generated during driver unload.
- o This product fixed PF reset reporting to VF.
- o This product fixed auto-advertised speeds for E610 adapters.

Supported Devices and Features

These drivers support the following network adapters:

- o HPE Ethernet 10Gb 2-port 560SFP+ Adapter
- o HPE Ethernet 10Gb 2-port 560FLR-SFP+ Adapter
- o HPE Ethernet 10Gb 2-port 561T Adapter
- o HPE Ethernet 10Gb 2-port 561FLR-T Adapter
- o HPE Ethernet 10Gb 2-port 562T Adapter
- o HPE Ethernet 10Gb 2-port 562FLR-T Adapter
- o Intel E610-IT4 Ethernet 1Gb 4-port BASE-T OCP3 Adapter for HPE

HPE QLogic FastLinQ 10/25/50 GbE Multifunction Driver for VMware vSphere 8.0

Version: 2026.03.00 **(Recommended)**

Filename: cp070110.compsig; cp070110.zip

Important Note!

This component is intended to be used by HPE applications. It is a zip file that contains the same driver deliverable available from the vmware.com and the HPE vibstdepot.hpe.com webpages, plus an HPE specific CP0xxxxx.xml file.

HPE recommends the firmware provided as below for use with these drivers,

- o HPE QLogic FastLinQ Firmware Package for Arrowhead adapters, version 8.65.23 or later.
- o HPE QLogic FastLinQ Online Firmware Upgrade Utility for VMware, version 4.20.0 or later.

Fixes

- o This product fixed an issue where it misses RX byte statistics for LRO queues in ENS mode

Enhancements

- o This product now enabled DRSS by default for non-ENS mode to improve RX traffic distribution and reduce latency between hosts and federated sites.

Supported Devices and Features

This product supports the following network adapters:

- o HPE Ethernet 10Gb 2-port 521T Adapter
- o HPE Ethernet 10Gb 2-port 524SFP+ Adapter
- o HPE Ethernet 10/25Gb 2-port 621SFP28 Adapter
- o HPE Ethernet 10/25Gb 2-port 622FLR-SFP28 Converged Network Adapter
- o HPE StoreFabric CN1200R-T Converged Network Adapter
- o HPE StoreFabric CN1300R Converged Network Adapter
- o HPE Ethernet 10/25Gb 2-port SFP28 QL41232HVCU OCP3 Adapter
- o HPE Ethernet 10/25Gb 2-port SFP28 QL41232HLCU Adapter
- o HPE Ethernet 10Gb 4-port SFP+ QL41134HLCU Adapter
- o HPE Ethernet 10Gb 2-port BaseT QL41132HLRJ Adapter
- o HPE Ethernet 10Gb 2-port BaseT QL41132HQRJ OCP3 Adapter
- o HPE Ethernet 10Gb 2-port SFP+ QL41132HVCU OCP3 Adapter
- o HPE Ethernet 10Gb 2-port SFP+ QL41132HLCU Adapter

HPE QLogic NX2 10/20 GbE Multifunction Driver for VMware vSphere 8.0

Version: 2025.03.00 **(Recommended)**

Filename: cp064345.compsig; cp064345.zip

Important Note!

This component is intended to be used by HPE applications. It is a zip file that contains the same driver deliverable available from the vmware.com and the HPE vibstdepot.hpe.com webpages, plus an HPE specific CP0xxxxx.xml file.

HPE recommends the firmware provided in *HPE QLogic NX2 Online Firmware Upgrade Utility for VMware*, version 1.37.0 or later, for use with this driver.

Fixes

- o This product corrects an issue which fix TSO (TCP Segmentation Offload) issue when single segment is larger than pkt length.
- o This product corrects an issue which PSOD while freeing DMA during 'esxcli qlfastlinq qcc' command execution.

Supported Devices and Features

These drivers support the following network adapters:

- o HPE Ethernet 10Gb 2-port 530T Adapter
- o HPE Ethernet 10Gb 2-port 530SFP+ Adapter
- o HPE FlexFabric 10Gb 2-port 533FLR-T Adapter
- o HPE FlexFabric 10Gb 2-port 534FLR-SFP+ Adapter
- o HPE FlexFabric 10Gb 4-port 536FLR-T Adapter

Intel icen Driver for VMware vSphere 8.0

Version: 2026.03.00 **(Recommended)**

Filename: cp068814.compsig; cp068814.zip

Important Note!

- o This component is intended to be used by HPE applications. It is a zip file that contains the same driver deliverable available from the vmware.com and the HPE vibsddepot.hpe.com webpages, plus an HPE specific CP0xxxxx.xml file.
- o HPE recommends the firmware provided in *Intel Firmware Package For E810 Ethernet Adapter*, version 4.71 or later, for use with these drivers.

Fixes

- o This product fixed RDMA configuration cleanup during transitions between Native and ENS modes, as well as state changes.
- o This product removed warning messages during driver unload by improving cleanup of TX scheduler configuration.
- o This product fixed VLAN list cleanup during VF reset, ensuring VLAN properties can be configured correctly by the OS.

Supported Devices and Features

This product supports the following network adapters:

- o Intel E810-CQDA2 Ethernet 100Gb 2-port QSFP28 Adapter for HPE
- o Intel E810-CQDA2 Ethernet 100Gb 2-port QSFP28 OCP3 Adapter for HPE
- o Intel E810-XXVDA4 Ethernet 10/25Gb 4-port SFP28 Adapter for HPE
- o Intel E810-XXVDA2 Ethernet 10/25Gb 2-port SFP28 Adapter for HPE
- o Intel E810-XXVDA2 Ethernet 10/25Gb 2-port SFP28 OCP3 Adapter for HPE
- o Intel E810-2CQDA2 Ethernet 100Gb 2-port QSFP28 Adapter for HPE
- o Intel E810-XXVDA4 Ethernet 10/25Gb 4-port SFP28 OCP3 Adapter for HPE

net-mst kernel module driver component for VMware ESXi 8.0 Update 3

Version: 2025.03.17 **(Recommended)**

Filename: cp052054.compsig; cp052054.zip

Important Note!

This component is intended to be used by HPE applications. It is a zip that contains the same driver deliverable available from the HPE vibsddepot.hpe.com webpage, plus an HPE specific CPXXXX.xml file.

Prerequisites

NA

Enhancements

NMST version 4.31.0.150

This version is supported on VMware ESXi 8.0 Update 3 only.

Supported Devices and Features

HPE Part Number	Device Name	PSID
764282-B21	HPE InfiniBand QDR/Ethernet 10Gb 2-port 544+M Adapter	HP_1350110023
764283-B21	HPE InfiniBand FDR/Ethernet 10Gb/40Gb 2-port 544+M Adapter	HP_1360110017
764284-B21	HPE InfiniBand FDR/Ethernet 10Gb/40Gb 2-port 544+QSFP Adapter	HP_1370110017
P24837-B21	HPE Ethernet 10/25Gb 2-port 642SFP28 Adapter	HPE0000000054
P11338-B21	HPE Ethernet 10Gb 2-port 548SFP+ Adapter	HP_1200111023
764285-B21	HPE InfiniBand FDR/Ethernet 10Gb/40Gb 2-port 544+FLR-QSFP Adapter	HP_1380110017
764286-B21	HPE InfiniBand QDR/Ethernet 10Gb 2-port 544+FLR-QSFP Adapter	HP_1390110023
825110-B21	HPE InfiniBand EDR/Ethernet 100Gb 1-port 840QSFP28 Adapter	HP_2180110032
825111-B21	HPE InfiniBand EDR/Ethernet 100Gb 2-port 840QSFP28 Adapter	HP_2190110032
872726-B21	HPE InfiniBand EDR/Ethernet 100Gb 2-port 841QSFP28 Adapter	HPE0000000009
879482-B21	HPE InfiniBand FDR/Ethernet 40/50Gb 2-port 547FLR-QSFP Adapter	HPE0000000022
868779-B21	HPE Synergy 6410C 25/50Gb Ethernet Adapter	HPE0000000006
779793-B21	HPE Ethernet 10Gb 2-port 546SFP+ Adapter	HP_1200111023
779799-B21	HPE Ethernet 10Gb 2-port 546FLR-SFP+ Adapter	HP_2240110004
817749-B21	HPE Ethernet 25Gb 2-port 640FLR-SFP28 Adapter	HP_2690110034
817753-B21	HPE Ethernet 25Gb 2-port 640SFP28 Adapter	HP_2420110034
P21927-B21	HPE Ethernet 100Gb 2-port QSFP28 MCX516A-CCHT Adapter	MT_00000000417
P10112-B21	HPE Ethernet 10/25Gb 2-port SFP28 MCX562A-ACAI OCP3 Adapter	MT_00000000241
P13188-B21	HPE Ethernet 10/25Gb 2-port SFP28 MCX512F-ACHT Adapter	MT_00000000416
P11341-B21	HPE Ethernet 10Gb 2-port SFP+ MCX4621A-ACAB OCP3 Adapter	MT_00000000238
P21930-B21	HPE Ethernet 10Gb 2-port SFP+ MCX4121A-XCHT Adapter	MT_00000000414
874253-B21	HPE Ethernet 100Gb 1-port 842QSFP28 Adapter	HPE0000000014
P25960-B21	HPE Ethernet 100Gb 2-Port QSFP56 MCX623106AS-CDAT Adapter	MT_00000000437
P06154-B21	HPE InfiniBand HDR/Ethernet 200Gb 1-port 940QSFP56 x16 Adapter	HPE00000000034
P06250-B21	HPE InfiniBand HDR100/Ethernet 100Gb 1-port 940QSFP56 x16 Adapter	HPE00000000035
P06251-B21	HPE InfiniBand HDR100/Ethernet 100Gb 2-port 940QSFP56 x16 Adapter	HPE00000000036
P23664-B21	HPE InfiniBand HDR/Ethernet 200Gb 1-port MCX653105A-HDAT QSFP56 x16 Adapter	MT_00000000451
P23665-B21	HPE InfiniBand HDR100/Ethernet 100Gb 1-port MCX653105A-ECAT QSFP56 x16 Adapter	MT_00000000452
P23666-B21	HPE InfiniBand HDR100/Ethernet 100Gb 2-port MCX653106A-ECAT QSFP56 x16 Adapter	MT_00000000453

P10180-B21	Mellanox MCX623105AS-VDAT Ethernet 200Gb 1-port QSFP56 Adapter for HPE	MT_0000000435
P31246-B21	HPE Ethernet 100Gb 1-port QSFP28 PCIe3 x16 MCX515A-CCAT Adapter	MT_0000000591
P31323-B21	HPE InfiniBand HDR/Ethernet 200Gb 1-port QSFP56 PCIe4 x16 OCP3 MCX653435A-HDAI Adapter	MT_0000000592
P31348-B21	HPE InfiniBand HDR/Ethernet 200Gb 2-port QSFP56 PCIe4 x16 OCP3 MCX653436A-HDAI Adapter	MT_0000000593
P31324-B21	HPE InfiniBand HDR/Ethernet 200Gb 2-port QSFP56 PCIe4 x16 MCX653106A-HDAT Adapter	MT_0000000594
P42041-B21	Mellanox MCX631432AS-ADAI Ethernet 10/25Gb 2-port SFP28 OCP3 Adapter for HPE	MT_0000000551
P42044-B21	Mellanox MCX631102AS-ADAT Ethernet 10/25Gb 2-port SFP28 Adapter for HPE	MT_0000000575

Driver - Storage Controller

[Top](#)

HPE MR416i-p, MR216i-a, MR216i-a Gen10 plus Controllers and MR416i-p, MR416i-o, MR216i-o, MR408i-o, MR216i-p, MR408i-p Gen11 Controllers Driver (64-bit) for vSphere 8.0

Version: 2026.03.01 **(Recommended)**

Filename: cp068884.compsig; cp068884.zip

Important Note!

- o Actual Version is 7.736.02.00

Fixes

- o Fix an issue that driver unload will fail if there is any management command is outstanding

HPE ProLiant Gen10 Smart Array and Gen10 Plus and Gen11 Smart RAID Controller Driver for VMware vSphere 8.0 (Driver Component).

Version: 2026.07.01 **(Recommended)**

Filename: cp071895.compsig; cp071895.zip

Important Note!

- o Actual ESXi8.0 driver version is 80.4902.0.103
- o Actual ESXi9.0 driver version is 90.4902.0.103
- o HPE Service Pack for ProLiant (SPP) provides a fully qualified recipe for specific firmware and drivers released within the same cycle, making it the primary recommended choice.
- o It is strongly recommended to use controller firmware version 8.23 for SR SAS/SATA controllers and firmware version 03.01.47.052 for SR tri-mode controllers, along with Windows 2022/2025 driver version 1016.38.0.1003, Linux driver version 2.1.40-020, and VMware ESXi driver version 80.4902.0.103/90.4902.0.103, as this combination has been fully qualified.
- o For Windows 2016 driver, please use 1010.84.0.1012 in below link: <https://www.hpe.com/global/swpublishing/MTX-c523e081ab344bc4b4bc9d5686>
- o For Windows 2019 driver, please use 1016.10.0.1004 in below link: <https://www.hpe.com/global/swpublishing/MTX-29e86213c3ab4e94b0b54906f7>

Enhancements

- o New release.

Firmware - Management

[Top](#)

ROM Flash Universal Firmware Package - HPE Edgeline Chassis Controller Firmware

Version: 2.1.0 **(Recommended)**

Filename: ACCE_2.1.0s.fwpkg

Fixes

Addressed an issue where the main power status could appear inconsistent in certain situations, resulting in more reliable and accurate status reporting.

Firmware - Network

[Top](#)

Broadcom Firmware Package for BCM57412 adapter

Version: 237.1.148.0 **(Recommended)**

Filename: BCM237.1.148.0_BCM957412A4121HC.fwpkg; BCM237.1.148.0_BCM957412A4121HC.json

Important Note!

For Firmware installation, there is no OS and drivers dependency.

For Firmware compatibility during production, HPE recommends the drivers for use with the firmware Package product as below,

- o Broadcom NetXtreme-E Driver for Microsoft Windows Server, version 237.1.124.0 or later
- o HPE Broadcom NetXtreme-E Drivers for Linux, version 1.10.3-237.1.137.0 or later
- o HPE Broadcom NetXtreme-E Drivers for VMware, version 2026.05.00 or later

Fixes

- o This product fixes the issue where the PXE boot failure due to missing link flap on warm reboot
- o This product fixes the issue where the Firmware timeout errors seen when reloading driver.
- o This product fixes the issue where brcm-niccli show ""Link Down"" even though link is up
- o This product fixes the issue where NC-SI over MCTP fails after BMC sends concurrent commands.
- o This product fixes the issue where Linux: Link down reason is not populated in Linux dmesg.

Supported Devices and Features

This product supports the following network adapters:

- o HPE Ethernet 10Gb 2-port SFP+ BCM57412 Adapter

Broadcom Firmware Package for BCM57412 OCP3 adapter
Version: 237.1.148.0 (**Recommended**)
Filename: BCM237.1.148.0_BCM957412N4120HC.fwpkg; BCM237.1.148.0_BCM957412N4120HC.json

Important Note!

For Firmware installation, there is no OS and drivers dependency.
For Firmware compatibility during production, HPE recommends the drivers for use with the firmware Package product as below,

- o Broadcom NetXtreme-E Driver for Microsoft Windows Server, version 237.1.124.0 or later
- o HPE Broadcom NetXtreme-E Drivers for Linux, version 1.10.3-237.1.137.0 or later
- o HPE Broadcom NetXtreme-E Drivers for VMware, version 2026.05.00 or later

Fixes

- o This product fixes the issue where the PXE boot failure due to missing link flap on warm reboot
- o This product fixes the issue where the Firmware timeout errors seen when reloading driver.
- o This product fixes the issue where brcm-niccli show ""Link Down"" even though link is up
- o This product fixes the issue where NC-SI over MCTP fails after BMC sends concurrent commands.
- o This product fixes the issue where Linux: Link down reason is not populated in Linux dmesg.

Supported Devices and Features

This product supports the following network adapters:

- o HPE Ethernet 10Gb 2-port SFP+ BCM57412 OCP3 Adapter

Broadcom Firmware Package for BCM57414 adapter
Version: 237.1.148.0 (**Recommended**)
Filename: BCM237.1.148.0_BCM957414A4142HC.fwpkg; BCM237.1.148.0_BCM957414A4142HC.json

Important Note!

For Firmware installation, there is no OS and drivers dependency.
For Firmware compatibility during production, HPE recommends the drivers for use with the firmware Package product as below,

- o Broadcom NetXtreme-E Driver for Microsoft Windows Server, version 237.1.124.0 or later
- o HPE Broadcom NetXtreme-E Drivers for Linux, version 1.10.3-237.1.137.0 or later
- o HPE Broadcom NetXtreme-E Drivers for VMware, version 2026.05.00 or later

Fixes

- o This product fixes the issue where the PXE boot failure due to missing link flap on warm reboot
- o This product fixes the issue where the Firmware timeout errors seen when reloading driver.
- o This product fixes the issue where brcm-niccli show ""Link Down"" even though link is up
- o This product fixes the issue where NC-SI over MCTP fails after BMC sends concurrent commands.
- o This product fixes the issue where Linux: Link down reason is not populated in Linux dmesg.

Supported Devices and Features

This product supports the following network adapters:

- o HPE Ethernet 10/25Gb 2-port SFP28 BCM57414 Adapter

Broadcom Firmware Package for BCM57414 OCP3 adapter
Version: 237.1.148.0 (**Recommended**)
Filename: BCM237.1.148.0_BCM957414N4140HC.fwpkg; BCM237.1.148.0_BCM957414N4140HC.json

Important Note!

For Firmware installation, there is no OS and drivers dependency.
For Firmware compatibility during production, HPE recommends the drivers for use with the firmware Package product as below,

- o Broadcom NetXtreme-E Driver for Microsoft Windows Server, version 237.1.124.0 or later
- o HPE Broadcom NetXtreme-E Drivers for Linux, version 1.10.3-237.1.137.0 or later
- o HPE Broadcom NetXtreme-E Drivers for VMware, version 2026.05.00 or later

Fixes

- o This product fixes the issue where the PXE boot failure due to missing link flap on warm reboot
- o This product fixes the issue where the Firmware timeout errors seen when reloading driver.
- o This product fixes the issue where brcm-niccli show ""Link Down"" even though link is up
- o This product fixes the issue where NC-SI over MCTP fails after BMC sends concurrent commands.
- o This product fixes the issue where Linux: Link down reason is not populated in Linux dmesg.

Supported Devices and Features

This product supports the following network adapter:

- o HPE Ethernet 10/25Gb 2-port SFP28 BCM57414 OCP3 Adapter

Broadcom Firmware Package for BCM57416 adapter
Version: 237.1.148.0 (**Recommended**)
Filename: BCM237.1.148.0_BCM957416A4162HC.fwpkg; BCM237.1.148.0_BCM957416A4162HC.json

Important Note!

For Firmware installation, there is no OS and drivers dependency.

For Firmware compatibility during production, HPE recommends the drivers for use with the firmware Package product as below,

- o Broadcom NetXtreme-E Driver for Microsoft Windows Server, version 237.1.124.0 or later
- o HPE Broadcom NetXtreme-E Drivers for Linux, version 1.10.3-237.1.137.0 or later
- o HPE Broadcom NetXtreme-E Drivers for VMware, version 2026.05.00 or later

Fixes

- o This product fixes the issue where the PXE boot failure due to missing link flap on warm reboot
- o This product fixes the issue where the Firmware timeout errors seen when reloading driver.
- o This product fixes the issue where brcm-niccli show ""Link Down"" even though link is up
- o This product fixes the issue where NC-SI over MCTP fails after BMC sends concurrent commands.
- o This product fixes the issue where Linux: Link down reason is not populated in Linux dmesg.

Supported Devices and Features

This product supports the following network adapters:

- o HPE Ethernet 10Gb 2-port BaseT BCM57416 Adapter

Broadcom Firmware Package for BCM57416 OCP3 adapter

Version: 237.1.148.0 (**Recommended**)

Filename: BCM237.1.148.0_BCM957416N4160HC.fwpkg; BCM237.1.148.0_BCM957416N4160HC.json

Important Note!

For Firmware installation, there is no OS and drivers dependency.

For Firmware compatibility during production, HPE recommends the drivers for use with the firmware Package product as below,

- o Broadcom NetXtreme-E Driver for Microsoft Windows Server, version 237.1.124.0 or later
- o HPE Broadcom NetXtreme-E Drivers for Linux, version 1.10.3-237.1.137.0 or later
- o HPE Broadcom NetXtreme-E Drivers for VMware, version 2026.05.00 or later

Fixes

- o This product fixes the issue where the PXE boot failure due to missing link flap on warm reboot
- o This product fixes the issue where the Firmware timeout errors seen when reloading driver.
- o This product fixes the issue where brcm-niccli show ""Link Down"" even though link is up
- o This product fixes the issue where NC-SI over MCTP fails after BMC sends concurrent commands.
- o This product fixes the issue where Linux: Link down reason is not populated in Linux dmesg.

Supported Devices and Features

This product supports the following network adapters:

- o HPE Ethernet 10Gb 2-port BaseT BCM57416 OCP3 Adapter

Broadcom Firmware Package for BCM57504 Ethernet 10/25Gb 4-port SFP28 Adapter

Version: 237.1.148.0 (**Recommended**)

Filename: BCM237.1.148.0_BCM957504-P425H.fwpkg; BCM237.1.148.0_BCM957504-P425H.json

Important Note!

For Firmware installation, there is no OS and drivers dependency.

For Firmware compatibility during production, HPE recommends the drivers for use with the firmware Package product as below,

- o Broadcom NetXtreme-E Driver for Microsoft Windows Server, version 237.1.124.0 or later
- o HPE Broadcom NetXtreme-E Drivers for Linux, version 1.10.3-237.1.137.0 or later
- o HPE Broadcom NetXtreme-E Drivers for VMware, version 2026.05.00 or later

Fixes

- o This product fixes the issue where wrong port speed in MCTP VDM Get PCIe Adapter Attributes response
- o This product fixes the issue where NC-SI over MCTP fails after BMC sends concurrent commands
- o This product fixes the issue where wrong temperature thresholds are reported for QSFP28 transceiver LTA8531
- o This product fixes the issue where PLDM Firmware Update error handling
- o This product fixes the issue where NC-SI Clear Initial State command can result in buffers being freed incorrectly.
- o This product fixes the issue where the power level setting for QSFP, QSFP+, and QSFP28 optical modules.
- o This product fixes the issue where link flap during BMC initiated host power cycle

Enhancements

- o This product enhancement to adds RDE support for SRIOVEnabled and VirtualFunctionAllocation

Supported Devices and Features

This product supports the following network adapters:

- o Broadcom BCM57504 Ethernet 10/25Gb 4-port SFP28 Adapter for HPE

Broadcom Firmware Package for BCM57504 Ethernet 10/25Gb 4-port SFP28 OCP3 Adapter

Important Note!

For Firmware installation, there is no OS and drivers dependency.
For Firmware compatibility during production, HPE recommends the drivers for use with the firmware Package product as below,

- o Broadcom NetXtreme-E Driver for Microsoft Windows Server, version 237.1.124.0 or later
- o HPE Broadcom NetXtreme-E Drivers for Linux, version 1.10.3-237.1.137.0 or later
- o HPE Broadcom NetXtreme-E Drivers for VMware, version 2026.05.00 or later

Fixes

- o This product fixes the issue where wrong port speed in MCTP VDM Get PCIe Adapter Attributes response
- o This product fixes the issue where NC-SI over MCTP fails after BMC sends concurrent commands
- o This product fixes the issue where wrong temperature thresholds are reported for QSFP28 transceiver LTA8531
- o This product fixes the issue where PLDM Firmware Update error handling
- o This product fixes the issue where NC-SI Clear Initial State command can result in buffers being freed incorrectly.
- o This product fixes the issue where the power level setting for QSFP, QSFP+, and QSFP28 optical modules.
- o This product fixes the issue where link flap during BMC initiated host power cycle

Enhancements

- o This product enhancement to adds RDE support for SRIOVEnabled and VirtualFunctionAllocation

Supported Devices and Features

This product supports the following network adapters:

- o Broadcom BCM57504 Ethernet 10/25Gb 4-port SFP28 OCP3 Adapter for HPE

Important Note!

This software package contains combo image v20.37.41 with the following firmware versions:

NIC	Boot Code Version	PXE Version	NCSI Version	UEFI Version
BCM 5719 1GbE 4p BASE-T Adptr	1.64	21.6.4	1.5.71	21.6.97
BCM 5719 1GbE 4p BASE-T OCP3 Adptr	1.64	21.6.4	1.5.71	21.6.97
BCM 5719 1GbE 4p BASE-T LOM Adptr	1.64	21.6.4	1.5.71	21.6.97
BCM 5720 1GbE 2p BASE-T LOM Adptr	1.43	21.6.4	1.5.71	21.6.97

Prerequisites

This product requires the appropriate driver for your device and operating system to be installed before the firmware is updated.

Fixes

- o This product fixes the issue where BMC ping may fail after host network interfaces are added, removed, or reconfigured.

Supported Devices and Features

This product supports the following network adapters:

- o Broadcom BCM5720 Ethernet 1Gb 2-port BASE-T LOM Adapter for HPE
- o Broadcom BCM5719 Ethernet 1Gb 4-port Base-T Adapter for HPE
- o Broadcom BCM5719 Ethernet 1Gb 4-port Base-T OCP3 Adapter for HPE
- o Broadcom BCM5719 Ethernet 1Gb 4-port Base-T LOM Adapter for HPE

Important Note!

HPE recommends *HPE Broadcom NetXtreme-E Drivers for VMware*, versions 2023.09.00 or later, for use with this firmware.

This software package contains NVM Image version 226.1.107000 with the following firmware versions:

NIC	Bootcode Version	NCSI Version	MBA Version	UEFI Version	RoCE Version
HPE Ethernet 10Gb 2-port 535FLR-T Adapter	226.0.145.0	226.0.145.0	226.0.135.0	226.0.135.0	226.0.145.0
HPE Ethernet 10Gb 2-port 535T Adapter					
HPE Ethernet 10/25Gb 2-port 631FLR-SFP28 Adapter					

HPE Ethernet 10/25Gb 2-port 631SFP28 Adapter					
HPE Ethernet 10Gb 2-port 537SFP+ Adapter					
HPE Ethernet 10Gb 2-port 537SFP+ FLR Adapter					

Prerequisites

This product requires the appropriate driver for your device and operating system be installed before firmware is updated.

Fixes

- o This product addressed the NC-SI passthrough algorithm for some FRU-reading commands from platform side.
- o This product addressed the packet forwarding rule while receiving packet which is bigger than 9600 jumbo size.
- o This product addressed the link failure under FreeBSD OS after changing link speed.
- o This product addressed the failure of bringing up VFs of SRIOV when doing on and off switch.
- o This product addressed adapter not responsive when work under heavy loading with 128 VMs.
- o The product addressed status reporting of PLDM sensor monitoring with BMC.
- o This product addressed the link-flap after link down or warm boot.

Enhancements

Added ESXi 9.1 Supported Environment

Supported Devices and Features

This product supports the following network adapters:

- o HPE Ethernet 10Gb 2-port 535FLR-T Adapter
- o HPE Ethernet 10Gb 2-port 535T Adapter
- o HPE Ethernet 10/25Gb 2-port 631FLR-SFP28 Adapter
- o HPE Ethernet 10/25Gb 2-port 631SFP28 Adapter
- o HPE Ethernet 10Gb 2-port 537SFP+ Adapter
- o HPE Ethernet 10Gb 2-port 537SFP+ FLR Adapter

HPE Broadcom NetXtreme-E Online Firmware Upgrade Utility for VMware
Version: 226.1.107.0 (C) **(Recommended)**
Filename: CP070641.compsig; CP070641.zip

Important Note!

HPE recommends *HPE Broadcom NetXtreme-E Drivers for VMware*, versions 2023.09.00 or later, for use with this firmware.

This software package contains NVM Image version 226.1.107000 with the following firmware versions:

NIC	Bootcode Version	NCSI Version	MBA Version	UEFI Version	RoCE Version
HPE Ethernet 10/25Gb 2-port SFP28 BCM57414 OCP3 Adapter	226.0.145.0	226.0.145.0	226.0.135.0	226.0.135.0	226.0.145.0
HPE Ethernet 10/25Gb 2-port SFP28 BCM57414 Adapter					
HPE Ethernet 10Gb 2-port BaseT BCM57416 OCP3 Adapter					
HPE Ethernet 10Gb 2-port BaseT BCM57416 Adapter					
HPE Ethernet 10Gb 2-port SFP+ BCM57412 OCP3 Adapter					
HPE Ethernet 10Gb 2-port SFP+ BCM57412 Adapter					
HPE Ethernet 10/25Gb 4-port SFP28 BCM57504 Adapter					
HPE Ethernet 10/25Gb 4-port SFP28 BCM57504 OCP3 Adapter					

Prerequisites

This product requires the appropriate driver for your device and operating system be installed before firmware is updated.

Fixes

- o This product addressed device lost symptom after continuously ungraceful restart on BCM57414 OCP3 adapter.
- o This product addressed some RDE pattern format for some LLDP properties.
- o This product addressed the NC-SI passthrough with BMC when device is under idle mode.
- o This product addressed new mechanism for loading factory default.

Enhancements

- o This product enhanced the device self-diagnostic matrix and MAC verification.
- o This product enhanced the link-speed calculation for internal variable.

Supported Devices and Features

This product supports the following network adapters:

- o HPE Ethernet 10/25Gb 2-port SFP28 BCM57414 OCP3 Adapter
- o HPE Ethernet 10Gb 2-port BaseT BCM57416 Adapter
- o HPE Ethernet 10Gb 2-port BaseT BCM57416 OCP3 Adapter
- o HPE Ethernet 10Gb 2-port SFP+ BCM57412 Adapter
- o HPE Ethernet 10Gb 2-port SFP+ BCM57412 OCP3 Adapter
- o HPE Ethernet 10/25Gb 2-port SFP28 BCM57414 Adapter
- o Broadcom BCM57504 Ethernet 10/25Gb 4-port SFP28 Adapter for HPE
- o Broadcom BCM57504 Ethernet 10/25Gb 4-port SFP28 OCP3 Adapter for HPE

HPE Broadcom NetXtreme-E Online Firmware Upgrade Utility for VMware

Version: 5.28.0 (**Recommended**)

Filename: CP071468.compsig; CP071468.zip

Important Note!

HPE recommends *HPE Broadcom NetXtreme-E Drivers for VMware*, versions 2026.05.00 or later, for use with this firmware.

This software package contains NVM Image version 237.1.148000 with the following firmware versions:

NIC	Bootcode Version	NCSI Version	MBA Version	UEFI Version	RoCE Version
HPE Ethernet 10Gb 2-port 535FLR-T Adapter	237.1.141.0	237.1.141.0	237.1.142.0	237.1.142.0	237.1.141.0
HPE Ethernet 10Gb 2-port 535T Adapter					
HPE Ethernet 10/25Gb 2-port 631FLR-SFP28 Adapter					
HPE Ethernet 10/25Gb 2-port 631SFP28 Adapter					
HPE Ethernet 10Gb 2-port 537SFP+ Adapter					
HPE Ethernet 10Gb 2-port 537SFP+ FLR Adapter					

Prerequisites

This product requires the appropriate driver for your device and operating system be installed before firmware is updated.

Fixes

- o This product fixes the issue where the PXE boot failure due to missing link flap on warm reboot
- o This product fixes the issue where the Firmware timeout errors seen when reloading driver.
- o This product fixes the issue where brcm-nicli show "Link Down" even though link is up
- o This product fixes the issue where NC-SI over MCTP fails after BMC sends concurrent commands.
- o This product fixes the issue where system resources may not be released properly if a PLDM firmware update is cancelled or times out.

Supported Devices and Features

This product supports the following network adapters:

- o HPE Ethernet 10Gb 2-port 537SFP+ Adapter
- o HPE Ethernet 10Gb 2-port 537SFP+ FLR Adapter
- o HPE Ethernet 10Gb 2-port 535T Adapter
- o HPE Ethernet 10Gb 2-port 535FLR-T Adapter
- o HPE Ethernet 10/25Gb 2-port 631SFP28 Adapter
- o HPE Ethernet 10/25Gb 2-port 631FLR-SFP28 Adapter

HPE Broadcom NX1 Online Firmware Upgrade Utility VMware for HPE ProLiant Gen10 server series Only.

Version: 1.44.0 (**Recommended**)

Filename: CP071591.compsig; CP071591.zip

Important Note!

- o **This component ONLY support HPE ProLiant Gen10 server series.**

This software package contains combo image v20.37.41 with the following firmware versions:

NIC	Boot Code Version	PXE Version	NCSI Version	UEFI Version
HPE Ethernet 1Gb 2-port 330i Adapter (22BD)	2.10	21.6.4	1.5.71	21.6.97
HPE Ethernet 1Gb 4-port 331i Adapter (22BE) HPE Ethernet 1Gb 4-port 331FLR Adapter HPE Ethernet 1Gb 4-port 331T Adapter	1.64	21.6.4	1.5.71	21.6.97
HPE Ethernet 1Gb 2-port 332i Adapter (22E8) HPE Ethernet 1Gb 2-port 332T Adapter	1.43	21.6.4	1.5.71	21.6.97

For previous firmware versions prior to v20.19.51, please refer to the link : <https://www.hpe.com/global/swpublishing/MTX-4f19da2bceff4b73a31531d71e>

Prerequisites

This product requires the appropriate driver for your device and operating system be installed before firmware is updated.

Fixes

- o This product fixes the issue where BMC ping may fail after host network interfaces are added, removed, or reconfigured.

Supported Devices and Features

This product supports the following network adapters:

- o HPE Ethernet 1Gb 2-port 330i Adapter (22BD)
- o HPE Ethernet 1Gb 4-port 331i Adapter (22BE)
- o HPE Ethernet 1Gb 4-port 331FLR Adapter
- o HPE Ethernet 1Gb 4-port 331T Adapter
- o HPE Ethernet 1Gb 2-port 332i Adapter (22E8)
- o HPE Ethernet 1Gb 2-port 332T Adapter

HPE Intel Online Firmware Upgrade Utility VMware for HPE ProLiant Gen9 and Gen10 server series Only.

Version: 3.30.0 (**Recommended**)

Filename: CP070388.compsig; CP070388.zip

Important Note!

- o This software package contains the following firmware versions for the below listed supported network adapters:

NIC	EEPROM/NVM Version	OROM Version	Single NVM Version
HPE Ethernet 1Gb 2-port 361i Adapter	8000119A	1.3911.0	N/A
HPE Ethernet 1Gb 2-port 361T Adapter	80001147	1.3911.0	N/A
HPE Ethernet 1Gb 4-port 366FLR Adapter	800011A1	1.3911.0	N/A
HPE Ethernet 1Gb 4-port 366T Adapter	800011F1	1.3911.0	N/A
HPE Ethernet 1Gb 2-port 368i Adapter	80003AC5	1.3911.0	N/A
HPE Ethernet 1Gb 2-port 368FLR-MMT Adapter	80003AC2	1.3911.0	N/A
HPE Ethernet 1Gb 4-port 369i Adapter	80003AC3	1.3911.0	N/A
HPE Ethernet 10Gb 2-port 568i Adapter	80003AC4	1.3911.0	N/A
HPE Ethernet 10Gb 2-port 568FLR-MMSFP+ Adapter	80003AC2	1.3911.0	N/A
HPE Ethernet 10Gb 2-port 568FLR-MMT Adapter	80003AC2	1.3911.0	N/A
HPE Ethernet 10Gb 2-port 563i Adapter	800035C0	1.3911.0	N/A
HPE Ethernet 10Gb 2-port 562FLR-SFP+ Adapter	8000F231	1.3911.0	11.1.7
HPE Ethernet 10Gb 2-port 562FLR-T Adapter	800016F1	1.3911.0	10.55.3
HPE Ethernet 10Gb 2-port 562SFP+ Adapter	8000F232	1.3911.0	11.1.7
HPE Ethernet 10Gb 2-port 562T Adapter	800016EF	1.3911.0	10.55.3

The combo image v1.3911.0 includes: Boot Agent: 1GbE - v1.5.90, 10GbE - v2.4.59, 40GbE - v1.1.45 & UEFI Drivers: 1GbE - v9.9.03, 10GbE - v8.3.05, 40GbE - v5.0.33

Single NVM Version is new firmware format which represent an unified version in place of the previously used EEPROM/NVM Version or OROM version.

This software package no longer contains Firmware for the below listed supported network adapters:

HPE Ethernet 1Gb 2-port 363i Adapter

HPE Ethernet 1Gb 4-port 366i Adapter

HPE Ethernet 1Gb 4-port 366i Communication Board

HPE Ethernet 10Gb 2-port 560FLR-SFP+ Adapter

HPE Ethernet 10Gb 2-port 560SFP+ Adapter

HPE Ethernet 10Gb 2-port 561FLR-T Adapter

HPE Ethernet 10Gb 2-port 561T Adapter

- o The latest firmware version of above adapters, please refer to the link : https://support.hpe.com/connect/s/softwaredetails?language=en_US&softwareId=MTX_d7826493bb5a4aa69b4aa9a1d5&tab=releaseNotes

Prerequisites

This product requires the appropriate driver for your device and operating system be installed before firmware is updated.

Fixes

- o This product fixed an HII defect where the "functionless default" overwrote modification information for the same flag field.
- o This product fixed an issue where BIOS failed to preserve greyed-out options, preventing unintended writes.

Enhancements

Added ESXi 9.1 Supported Environment

Supported Devices and Features

This package supports the following network adapters:

- o HPE Ethernet 1Gb 2-port 361i Adapter
- o HPE Ethernet 1Gb 2-port 361T Adapter
- o HPE Ethernet 1Gb 2-port 368FLR-MMT Adapter
- o HPE Ethernet 1Gb 2-port 368i Adapter
- o HPE Ethernet 1Gb 4-port 366FLR Adapter

- o HPE Ethernet 1Gb 4-port 366T Adapter
- o HPE Ethernet 1Gb 4-port 369i Adapter
- o HPE Ethernet 10Gb 2-port 562FLR-SFP+ Adapter
- o HPE Ethernet 10Gb 2-port 562FLR-T Adapter
- o HPE Ethernet 10Gb 2-port 562SFP+ Adapter
- o HPE Ethernet 10Gb 2-port 562T Adapter
- o HPE Ethernet 10Gb 2-port 568FLR-MMSFP+ Adapter
- o HPE Ethernet 10Gb 2-port 568FLR-MMT Adapter
- o HPE Ethernet 10Gb 2-port 568i Adapter
- o HPE Ethernet 10Gb 2-port 563i Adapter

HPE QLogic FastLinQ Firmware Package for Arrowhead adapters

Version: 8.65.23 (C) **(Recommended)**

Filename: ql_hp_ah_mbi_8.65.23_pldm.fwpkg

Important Note!

For Firmware installation, there is no OS and drivers dependency.

For Firmware compatibility during production, HPE recommends the drivers for use with the firmware Package product as below,

- o HPE QLogic FastLinQ 10/25/50 GbE Drivers for Linux, version 8.76.2.0-10 or later
- o HPE QLogic FastLinQ 10/25/50 GbE Drivers for Microsoft Windows Server x64 Editions, version 8.72.21.0 or later
- o HPE QLogic FastLinQ 10/25/50 GbE Multifunction Drivers for VMware, version 2025.09.00 or later

This software package contains combo image v8.65.23. This combo image includes: Boot Code (MFW): 8.65.7.0, PXE: 2.0.19, and UEFI: 4.1.13.2.

Enhancements

Added SLES16 Support Environment

Supported Devices and Features

This product supports the following network adapters:

- o HPE Ethernet 10Gb 2-port 521T Adapter
- o HPE Ethernet 10Gb 2-port 524SFP+ Adapter
- o HPE Ethernet 10/25Gb 2-port 621SFP28 Adapter
- o HPE Ethernet 10/25Gb 2-port 622FLR-SFP28 Adapter
- o HPE StoreFabric CN1200R-T Converged Network Adapter
- o HPE StoreFabric CN1300R Converged Network Adapter

HPE QLogic FastLinQ Online Firmware Upgrade Utility for VMware

Version: 4.20.0 (B) **(Recommended)**

Filename: CP070386.compsig; CP070386.zip

Important Note!

HPE recommends *HPE QLogic FastLinQ 10/25/50GbE Multifunction Drivers for VMware*, versions 2025.03.00 or later, for use with this firmware.

This software package contains combo image version v8.65.23 includes:

- o Boot Code (MFW): 8.65.7.0
- o UEFI: 4.1.13.2
- o PXE: 2.0.19

The users will only see the combo image versions in the interactive mode firmware update or while using HPSUM/SPP to update the firmware on the supported adapters.

Prerequisites

This product requires the appropriate driver for your device and operating system be installed before firmware is updated.

Fixes

This product fixed the ESXi 9.1 supported issue.

Enhancements

This product enhanced the compatibility with drivers.

Supported Devices and Features

This product supports the following network adapters:

- HPE Ethernet 10Gb 2-port 521T Adapter
- HPE Ethernet 10Gb 2-port 524SFP+ Adapter
- HPE Ethernet 10/25Gb 2-port 621SFP28 Adapter
- HPE Ethernet 10/25Gb 2-port 622FLR-SFP28 Converged Network Adapter
- HPE StoreFabric CN1200R-T Converged Network Adapter
- HPE StoreFabric CN1300R Converged Network Adapter

HPE QLogic FastLinQ Online Firmware Upgrade Utility for VMware

Version: 8.55.12 (C) **(Recommended)**

Filename: CP070642.compsig; CP070642.zip

Important Note!

HPE recommends *HPE QLogic FastLinQ 10/25/50GbE Multifunction Drivers for VMware*, versions 2021.04.05 or later, for use with this firmware.

This software package contains combo image version v8.55.12 includes:

- Boot Code (MFW): 8.55.21.0
- UEFI: 4.1.11.2
- PXE: 2.0.19

The users will only see the combo image versions in the interactive mode firmware update or while using HPSUM/SPP to update the firmware on the supported adapters.

Prerequisites

This product requires the appropriate driver for your device and operating system be installed before firmware is updated.

Fixes

This product addresses a pause flood condition on switch when attempting iPXE boot.

Enhancements

This product contains support PLDM firmware upgrade base improvements.

Supported Devices and Features

This product supports the following network adapters:

- HPE Ethernet 10Gb 2-port 521T Adapter
- HPE Ethernet 10Gb 2-port 524SFP+ Adapter
- HPE Ethernet 10/25Gb 2-port 621SFP28 Adapter
- HPE Ethernet 10/25Gb 2-port 622FLR-SFP28 Converged Network Adapter
- HPE StoreFabric CN1200R-T Converged Network Adapter
- HPE StoreFabric CN1300R Converged Network Adapter

HPE QLogic NX2 Online Firmware Upgrade Utility for VMware
Version: 1.37.0 (B) **(Recommended)**
Filename: CP070394.compsig; CP070394.zip

Important Note!

HPE recommends HPE QLogic NX2 10/20GbE Multifunction Drivers for VMware, versions 2025.03.00 or later, for use with this firmware.

This software package contains combo image v7.19.27 with the following firmware versions:

NIC	Boot Code Version	PXE Version	UEFI Version	iSCSI Version	FCoE Version	CCM Version	L2 Version
HPE Ethernet 10Gb 2-port 530SFP+ Adapter HPE Ethernet 10Gb 2-port 530T Adapter	7.16.15	7.14.13	8.9.3	n/a	n/a	7.14.4	7.12.25
HPE Ethernet 10Gb 2-port 533FLR-T Adapter HPE FlexFabric 10Gb 2-port 534FLR-SFP+ Adapter HPE FlexFabric 10Gb 4-port 536FLR-T Adapter	7.16.15	7.14.13	8.9.3	7.14.0	7.14.3	7.14.4	7.12.25

Prerequisites

This product requires the appropriate driver for your device and operating system be installed before firmware is updated.

Fixes

This product fixed the ESXi 9.1 supported issue.

Enhancements

This product enhanced the compatibility with drivers.

Supported Devices and Features

This product supports the following network adapters:

- HPE Ethernet 10Gb 2-port 530SFP+ Adapter
- HPE Ethernet 10Gb 2-port 530T Adapter
- HPE Ethernet 10Gb 2-port 533FLR-T Adapter
- HPE FlexFabric 10Gb 2-port 534FLR-SFP+ Adapter
- HPE FlexFabric 10Gb 4-port 536FLR-T Adapter

Intel Firmware Package For E810-2CQDA2 Ethernet 100Gb 2-port QSFP28 Adapter
Version: 4.20 **(Recommended)**
Filename: HPE_E810_2CQDA2_O_SEC_4p20_PLDMoMCTP_80017784.fwpkg

Important Note!

For Firmware installation, there is no OS and drivers dependency.
For Firmware compatibility during production, HPE recommends the drivers for use with the firmware Package product as below,

- Intel icea Driver for Microsoft Windows Server, version 1.12.164.0 or later
- Intel ice Drivers for Linux, version 1.11.14-1 or later
- Intel icen Driver for VMware, version 2023.09.00 or later

This FW version does not support Port.Reset RDE metrics. This product will be enhance to improve the functions in the future release

Fixes

- This product addresses an issue where InterfaceEnabled property is read only and it can't patch this property
- This product addresses an issue where UMCE is seen

Enhancements

This product now supports ResetToDefault property(RDE Port Schema).

Supported Devices and Features

This product supports the following network adapters:

- Intel E810-2CQDA2 Ethernet 100Gb 2-port QSFP28 Adapter for HPE

Intel Firmware Package For E810-2CQDA2 Ethernet 100Gb 2-port QSFP28 Adapter

Version: 4.91 (**Recommended**)

Filename: HPE_E810_2CQDA2_O_SEC_4p91_PLDMoMCTP_800214AE.fwpkg; HPE_E810_2CQDA2_O_SEC_4p91_PLDMoMCTP_800214AE.json

Important Note!

For Firmware installation, there is no OS and drivers dependency.

For Firmware compatibility during production, HPE recommends the drivers for use with the firmware Package product as below,

- Intel icea Driver for Microsoft Windows Server, version 1.18.71.0 or later
- Intel ice Drivers for Linux, version 2.4.5-1 or later
- Intel icen Driver for VMware, version 2026.03.00 or later

This FW version does not support Port.Reset RDE metrics. This product will be enhance to improve the functions in the future release

Fixes

- This product fixed an issue where the Shared NIC IP was not assigned for OCP Slot B network adapters on Gen12 ProLiant servers.

Supported Devices and Features

This product supports the following network adapters:

- Intel E810-2CQDA2 Ethernet 100Gb 2-port QSFP28 Adapter for HPE

Intel Firmware Package For E810-CQDA2 Ethernet 100Gb 2-port QSFP28 Adapter

Version: 4.20 (**Recommended**)

Filename: HPE_E810_CQDA2_4p20_PLDMoMCTP_80017785.fwpkg

Important Note!

For Firmware installation, there is no OS and drivers dependency.

For Firmware compatibility during production, HPE recommends the drivers for use with the firmware Package product as below,

- Intel icea Driver for Microsoft Windows Server, version 1.12.164.0 or later
- Intel ice Drivers for Linux, version 1.11.14-1 or later
- Intel icen Driver for VMware, version 2023.09.00 or later

This FW version does not support Port.Reset RDE metrics. This product will be enhance to improve the functions in the future release

Fixes

- This product addresses an issue where InterfaceEnabled property is read only and it can't patch this property
- This product addresses an issue where UMCE is seen

Enhancements

This product now supports ResetToDefault property(RDE Port Schema).

Supported Devices and Features

This product supports the following network adapters:

- Intel E810-CQDA2 Ethernet 100Gb 2-port QSFP28 Adapter for HPE

Intel Firmware Package For E810-CQDA2 Ethernet 100Gb 2-port QSFP28 Adapter

Version: 4.91 (**Recommended**)

Filename: HPE_E810_CQDA2_4p91_PLDMoMCTP_800214AF.fwpkg; HPE_E810_CQDA2_4p91_PLDMoMCTP_800214AF.json

Important Note!

For Firmware installation, there is no OS and drivers dependency.
For Firmware compatibility during production, HPE recommends the drivers for use with the firmware Package product as below,

- o Intel icea Driver for Microsoft Windows Server, version 1.18.71.0 or later
- o Intel ice Drivers for Linux, version 2.4.5-1 or later
- o Intel icen Driver for VMware, version 2026.03.00 or later

This FW version does not support Port.Reset RDE metrics. This product will be enhance to improve the functions in the future release

Fixes

- o This product fixed an issue where the Shared NIC IP was not assigned for OCP Slot B network adapters on Gen12 ProLiant servers.

Supported Devices and Features

This product supports the following network adapters:

- o Intel E810-CQDA2 Ethernet 100Gb 2-port QSFP28 Adapter for HPE

Intel Firmware Package For E810-CQDA2 Ethernet 100Gb 2-port QSFP28 OCP3 Adapter
Version: 4.20 **(Recommended)**
Filename: HPE_E810_CQDA2_OCP_4p20_NCSIwPLDMoMCTP_80017783.fwpkg

Important Note!

For Firmware installation, there is no OS and drivers dependency.
For Firmware compatibility during production, HPE recommends the drivers for use with the firmware Package product as below,

- o Intel icea Driver for Microsoft Windows Server, version 1.12.164.0 or later
- o Intel ice Drivers for Linux, version 1.11.14-1 or later
- o Intel icen Driver for VMware, version 2023.09.00 or later

This FW version does not support Port.Reset RDE metrics. This product will be enhance to improve the functions in the future release

Fixes

- o This product addresses an issue where InterfaceEnabled property is read only and it can't patch this property
- o This product addresses an issue where UMCE is seen

Enhancements

This product now supports ResetToDefault property(RDE Port Schema).

Supported Devices and Features

This product supports the following network adapters:

- o Intel E810-CQDA2 Ethernet 100Gb 2-port QSFP28 OCP3 Adapter for HPE

Intel Firmware Package For E810-CQDA2 Ethernet 100Gb 2-port QSFP28 OCP3 Adapter
Version: 4.91 **(Recommended)**
Filename: HPE_E810_CQDA2_OCP_4p91_NCSIwPLDMoMCTP_800214AD.fwpkg; HPE_E810_CQDA2_OCP_4p91_NCSIwPLDMoMCTP_800214AD.json

Important Note!

For Firmware installation, there is no OS and drivers dependency.
For Firmware compatibility during production, HPE recommends the drivers for use with the firmware Package product as below,

- o Intel icea Driver for Microsoft Windows Server, version 1.18.71.0 or later
- o Intel ice Drivers for Linux, version 2.4.5-1 or later
- o Intel icen Driver for VMware, version 2026.03.00 or later

This FW version does not support Port.Reset RDE metrics. This product will be enhance to improve the functions in the future release

Fixes

- o This product fixed an issue where the Shared NIC IP was not assigned for OCP Slot B network adapters on Gen12 ProLiant servers.

Supported Devices and Features

This product supports the following network adapters:

- o Intel E810-CQDA2 Ethernet 100Gb 2-port QSFP28 OCP3 Adapter for HPE

Intel Firmware Package For E810-XXVDA2 Ethernet 10/25Gb 2-port SFP28 Adapter
Version: 4.20 **(Recommended)**
Filename: HPE_E810_XXVDA2_SD_4p20_PLDMoMCTP_8001778C.fwpkg

Important Note!

For Firmware installation, there is no OS and drivers dependency.
For Firmware compatibility during production, HPE recommends the drivers for use with the firmware Package product as below,

- o Intel icea Driver for Microsoft Windows Server, version 1.12.164.0 or later
- o Intel ice Drivers for Linux, version 1.11.14-1 or later
- o Intel icen Driver for VMware, version 2023.09.00 or later

This FW version does not support Port.Reset RDE metrics. This product will be enhance to improve the functions in the future release

Fixes

- o This product addresses an issue where InterfaceEnabled property is read only and it can't patch this property
- o This product addresses an issue where UMCE is seen

Enhancements

This product now supports ResetToDefault property(RDE Port Schema).

Supported Devices and Features

This product supports the following network adapters:

- o Intel E810-XXVDA2 Ethernet 10/25Gb 2-port SFP28 Adapter for HPE

Intel Firmware Package For E810-XXVDA2 Ethernet 10/25Gb 2-port SFP28 Adapter

Version: 4.91 (**Recommended**)

Filename: HPE_E810_XXVDA2_SD_4p91_PLDMoMCTP_800214AB.fwpkg; HPE_E810_XXVDA2_SD_4p91_PLDMoMCTP_800214AB.json

Important Note!

For Firmware installation, there is no OS and drivers dependency.

For Firmware compatibility during production, HPE recommends the drivers for use with the firmware Package product as below,

- o Intel icea Driver for Microsoft Windows Server, version 1.18.71.0 or later
- o Intel ice Drivers for Linux, version 2.4.5-1 or later
- o Intel icen Driver for VMware, version 2026.03.00 or later

This FW version does not support Port.Reset RDE metrics. This product will be enhance to improve the functions in the future release

Fixes

- o This product fixed an issue where the Shared NIC IP was not assigned for OCP Slot B network adapters on Gen12 ProLiant servers.

Supported Devices and Features

This product supports the following network adapters:

- o Intel E810-XXVDA2 Ethernet 10/25Gb 2-port SFP28 Adapter for HPE

Intel Firmware Package For E810-XXVDA2 Ethernet 10/25Gb 2-port SFP28 OCP3 Adapter

Version: 4.20 (**Recommended**)

Filename: HPE_E810_XXVDA2_SD_OCP_4p20_NCSIwPLDMoMCTP_80017787.fwpkg

Important Note!

For Firmware installation, there is no OS and drivers dependency.

For Firmware compatibility during production, HPE recommends the drivers for use with the firmware Package product as below,

- o Intel icea Driver for Microsoft Windows Server, version 1.12.164.0 or later
- o Intel ice Drivers for Linux, version 1.11.14-1 or later
- o Intel icen Driver for VMware, version 2023.09.00 or later

This FW version does not support Port.Reset RDE metrics. This product will be enhance to improve the functions in the future release

Fixes

- o This product addresses an issue where InterfaceEnabled property is read only and it can't patch this property
- o This product addresses an issue where UMCE is seen

Enhancements

This product now supports ResetToDefault property(RDE Port Schema).

Supported Devices and Features

This product supports the following network adapters:

- o Intel E810-XXVDA2 Ethernet 10/25Gb 2-port SFP28 OCP3 Adapter for HPE

Intel Firmware Package For E810-XXVDA2 Ethernet 10/25Gb 2-port SFP28 OCP3 Adapter
Version: 4.91 (**Recommended**)
Filename: HPE_E810_XXVDA2_SD_OCP_4p91_NCSIwPLDMoMCTP_800214B2.fwpkg; HPE_E810_XXVDA2_SD_OCP_4p91_NCSIwPLDMoMCTP_800214B2.json

Important Note!

For Firmware installation, there is no OS and drivers dependency.
For Firmware compatibility during production, HPE recommends the drivers for use with the firmware Package product as below,

- o Intel icea Driver for Microsoft Windows Server, version 1.18.71.0 or later
- o Intel ice Drivers for Linux, version 2.4.5-1 or later
- o Intel icen Driver for VMware, version 2026.03.00 or later

This FW version does not support Port.Reset RDE metrics. This product will be enhance to improve the functions in the future release

Fixes

- o This product fixed an issue where the Shared NIC IP was not assigned for OCP Slot B network adapters on Gen12 ProLiant servers.

Supported Devices and Features

This product supports the following network adapters:

- o Intel E810-XXVDA2 Ethernet 10/25Gb 2-port SFP28 OCP3 Adapter for HPE

Intel Firmware Package For E810-XXVDA4 Ethernet 10/25Gb 4-port SFP28 Adapter
Version: 4.20 (**Recommended**)
Filename: HPE_E810_XXVDA4_FH_4p20_PLDMoMCTP_80017789.fwpkg

Important Note!

For Firmware installation, there is no OS and drivers dependency.
For Firmware compatibility during production, HPE recommends the drivers for use with the firmware Package product as below,

- o Intel icea Driver for Microsoft Windows Server, version 1.12.164.0 or later
- o Intel ice Drivers for Linux, version 1.11.14-1 or later
- o Intel icen Driver for VMware, version 2023.09.00 or later

This FW version does not support Port.Reset RDE metrics. This product will be enhance to improve the functions in the future release

Fixes

- o This product addresses an issue where InterfaceEnabled property is read only and it can't patch this property
- o This product addresses an issue where UMCE is seen

Enhancements

This product now supports ResetToDefault property(RDE Port Schema).

Supported Devices and Features

This product supports the following network adapters:

- o Intel E810-XXVDA4 Ethernet 10/25Gb 4-port SFP28 Adapter for HPE

Intel Firmware Package For E810-XXVDA4 Ethernet 10/25Gb 4-port SFP28 Adapter
Version: 4.91 (**Recommended**)
Filename: HPE_E810_XXVDA4_FH_4p91_PLDMoMCTP_800214B3.fwpkg; HPE_E810_XXVDA4_FH_4p91_PLDMoMCTP_800214B3.json

Important Note!

For Firmware installation, there is no OS and drivers dependency.
For Firmware compatibility during production, HPE recommends the drivers for use with the firmware Package product as below,

- o Intel icea Driver for Microsoft Windows Server, version 1.18.71.0 or later
- o Intel ice Drivers for Linux, version 2.4.5-1 or later
- o Intel icen Driver for VMware, version 2026.03.00 or later

This FW version does not support Port.Reset RDE metrics. This product will be enhance to improve the functions in the future release

Fixes

- o This product fixed an issue where the Shared NIC IP was not assigned for OCP Slot B network adapters on Gen12 ProLiant servers.

Supported Devices and Features

This product supports the following network adapters:

- o Intel E810-XXVDA4 Ethernet 10/25Gb 4-port SFP28 Adapter for HPE
-

Intel Firmware Package For E810-XXVDA4 Ethernet 10/25Gb 4-port SFP28 OCP3 Adapter
Version: 4.20 **(Recommended)**
Filename: HPE_E810_XXV4_OCP_4p20_NCSIwPLDMoMCTP_80017788.fwpkg

Important Note!

- For Firmware installation, there is no OS and drivers dependency.
For Firmware compatibility during production, HPE recommends the drivers for use with the firmware Package product as below,
- Intel icea Driver for Microsoft Windows Server, version 1.12.164.0 or later
 - Intel ice Drivers for Linux, version 1.11.14-1 or later
 - Intel icen Driver for VMware, version 2023.09.00 or later

This FW version does not support Port.Reset RDE metrics. This product will be enhance to improve the functions in the future release

Fixes

- This product addresses an issue where InterfaceEnabled property is read only and it can't patch this property
- This product addresses an issue where UMCE is seen

Enhancements

This product now supports ResetToDefault property(RDE Port Schema).

Supported Devices and Features

- This product supports the following network adapters:
- Intel E810-XXVDA4 Ethernet 10/25Gb 4-port SFP28 OCP3 Adapter for HPE

Intel Firmware Package For E810-XXVDA4 Ethernet 10/25Gb 4-port SFP28 OCP3 Adapter
Version: 4.91 **(Recommended)**
Filename: HPE_E810_XXV4_OCP_4p91_NCSIwPLDMoMCTP_800214AC.fwpkg; HPE_E810_XXV4_OCP_4p91_NCSIwPLDMoMCTP_800214AC.json

Important Note!

- For Firmware installation, there is no OS and drivers dependency.
For Firmware compatibility during production, HPE recommends the drivers for use with the firmware Package product as below,
- Intel icea Driver for Microsoft Windows Server, version 1.18.71.0 or later
 - Intel ice Drivers for Linux, version 2.4.5-1 or later
 - Intel icen Driver for VMware, version 2026.03.00 or later

This FW version does not support Port.Reset RDE metrics. This product will be enhance to improve the functions in the future release

Fixes

- This product fixed an issue where the Shared NIC IP was not assigned for OCP Slot B network adapters on Gen12 ProLiant servers.

Supported Devices and Features

- This product supports the following network adapters:
- Intel E810-XXVDA4 Ethernet 10/25Gb 4-port SFP28 OCP3 Adapter for HPE

Intel Online Firmware Upgrade Utility for VMware
Version: 3.29.0 **(Recommended)**
Filename: CP070391.compsig; CP070391.zip

Important Note!

This software package contains the following firmware versions for the below listed supported network adapters:

NIC	EEPROM/NVM Version	OROM Version	Single NVM Version	FW Version
HPE Ethernet 10Gb 2-port SFP+ OCP3 X710-DA2 Adapter	800100D3	1.3909.0	N/A	9.56
HPE Ethernet 10Gb 2-port SFP+ X710-DA2 Adapter	800100DE	1.3909.0	N/A	9.56
Intel I350-T4 Ethernet 1Gb 4-port BASE-T Adapter	8000123F	1.3909.0	N/A	N/A
Intel I350-T4 Ethernet 1Gb 4-port BASE-T OCP3 Adapter	80001234	1.3909.0	N/A	N/A
Intel(R) I350 Gigabit Network Connection (2-port)	8000119C	1.3909.0	N/A	N/A
Intel(R) I350 Gigabit Network Connection (4-port)	8000E897	1.3909.0	N/A	N/A

The combo image v1.3909.0 includes: Boot Agent: 1GbE - v1.5.90, 10GbE - v2.4.59, 40GbE - v1.1.45 & UEFI Drivers: 1GbE - v9.9.03, 10GbE - v8.3.05, 40GbE - v5.0.33
Single NVM Version is new firmware format which represent an unified version in place of the previously used EEPROM/NVM Version or OROM version.

Prerequisites

This product requires the appropriate driver for your device and operating system be installed before firmware is updated.

Fixes

- o This product fixed an HII defect where the "functionless default" overwrote modification information for the same flag field.
- o This product fixed an issue where BIOS failed to preserve greyed-out options, preventing unintended writes.

Enhancements

Added ESXi 9.1 Supported Environment

Supported Devices and Features

This package supports the following network adapters:

- o Intel(R) I350 Gigabit Network Connection (2-port)
- o Intel(R) I350 Gigabit Network Connection (4-port)
- o HPE Ethernet 1Gb 4-port BaseT I350-T4 Adapter
- o HPE Ethernet 1Gb 4-port BaseT I350-T4 OCP3 Adapter
- o HPE Ethernet 10Gb 2-port SFP+ X710-DA2 OCP3 Adapter
- o HPE Ethernet 10Gb 2-port SFP+ X710-DA2 Adapter

Marvell FastLinQ Firmware Package for Arrowhead adapters

Version: 8.65.21 (C) **(Recommended)**

Filename: ql_ah_mbi_open_8.65.21_pldm.fwpkg

Important Note!

For Firmware installation, there is no OS and drivers dependency.

For Firmware compatibility during production, HPE recommends the drivers for use with the firmware Package product as below,

- o Marvell FastLinQ 10/25/50 GbE Drivers for Microsoft Windows Server x64 Editions, version 8.72.21.0 or later
- o HPE QLogic FastLinQ 10/25/50 GbE Drivers for Linux, version 8.76.2.0-10 or later
- o HPE QLogic FastLinQ 10/25/50 GbE Multifunction Drivers for VMware, version 2025.09.00 or later

Enhancements

Added SLES16 Support Environment

Supported Devices and Features

This product supports the following network adapters:

- o HPE Ethernet 10/25Gb 2-port SFP28 QL41232HLCU Adapter
- o HPE Ethernet 10/25Gb 2-port SFP28 QL41232HQCUC OCP3 Adapter
- o HPE Ethernet 10Gb 2-port BaseT QL41132HLRJ Adapter
- o HPE Ethernet 10Gb 2-port BaseT QL41132HQRJ OCP3 Adapter
- o HPE Ethernet 10Gb 2-port SFP+ QL41132HLCU Adapter
- o HPE Ethernet 10Gb 2-port SFP+ QL41132HQCUC OCP3 Adapter
- o HPE Ethernet 10Gb 4-port SFP+ QL41134HLCU Adapter

Marvell FastLinQ Online Firmware Upgrade Utility for VMware

Version: 8.55.12 (C) **(Recommended)**

Filename: CP070643.compsig; CP070643.zip

Important Note!

This software package contains combo image v8.55.12. This combo image includes:

- o PXE: 2.0.19
- o Boot Code (MFW): 8.55.22.0
- o UEFI: 6.1.8.2

Prerequisites

This product requires the appropriate driver for your device and operating system be installed before firmware is updated.

Fixes

- o This product contains support PLDM firmware upgrade base improvements.
- o This product addresses an overheat issue on the network adapters as below,
 - HPE Ethernet 10Gb 2-port BaseT QL41132HLRJ Adapter
 - HPE Ethernet 10Gb 2-port BaseT QL41132HQRJ OCP3 Adapter

Enhancements

This product now supported NPAR enabling option.

Supported Devices and Features

This product supports the following network adapters:

- o HPE Ethernet 10/25Gb 2-port SFP28 QL41232HQCUC OCP3 Adapter
- o HPE Ethernet 10/25Gb 2-port SFP28 QL41232HLCU Adapter

- o HPE Ethernet 10Gb 4-port SFP+ QL41134HLCU Adapter
- o HPE Ethernet 10Gb 2-port BaseT QL41132HLRJ Adapter
- o HPE Ethernet 10Gb 2-port BaseT QL41132HQRJ OCP3 Adapter
- o HPE Ethernet 10Gb 2-port SFP+ QL41132HQCUC OCP3 Adapter
- o HPE Ethernet 10Gb 2-port SFP+ QL41132HLCU Adapter

Mellanox Firmware Package (FWPKG) for HPE Edgeline e920 ConnectX-6Lx 10Gb 2-port Mezzanine Adapter : HPE part number P40899-B21
Version: 26.43.1014 **(Recommended)**
Filename: 26_43_1014-FWEdgelinee920ConnectX-6Lx10Gb2-portNetworkMezzanine_Ax.pldm.fwpkg; 26_43_1014-FWEdgelinee920ConnectX-6Lx10Gb2-portNetworkMezzanine_Ax.pldm.json

Prerequisites

FWPKG will work only if the firmware version flashed on the adapter is 20.27.1016 or later and iLO5 firmware version must be 2.30 or higher.

Fixes

The following issues have been fixed in version 26.43.1014:

Enhancements

Security Hardening Enhancements: This release contains important reliability improvements and security hardening enhancements. HPE recommends upgrading your device's firmware to this release to improve the firmware security and reliability of your device.

New features and changes included in version 26.43.1014:

Supported Devices and Features

This software package contains the following firmware versions:

Mellanox InfiniBand Adapter	Firmware Version	PSID
HPE Edgeline e920 ConnectX-6Lx 10Gb 2-port Mezzanine Adapter(P40899-B21)	26.43.1014	HPE0000000059

Mellanox Firmware Package(FWPKG) for HPE NVIDIA Ethernet 100Gb 2-port NVMe-oF Offload Adapter for HPE
Version: 22.45.1020 **(Recommended)**
Filename: 22_45_1020-R8M41-63001_Ax_header.pldm.fwpkg

Prerequisites

FWPKG will work only if the firmware version flashed on the adapter is 22.27.1016 or later and iLO5 firmware version must be 2.30 or higher.

Enhancements

Upgraded to version 22.45.1020

Supported Devices and Features

HPE Part Number	Mellanox Ethernet Only Adapters	PSID
P46603-B21	NVIDIA Ethernet 100Gb 2-port NVMe-oF Offload Adapter for HPE	HPE0000000062

Mellanox Firmware Package(FWPKG) for NVIDIA Ethernet 10/25Gb 2-port SFP28 NVMe-oF Crypto Adapter for HPE
Version: 26.45.1020 **(Recommended)**
Filename: 26_45_1020-S2A69-63001_Ax_header.pldm.fwpkg

Prerequisites

FWPKG will work only if the firmware version flashed on the adapter is 22.27.1016 or later and iLO5 firmware version must be 2.30 or higher.

Enhancements

Upgraded to version 26.45.1020

Supported Devices and Features

HPE SKU Part Number	Mellanox Ethernet Only Adapters	PSID
S2A69A	NVIDIA Ethernet 10/25Gb 2-port SFP28 NVMe-oF Crypto Adapter for HPE	HPE0000000077

NVIDIA Firmware Package (FWPKG) - Mellanox MCX631102AS-ADAT Ethernet 10/25Gb 2-port SFP28 Adapter for HPE
Version: 26.49.1014 **(Recommended)**
Filename: 26_49_1014-MCX631102AS-ADA_Ax.pldm.fwpkg; 26_49_1014-MCX631102AS-ADA_Ax.pldm.json

Important Note!

Disclaimer: Certain software including drivers and documents may be available from NVIDIA. If you select a URL that directs you to <http://www.nvidia.com/>, you are then leaving HPE.com. Please follow the instructions on <http://www.nvidia.com/> to download NVIDIA software or documentation. When downloading the NVIDIA software or documentation, you may be subject to NVIDIA terms and conditions, including licensing terms, if any, provided on its website or otherwise. HPE is not responsible for your use of any software or documents that you download from <http://www.nvidia.com/>, except that HPE may provide a limited warranty for NVIDIA software in accordance with the terms and conditions of your purchase of the HPE product or solution.

A list of known issues with this release is available under Section 6 in : <https://docs.nvidia.com/nvidia-connectx-6-lx-adapter-cards-firmware-release-notes-v26-49-1014.pdf>

Prerequisites

FWPKG will work only if the firmware version flashed on the adapter is 20.27.1016 or later and iLO5 firmware version must be 2.30 or higher.

Fixes

The following issues have been fixed in version 26.49.1014:

- o Live migration target would not receive a port state change event on the resume VHCA command. The target now generates this event so software that depends on port state is notified of any changes.
- o PCC issue where RDMA traffic would stall at large scale for certain IP and UDP source-port combinations when a PCC user algorithm was active and no CC algorithm was configured in slot 0.

Enhancements

No new features or changes are included in version 26.49.1014.

Supported Devices and Features

HPE Part Number	NVIDIA Ethernet Only Adapters	PSID
P42044-B21	Mellanox MCX631102AS-ADAT Ethernet 10/25Gb 2-port SFP28 Adapter for HPE	MT_0000000575

NVIDIA Firmware Package (FWPKG) - Mellanox MCX631432AS-ADAI Ethernet 10/25Gb 2-port SFP28 OCP3 Adapter for HPE

Version: 26.49.1014 **(Recommended)**

Filename: 26_49_1014-MCX631432AS-ADA_Ax.pldm.fwpkg; 26_49_1014-MCX631432AS-ADA_Ax.pldm.json

Important Note!

Disclaimer: Certain software including drivers and documents may be available from NVIDIA. If you select a URL that directs you to <http://www.nvidia.com/>, you are then leaving HPE.com. Please follow the instructions on <http://www.nvidia.com/> to download NVIDIA software or documentation. When downloading the NVIDIA software or documentation, you may be subject to NVIDIA terms and conditions, including licensing terms, if any, provided on its website or otherwise. HPE is not responsible for your use of any software or documents that you download from <http://www.nvidia.com/>, except that HPE may provide a limited warranty for NVIDIA software in accordance with the terms and conditions of your purchase of the HPE product or solution.

A list of known issues with this release is available under Section 6 in : <https://docs.nvidia.com/nvidia-connectx-6-lx-adapter-cards-firmware-release-notes-v26-49-1014.pdf>

Prerequisites

FWPKG will work only if the firmware version flashed on the adapter is 20.27.1016 or later and iLO5 firmware version must be 2.30 or higher.

Fixes

The following issues have been fixed in version 26.49.1014:

- o Live migration target would not receive a port state change event on the resume VHCA command. The target now generates this event so software that depends on port state is notified of any changes.
- o PCC issue where RDMA traffic would stall at large scale for certain IP and UDP source-port combinations when a PCC user algorithm was active and no CC algorithm was configured in slot 0.

Enhancements

No new features or changes are included in version 26.49.1014.

Supported Devices and Features

HPE Part Number	NVIDIA Ethernet Only Adapters	PSID
P42041-B21	Mellanox MCX631432AS-ADAI Ethernet 10/25Gb 2-port SFP28 OCP3 Adapter for HPE	MT_0000000551

NVIDIA Firmware Package (FWPKG) for HPE Ethernet 100Gb 1-port QSFP28 PCIe3 x16 MCX515A-CCAT Adapter : HPE part numbers P31246-B21 and P31246-H21

Version: 16.35.8008 **(Recommended)**

Filename: 16_35_8008-MCX515A-CCA_HPE_Ax.pldm.fwpkg; 16_35_8008-MCX515A-CCA_HPE_Ax.pldm.json

Important Note!

For PLDM enabled VPI (Virtual Protocol Interconnect) adapters supporting both InfiniBand mode and Ethernet modes, every firmware version is made available in two different formats at HPE.com:

1. HPE signed PLDM Firmware Package (.FWPKG filename extension) updatable via iLO.

2. Firmware binary (.bin filename extension) updatable via mstflint utility from the Operating System.

Choose the appropriate firmware file format based on your preference and what suits your environment.

Disclaimer: Certain software including drivers and documents may be available from NVIDIA. If you select a URL that directs you to <http://www.nvidia.com/>, you are then leaving HPE.com. Please follow the instructions on <http://www.nvidia.com/> to download NVIDIA software or documentation. When downloading the NVIDIA software or documentation, you may be subject to NVIDIA terms and conditions, including licensing terms, if any, provided on its website or otherwise. HPE is not responsible for your use of any software or documents that you download from <http://www.nvidia.com/>, except that HPE may provide a limited warranty for NVIDIA software in accordance with the terms and conditions of your purchase of the HPE product or solution.

A list of known issues with this release is available at: <https://networking-docs.nvidia.com/connectx5fwrn/16358008its/known-issues>

Prerequisites

FWPKG will work only if the firmware version flashed on the adapter is 16.27.1016 or later and iLO5 firmware version must be 2.30 or higher.

Fixes

No fixes are included in version 16.35.8008.

Enhancements

New features and changes included in version 16.35.8008:

- o To align with updated Microsoft UEFI Secure Boot requirements and the upcoming end-of-life of the 2011 Certificate Authority (CA), a transition to the 2023 CA has been done.

Please also refer to the HPE advisory on Microsoft Windows UEFI CA 2023 certificate update: https://support.hpe.com/hpsc/public/docDisplay?docId=a00156355en_us&docLocale=en_US

Supported Devices and Features

This software package contains the following firmware versions:

NVIDIA Ethernet Only Adapters	Firmware Version	PSID
HPE Ethernet 100Gb 1-port QSFP28 PCIe3 x16 MCX515A-CCAT Adapter(P31246-B21 and P31246-H21)	16.35.8008	MT_0000000591

NVIDIA Firmware Package (FWPKG) for HPE InfiniBand HDR/Ethernet 200Gb 1-port QSFP56 PCIe4 x16 MCX653105A-HDAT Adapter : HPE part numbers P23664-B21 and P23664-H21

Version: 20.43.8004 **(Recommended)**

Filename: 20_43_8004-MCX653105A-HDA_HPE_Ax.pldm.fwpkg; 20_43_8004-MCX653105A-HDA_HPE_Ax.pldm.json

Important Note!

For PLDM enabled VPI (Virtual Protocol Interconnect) adapters supporting both InfiniBand mode and Ethernet modes, every firmware version is made available in two different formats at HPE.com:

1. HPE signed PLDM Firmware Package (.FWPKG filename extension) updatable via iLO.
2. Firmware binary (.bin filename extension) updatable via mstflint utility from the Operating System.

Choose the appropriate firmware file format based on your preference and what suits your environment.

Disclaimer: Certain software including drivers and documents may be available from NVIDIA. If you select a URL that directs you to <http://www.nvidia.com/>, you are then leaving HPE.com. Please follow the instructions on <http://www.nvidia.com/> to download NVIDIA software or documentation. When downloading the NVIDIA software or documentation, you may be subject to NVIDIA terms and conditions, including licensing terms, if any, provided on its website or otherwise. HPE is not responsible for your use of any software or documents that you download from <http://www.nvidia.com/>, except that HPE may provide a limited warranty for NVIDIA software in accordance with the terms and conditions of your purchase of the HPE product or solution.

A list of known issues with this release is available at: <https://docs.nvidia.com/networking/display/connectx6firmwarev20438004its/known-issues>

Prerequisites

FWPKG will work only if the firmware version flashed on the adapter is 20.27.1016 or later and iLO5 firmware version must be 2.30 or higher.

Fixes

No new fixes have been included in version 20.43.8004.

Enhancements

New features and changes included in version 20.43.8004:

- o To align with updated Microsoft UEFI Secure Boot requirements and the upcoming end-of-life of the 2011 Certificate Authority (CA), a transition to the 2023 CA has been done.

Note: When performing a firmware update of ConnectX and BlueField devices the new certificate is required for Secure Boot. To continue supporting Secure Boot, systems must be updated to recognize the "Microsoft Option ROM UEFI CA 2023".

Please also refer to the HPE advisory on Microsoft Windows UEFI CA 2023 certificate update: https://support.hpe.com/hpsc/public/docDisplay?docId=a00156355en_us&docLocale=en_US

Supported Devices and Features

This software package contains the following firmware versions:

NVIDIA VPI Adapter	Firmware Version	PSID
HPE InfiniBand HDR/Ethernet 200Gb 1-port QSP56 PCIe4 x16 MCX653105A-HDAT Adapter (P23664-B21 and P23664-H21)	20.43.8004	MT_0000000451

NVIDIA Firmware Package (FWPKG) for HPE InfiniBand HDR/Ethernet 200Gb 1-port QSP56 PCIe4 x16 OCP3 MCX653435A-HDAI Adapter : HPE part numbers P31323-B21 and P31323-H21

Version: 20.43.8004 (**Recommended**)

Filename: 20_43_8004-MCX653435A-HDA_HPE_Ax.pldm.fwpkg; 20_43_8004-MCX653435A-HDA_HPE_Ax.pldm.json

Important Note!

For PLDM enabled VPI (Virtual Protocol Interconnect) adapters supporting both InfiniBand mode and Ethernet modes, every firmware version is made available in two different formats at HPE.com:

1. HPE signed PLDM Firmware Package (.FWPKG filename extension) updatable via iLO.
2. Firmware binary (.bin filename extension) updatable via mstflint utility from the Operating System.

Choose the appropriate firmware file format based on your preference and what suits your environment.

Disclaimer: Certain software including drivers and documents may be available from NVIDIA. If you select a URL that directs you to <http://www.nvidia.com/>, you are then leaving HPE.com. Please follow the instructions on <http://www.nvidia.com/> to download NVIDIA software or documentation. When downloading the NVIDIA software or documentation, you may be subject to NVIDIA terms and conditions, including licensing terms, if any, provided on its website or otherwise. HPE is not responsible for your use of any software or documents that you download from <http://www.nvidia.com/>, except that HPE may provide a limited warranty for NVIDIA software in accordance with the terms and conditions of your purchase of the HPE product or solution.

A list of known issues with this release is available at: <https://docs.nvidia.com/networking/display/connectx6firmwarev20438004/its-known-issues>

Prerequisites

FWPKG will work only if the firmware version flashed on the adapter is 20.27.1016 or later and iLO5 firmware version must be 2.30 or higher.

Fixes

No new fixes have been included in version 20.43.8004.

Enhancements

New features and changes included in version 20.43.8004:

- o To align with updated Microsoft UEFI Secure Boot requirements and the upcoming end-of-life of the 2011 Certificate Authority (CA), a transition to the 2023 CA has been done.

Note: When performing a firmware update of ConnectX and BlueField devices the new certificate is required for Secure Boot. To continue supporting Secure Boot, systems must be updated to recognize the "Microsoft Option ROM UEFI CA 2023".

Please also refer to the HPE advisory on Microsoft Windows UEFI CA 2023 certificate update: https://support.hpe.com/hpesc/public/docDisplay?docId=a00156355en_us&docLocale=en_US

Supported Devices and Features

This software package contains the following firmware versions:

NVIDIA VPI Adapter	Firmware Version	PSID
HPE InfiniBand HDR/Ethernet 200Gb 1-port QSP56 PCIe4 x16 OCP3 MCX653435A-HDAI Adapter (P31323-B21 and P31323-H21)	20.43.8004	MT_0000000592

NVIDIA Firmware Package (FWPKG) for HPE InfiniBand HDR/Ethernet 200Gb 2-port QSP56 PCIe4 x16 MCX653106A-HDAT Adapter : HPE part numbers P31324-B21 and P31324-H21

Version: 20.43.8004 (**Recommended**)

Filename: 20_43_8004-MCX653106A-HDA_HPE_Ax.pldm.fwpkg; 20_43_8004-MCX653106A-HDA_HPE_Ax.pldm.json

Important Note!

For PLDM enabled VPI (Virtual Protocol Interconnect) adapters supporting both InfiniBand mode and Ethernet modes, every firmware version is made available in two different formats at HPE.com:

1. HPE signed PLDM Firmware Package (.FWPKG filename extension) updatable via iLO.
2. Firmware binary (.bin filename extension) updatable via mstflint utility from the Operating System.

Choose the appropriate firmware file format based on your preference and what suits your environment.

ConnectX-6 VPI supports having one port as InfiniBand and the other port as Ethernet according to the following matrix of combinations.

Port #2 - InfiniBand				
Port #1 - Ethernet	HDR/HDR100	EDR	FDR	QDR
200GbE/50GbE	supported	not supported	not supported	supported
100GbE/25GbE	supported	not supported	not supported	supported
40GbE/10GbE	supported	not supported	not supported	supported

1GbE	supported	not supported	not supported	supported
------	-----------	---------------	---------------	-----------

Port #2 - Ethernet				
Port #1 - InfiniBand	200GbE/50GbE	100GbE/25GbE	40GbE/10GbE	1GbE
HDR / HDR100	supported	supported	not supported	supported
EDR	supported	supported	not supported	supported
FDR	not supported	not supported	not supported	not supported
QDR/SDR	supported	supported	not supported	supported

Disclaimer: Certain software including drivers and documents may be available from NVIDIA. If you select a URL that directs you to <http://www.nvidia.com/>, you are then leaving HPE.com. Please follow the instructions on <http://www.nvidia.com/> to download NVIDIA software or documentation. When downloading the NVIDIA software or documentation, you may be subject to NVIDIA terms and conditions, including licensing terms, if any, provided on its website or otherwise. HPE is not responsible for your use of any software or documents that you download from <http://www.nvidia.com/>, except that HPE may provide a limited warranty for NVIDIA software in accordance with the terms and conditions of your purchase of the HPE product or solution.

A list of known issues with this release is available at: <https://docs.nvidia.com/networking/display/connectx6firmwarev20438004/its/known-issues>

Prerequisites

FWPKG will work only if the firmware version flashed on the adapter is 20.27.1016 or later and iLO5 firmware version must be 2.30 or higher.

Fixes

No new fixes have been included in version 20.43.8004.

Enhancements

New features and changes included in version 20.43.8004:

- To align with updated Microsoft UEFI Secure Boot requirements and the upcoming end-of-life of the 2011 Certificate Authority (CA), a transition to the 2023 CA has been done.

Note: When performing a firmware update of ConnectX and BlueField devices the new certificate is required for Secure Boot. To continue supporting Secure Boot, systems must be updated to recognize the "Microsoft Option ROM UEFI CA 2023".

Please also refer to the HPE advisory on Microsoft Windows UEFI CA 2023 certificate update: https://support.hpe.com/hpsc/public/docDisplay?docId=a00156355en_us&docLocale=en_US

Supported Devices and Features

This software package contains the following firmware versions:

NVIDIA VPI Adapter	Firmware Version	PSID
HPE InfiniBand HDR/Ethernet 200Gb 2-port QSFP56 PCIe4 x16 MCX653106A-HDAT Adapter(P31324-B21 and P31324-H21)	20.43.8004	MT_0000000594

NVIDIA Firmware Package (FWPKG) for HPE InfiniBand HDR/Ethernet 200Gb 2-port QSFP56 PCIe4 x16 OCP3 MCX653436A-HDAI Adapter : HPE part numbers P31348-B21 and P31348-H21

Version: 20.43.8004 **(Recommended)**

Filename: 20_43_8004-MCX653436A-HDA_HPE_Ax.pldm.fwpkg; 20_43_8004-MCX653436A-HDA_HPE_Ax.pldm.json

Important Note!

For PLDM enabled VPI (Virtual Protocol Interconnect) adapters supporting both InfiniBand mode and Ethernet modes, every firmware version is made available in two different formats at HPE.com:

- HPE signed PLDM Firmware Package (.FWPKG filename extension) updatable via iLO.
- Firmware binary (.bin filename extension) updatable via mstflint utility from the Operating System.

Choose the appropriate firmware file format based on your preference and what suits your environment.

ConnectX-6 VPI supports having one port as InfiniBand and the other port as Ethernet according to the following matrix of combinations.

Port #2 - InfiniBand				
Port #1 - Ethernet	HDR/HDR100	EDR	FDR	QDR
200GbE/50GbE	supported	not supported	not supported	supported
100GbE/25GbE	supported	not supported	not supported	supported
40GbE/10GbE	supported	not supported	not supported	supported
1GbE	supported	not supported	not supported	supported

Port #2 - Ethernet				
Port #1 - InfiniBand	200GbE/50GbE	100GbE/25GbE	40GbE/10GbE	1GbE
HDR / HDR100	supported	supported	not supported	supported
EDR	supported	supported	not supported	supported
FDR	not supported	not supported	not supported	not supported
QDR/SDR	supported	supported	not supported	supported

Disclaimer: Certain software including drivers and documents may be available from NVIDIA. If you select a URL that directs you to <http://www.nvidia.com/>, you are then leaving HPE.com. Please follow the instructions on <http://www.nvidia.com/> to download NVIDIA software or documentation. When downloading the NVIDIA software or documentation, you may be subject to NVIDIA terms and conditions, including licensing terms, if any, provided on its website or otherwise. HPE is not responsible for your use of any software or documents that you download from <http://www.nvidia.com/>, except that HPE may provide a limited warranty for NVIDIA software in accordance with the terms and conditions of your purchase of the HPE product or solution.

A list of known issues with this release is available at: <https://docs.nvidia.com/networking/display/connectx6firmwarev20438004/known-issues>

Prerequisites

FWPKG will work only if the firmware version flashed on the adapter is 20.27.1016 or later and iLO5 firmware version must be 2.30 or higher.

Fixes

No new fixes have been included in version 20.43.8004.

Enhancements

New features and changes included in version 20.43.8004:

- o To align with updated Microsoft UEFI Secure Boot requirements and the upcoming end-of-life of the 2011 Certificate Authority (CA), a transition to the 2023 CA has been done.

Note: When performing a firmware update of ConnectX and BlueField devices the new certificate is required for Secure Boot. To continue supporting Secure Boot, systems must be updated to recognize the "Microsoft Option ROM UEFI CA 2023".

Please also refer to the HPE advisory on Microsoft Windows UEFI CA 2023 certificate update: https://support.hpe.com/hpsc/public/docDisplay?docId=a00156355en_us&docLocale=en_US

Supported Devices and Features

This software package contains the following firmware versions:

NVIDIA VPI Adapter	Firmware Version	PSID
HPE InfiniBand HDR/Ethernet 200Gb 2-port QSFP56 PCIe4 x16 OCP3 MCX653436A-HDAI Adapter (P31348-B21 and P31348-H21)	20.43.8004	MT_0000000593

NVIDIA Firmware Package (FWPKG) for HPE InfiniBand HDR100/Ethernet 100Gb 1-port QSFP56 PCIe4 x16 MCX653105A-ECAT Adapter : HPE part numbers P23665-B21 and P23665-H21

Version: 20.43.8004 (**Recommended**)

Filename: 20_43_8004-MCX653105A-ECA_HPE_Ax.pldm.fwpgk; 20_43_8004-MCX653105A-ECA_HPE_Ax.pldm.json

Important Note!

For PLDM enabled VPI (Virtual Protocol Interconnect) adapters supporting both InfiniBand mode and Ethernet modes, every firmware version is made available in two different formats at HPE.com:

1. HPE signed PLDM Firmware Package (.FWPKG filename extension) updatable via iLO.
2. Firmware binary (.bin filename extension) updatable via mstflint utility from the Operating System.

Choose the appropriate firmware file format based on your preference and what suits your environment.

Disclaimer: Certain software including drivers and documents may be available from NVIDIA. If you select a URL that directs you to <http://www.nvidia.com/>, you are then leaving HPE.com. Please follow the instructions on <http://www.nvidia.com/> to download NVIDIA software or documentation. When downloading the NVIDIA software or documentation, you may be subject to NVIDIA terms and conditions, including licensing terms, if any, provided on its website or otherwise. HPE is not responsible for your use of any software or documents that you download from <http://www.nvidia.com/>, except that HPE may provide a limited warranty for NVIDIA software in accordance with the terms and conditions of your purchase of the HPE product or solution.

A list of known issues with this release is available at: <https://docs.nvidia.com/networking/display/connectx6firmwarev20438004/known-issues>

Prerequisites

FWPKG will work only if the firmware version flashed on the adapter is 20.27.1016 or later and iLO5 firmware version must be 2.30 or higher.

Fixes

No new fixes have been included in version 20.43.8004.

Enhancements

New features and changes included in version 20.43.8004:

- To align with updated Microsoft UEFI Secure Boot requirements and the upcoming end-of-life of the 2011 Certificate Authority (CA), a transition to the 2023 CA has been done.

Note: When performing a firmware update of ConnectX and BlueField devices the new certificate is required for Secure Boot. To continue supporting Secure Boot, systems must be updated to recognize the "Microsoft Option ROM UEFI CA 2023".

Please also refer to the HPE advisory on Microsoft Windows UEFI CA 2023 certificate update: https://support.hpe.com/hpsc/public/docDisplay?docId=a00156355en_us&docLocale=en_US

Supported Devices and Features

This software package contains the following firmware versions:

NVIDIA VPI Adapter	Firmware Version	PSID
HPE InfiniBand HDR100/Ethernet 100Gb 1-port QSFP56 PCIe4 x16 MCX653105A-ECAT Adapter (P23665-B21 and P23665-H21)	20.43.8004	MT_0000000452

NVIDIA Firmware Package (FWPKG) for HPE InfiniBand HDR100/Ethernet 100Gb 2-port QSFP56 PCIe4 x16 MCX653106A-ECAT Adapter : HPE part numbers P23666-B21 and P23666-H21

Version: 20.43.8004 **(Recommended)**

Filename: 20_43_8004-MCX653106A-ECA_HPE_Ax.pldm.fwpkg; 20_43_8004-MCX653106A-ECA_HPE_Ax.pldm.json

Important Note!

For PLDM enabled VPI (Virtual Protocol Interconnect) adapters supporting both InfiniBand mode and Ethernet modes, every firmware version is made available in two different formats at HPE.com:

- HPE signed PLDM Firmware Package (.FWPKG filename extension) updatable via iLO.
- Firmware binary (.bin filename extension) updatable via mstflint utility from the Operating System.

Choose the appropriate firmware file format based on your preference and what suits your environment.

ConnectX-6 VPI supports having one port as InfiniBand and the other port as Ethernet according to the following matrix of combinations.

Port #2 - InfiniBand				
Port #1 - Ethernet	HDR/HDR100	EDR	FDR	QDR
50GbE	supported	not supported	not supported	supported
100GbE/25GbE	supported	not supported	not supported	supported
40GbE/10GbE	supported	not supported	not supported	supported
1GbE	supported	not supported	not supported	supported

Port #2 - Ethernet				
Port #1 - InfiniBand	50GbE	100GbE/25GbE	40GbE/10GbE	1GbE
HDR / HDR100	supported	supported	not supported	supported
EDR	supported	supported	not supported	supported
FDR	not supported	not supported	not supported	not supported
QDR/SDR	supported	supported	not supported	supported

Disclaimer: Certain software including drivers and documents may be available from NVIDIA. If you select a URL that directs you to <http://www.nvidia.com/>, you are then leaving HPE.com. Please follow the instructions on <http://www.nvidia.com/> to download NVIDIA software or documentation. When downloading the NVIDIA software or documentation, you may be subject to NVIDIA terms and conditions, including licensing terms, if any, provided on its website or otherwise. HPE is not responsible for your use of any software or documents that you download from <http://www.nvidia.com/>, except that HPE may provide a limited warranty for NVIDIA software in accordance with the terms and conditions of your purchase of the HPE product or solution.

A list of known issues with this release is available at: <https://docs.nvidia.com/networking/display/connectx6firmwarev20438004/known-issues>

Prerequisites

FWPKG will work only if the firmware version flashed on the adapter is 20.27.1016 or later and iLO5 firmware version must be 2.30 or higher.

Fixes

No new fixes have been included in version 20.43.8004.

Enhancements

New features and changes included in version 20.43.8004:

- To align with updated Microsoft UEFI Secure Boot requirements and the upcoming end-of-life of the 2011 Certificate Authority (CA), a transition to the 2023 CA has been done.

Note: When performing a firmware update of ConnectX and BlueField devices the new certificate is required for Secure Boot. To continue supporting Secure Boot, systems must be updated to recognize the "Microsoft Option ROM UEFI CA 2023".

Please also refer to the HPE advisory on Microsoft Windows UEFI CA 2023 certificate update: https://support.hpe.com/hpesc/public/docDisplay?docId=a00156355en_us&docLocale=en_US

Supported Devices and Features

This software package contains the following firmware versions:

NVIDIA VPI Adapter	Firmware Version	PSID
HPE InfiniBand HDR100/Ethernet 100Gb 2-port QSFP56 PCIe4 x16 MCX653106A-ECAT Adapter (P23666-B21 and P23666-H21)	20.43.8004	MT_0000000453

NVIDIA Firmware Package (FWPKG) for HPE InfiniBand NDR200/Ethernet 200Gb 1-port OSFP PCIe5 x16 MCX75310AAS-HEAT Adapter : HPE part numbers P45642-B22 and P45642-H22

Version: 28.49.1014 (Recommended)

Filename: 28_49_1014-MCX75310AAS-HEAT_HPE2_Ax.pldm.fwpkg; 28_49_1014-MCX75310AAS-HEAT_HPE2_Ax.pldm.json

Important Note!

For PLDM enabled VPI (Virtual Protocol Interconnect) adapters supporting both InfiniBand mode and Ethernet modes, every firmware version is made available in two different formats at HPE.com:

- HPE signed PLDM Firmware Package (.FWPKG filename extension) updatable via iLO.
- Firmware binary (.bin filename extension) updatable via mstflint utility from the Operating System.

Choose the appropriate firmware file format based on your preference and what suits your environment.

Disclaimer: Certain software including drivers and documents may be available from NVIDIA. If you select a URL that directs you to <http://www.nvidia.com/>, you are then leaving HPE.com. Please follow the instructions on <http://www.nvidia.com/> to download NVIDIA software or documentation. When downloading the NVIDIA software or documentation, you may be subject to NVIDIA terms and conditions, including licensing terms, if any, provided on its website or otherwise. HPE is not responsible for your use of any software or documents that you download from <http://www.nvidia.com/>, except that HPE may provide a limited warranty for NVIDIA software in accordance with the terms and conditions of your purchase of the HPE product or solution.

A list of known issues with this release is available at: <https://networking-docs.nvidia.com/connectx7fwrn/28.49.1014/known-issues>

Prerequisites

FWPKG will work only if the iLO5 firmware version is 2.30 or higher.

Fixes

The following issues have been fixed in version 28.49.1014:

- NSM Get-Port-Network-Addresses returned an invalid format on B200/B300 HMC. It now follows the documented non-compact format.
- An issue that could prevent the adapter's PCIe link from re-establishing after the host resumed from a deep power-down state. This fix improves the reliability of suspend/resume cycles.
- A DEAD IRISC assert that could occur during TLV NV_DATA flash access by suspending the watchdog while waiting for flash IPC (until timeout), preventing the assert on TLV access.
- An issue where repeatedly writing NVCONFIG TLVs could cause excessive NV_DATA partition swaps during garbage collection. This rapid cycling could accelerate flash wear (end-of-life at 100,000 erases) and potentially render the device inoperable. Firmware now avoids unnecessary physical writes by returning OK when the requested configuration already exists in flash, and increases the maximum supported NV_DATA partition swaps from 100,000 to 200,000.
- ICM_RES_HW_DMFS_ENCAP_H_FW was allocated per GVMI, preventing some RTTs from using it.
- vDPA doorbell resources were not released, which could cause failures when running other functionality after a vDPA FLR. Doorbell resources are now properly unlocked.
- RDMA traffic could stall in large-scale deployments for certain source IP and UDP source-port combinations when DOCA PCC was active and no congestion-control algorithm was configured in algorithm slot 0.
- The live migration target did not receive a port state change event on the resume VHCA command. The target now generates this event so software that depends on port state is notified of any changes.
- A precopy image was processed during the stop-copy phase, causing prolonged downtime due to a software limitation. The handling was slow because the handler performed a linear search for data; this was improved by replacing it with a faster search approach enabled via compile-time preprocessing.
- QPs established before loading DOCA PCC could exhibit inconsistent algorithm-selected behavior between ports in LAG mode after DOCA PCC is loaded.

Enhancements

New features and changes included in version 28.49.1014:

- Added support for Congestion-Control histogram collection in the PCC/ZTR-RTT algorithm. After enabling this capability, customers can read RATE and RTT histogram counters for PCC-managed flows.
- Added a new parameter to the ZTR_RTTCC algorithm to define the probe-packet timeout threshold.
- Added support for a new packet reformat type for PSP transport packets. This reformat removes the PSP trailer and the UDP + PSP transport headers, and updates the IP Protocol field based on the PSP next_header value.

Supported Devices and Features

HPE Part Number	NVIDIA VPI Adapter	PSID
P45642-B22	HPE InfiniBand NDR200/Ethernet 200Gb 1-port OSFP PCIe5 x16 MCX75310AAS-HEAT Adapter (P45642-B22 and P45642-H22)	MT_0000001119

NVIDIA Firmware Package (FWPKG) for Mellanox MCX562A-ACAI Ethernet 10/25Gb 2-port SFP28 OCP3 Adapter for HPE

Version: 16.35.8008 **(Recommended)**

Filename: 16_35_8008-MCX562A-ACA_Ax_Bx.pldm.fwpgk; 16_35_8008-MCX562A-ACA_Ax_Bx.pldm.json

Important Note!

Disclaimer: Certain software including drivers and documents may be available from NVIDIA. If you select a URL that directs you to <http://www.nvidia.com/>, you are then leaving HPE.com. Please follow the instructions on <http://www.nvidia.com/> to download NVIDIA software or documentation. When downloading the NVIDIA software or documentation, you may be subject to NVIDIA terms and conditions, including licensing terms, if any, provided on its website or otherwise. HPE is not responsible for your use of any software or documents that you download from <http://www.nvidia.com/>, except that HPE may provide a limited warranty for NVIDIA software in accordance with the terms and conditions of your purchase of the HPE product or solution.

A list of known issues with this release is available at: <https://networking-docs.nvidia.com/connectx5fwrn/16358008/known-issues>

Prerequisites

FWPKG will work only if the firmware version flashed on the adapter is 16.27.1016 or later and iLO5 firmware version must be 2.30 or higher.

Fixes

No fixes are included in version 16.35.8008.

Enhancements

New features and changes included in version 16.35.8008:

- o To align with updated Microsoft UEFI Secure Boot requirements and the upcoming end-of-life of the 2011 Certificate Authority (CA), a transition to the 2023 CA has been done.

Please also refer to the HPE advisory on Microsoft Windows UEFI CA 2023 certificate update: https://support.hpe.com/hpsc/public/docDisplay?docId=a00156355en_us&docLocale=en_US

Supported Devices and Features

HPE Part Number	NVIDIA Ethernet Only Adapters	PSID
P10112-B21	Mellanox MCX562A-ACAI Ethernet 10/25Gb 2-port SFP28 OCP3 Adapter for HPE	MT_0000000241

NVIDIA Firmware Package (FWPKG) for Mellanox MCX623105AS-VDAT Ethernet 200Gb 1-port QSFP56 Adapter for HPE

Version: 22.49.1014 **(Recommended)**

Filename: 22_49_1014-MCX623105AS-VDA_Ax.pldm.fwpgk; 22_49_1014-MCX623105AS-VDA_Ax.pldm.json

Important Note!

Disclaimer: Certain software including drivers and documents may be available from NVIDIA. If you select a URL that directs you to <http://www.nvidia.com/>, you are then leaving HPE.com. Please follow the instructions on <http://www.nvidia.com/> to download NVIDIA software or documentation. When downloading the NVIDIA software or documentation, you may be subject to NVIDIA terms and conditions, including licensing terms, if any, provided on its website or otherwise. HPE is not responsible for your use of any software or documents that you download from <http://www.nvidia.com/>, except that HPE may provide a limited warranty for NVIDIA software in accordance with the terms and conditions of your purchase of the HPE product or solution.

A list of known issues with this release is available at: <https://networking-docs.nvidia.com/connectx6dxfrn/22.49.1014/known-issues>

Prerequisites

FWPKG will work only if the firmware version flashed on the adapter is 22.27.1016 or later and iLO5 firmware version must be 2.30 or higher.

Fixes

The following issues have been fixed in version 22.49.1014:

- o vDPA doorbell resources were not released causing failures when running other functionality after a vDPA FLR. Doorbell resources are now properly unlocked.
- o Live migration target would not receive a port state change event on the resume VHCA command. The target now generates this event so software that depends on port state is notified of any changes.
- o PCC issue where RDMA traffic would stall at large scale for certain IP and UDP source-port combinations when a PCC user algorithm was active and no CC algorithm was configured in slot 0.

Enhancements

No new features or changes are included in version 22.49.1014.

Supported Devices and Features

HPE Part Number	Mellanox Ethernet Only Adapters	PSID
P10180-B21	Mellanox MCX623105AS-VDAT Ethernet 200Gb 1-port QSFP56 Adapter for HPE	MT_0000000435

NVIDIA Firmware Package (FWPKG) for Mellanox MCX623106AS-CDAT Ethernet 100Gb 2-port QSFP56 Adapter for HPE
Version: 22.49.1014 (**Recommended**)
Filename: 22_49_1014-MCX623106AS-CDA_Ax.pldm.fwpkg; 22_49_1014-MCX623106AS-CDA_Ax.pldm.json

Important Note!

Disclaimer: Certain software including drivers and documents may be available from NVIDIA. If you select a URL that directs you to <http://www.nvidia.com/>, you are then leaving HPE.com. Please follow the instructions on <http://www.nvidia.com/> to download NVIDIA software or documentation. When downloading the NVIDIA software or documentation, you may be subject to NVIDIA terms and conditions, including licensing terms, if any, provided on its website or otherwise. HPE is not responsible for your use of any software or documents that you download from <http://www.nvidia.com/>, except that HPE may provide a limited warranty for NVIDIA software in accordance with the terms and conditions of your purchase of the HPE product or solution.

A list of known issues with this release is available at: <https://networking-docs.nvidia.com/connectx6dxfwrn/22.49.1014/known-issues>

Prerequisites

FWPKG will work only if the firmware version flashed on the adapter is 22.27.1016 or later and iLO5 firmware version must be 2.30 or higher.

Fixes

The following issues have been fixed in version 22.49.1014:

- o vDPA doorbell resources were not released causing failures when running other functionality after a vDPA FLR. Doorbell resources are now properly unlocked.
- o Live migration target would not receive a port state change event on the resume VHCA command. The target now generates this event so software that depends on port state is notified of any changes.
- o PCC issue where RDMA traffic would stall at large scale for certain IP and UDP source-port combinations when a PCC user algorithm was active and no CC algorithm was configured in slot 0.

Enhancements

No new features or changes are included in version 22.49.1014.

Supported Devices and Features

HPE Part Number	NVIDIA Ethernet Only Adapters	PSID
P25960-B21	Mellanox MCX623106AS-CDAT Ethernet 100Gb 2-port QSFP56 Adapter for HPE	MT_0000000437

NVIDIA Firmware Package(FWPKG) for HPE Ethernet 10/25Gb 2-port SFP28 MCX512F-ACHT Adapter
Version: 16.35.8008 (**Recommended**)
Filename: 16_35_8008-MCX512F-ACH_Ax_Bx.pldm.fwpkg; 16_35_8008-MCX512F-ACH_Ax_Bx.pldm.json

Important Note!

Disclaimer: Certain software including drivers and documents may be available from NVIDIA. If you select a URL that directs you to <https://www.nvidia.com/>, you are then leaving HPE.com. Please follow the instructions on <https://www.nvidia.com/> to download NVIDIA software or documentation. When downloading the NVIDIA software or documentation, you may be subject to NVIDIA terms and conditions, including licensing terms, if any, provided on its website or otherwise. HPE is not responsible for your use of any software or documents that you download from <https://www.nvidia.com/>, except that HPE may provide a limited warranty for NVIDIA software in accordance with the terms and conditions of your purchase of the HPE product or solution.

A list of known issues with this release is available at: <https://networking-docs.nvidia.com/connectx5fwrn/16358008/known-issues>

Prerequisites

FWPKG will work only if the firmware version flashed on the adapter is 16.27.1016 or later and iLO5 firmware version must be 2.30 or higher.

Fixes

No fixes are included in version 16.35.8008.

Enhancements

New features and changes included in version 16.35.8008:

- o To align with updated Microsoft UEFI Secure Boot requirements and the upcoming end-of-life of the 2011 Certificate Authority (CA), a transition to the 2023 CA has been done.

Please also refer to the HPE advisory on Microsoft Windows UEFI CA 2023 certificate update: https://support.hpe.com/hpesc/public/docDisplay?docId=a00156355en_us&docLocale=en_US

Supported Devices and Features

HPE Part Number	NVIDIA Ethernet Only Adapters	PSID
P13188-B21	HPE Ethernet 10/25Gb 2-port SFP28 MCX512F-ACHT Adapter	MT_0000000416

Online Firmware Upgrade Utility (ESXi 8.0) for HPE Ethernet 10Gb 2-port 548SFP+ Adapter
Version: 1.0.4 (**Recommended**)
Filename: CP072380.compsig; CP072380.zip

Prerequisites

Use iLO5 firmware version 2.30 or higher with ConnectX4-Lx firmware version 14.32.1010. Thermal sensor reporting on the adapter will not be functional with older versions of iLO5 firmware.

Fixes

No fixes are included in version 14.32.1912.

Enhancements

New features and changes included in version 14.32.1912:

- To align with updated Microsoft UEFI Secure Boot requirements and the upcoming end-of-life of the 2011 Certificate Authority (CA), a transition to the 2023 CA has been done.

Please also refer to the HPE advisory on Microsoft Windows UEFI CA 2023 certificate update: https://support.hpe.com/hpesc/public/docDisplay?docId=a00156355en_us&docLocale=en_US

Supported Devices and Features

HPE Part Number	Mellanox Ethernet Only Adapters	PSID
P11338-B21	HPE Ethernet 10Gb 2-port 548SFP+ Adapter	HPE0000000038

Online Firmware Upgrade Utility (ESXi 8.0) for HPE Mellanox Ethernet only adapters
Version: 1.0.8 (**Recommended**)
Filename: CP072361.compsig; CP072361.zip

Important Note!

The Firmware Upgrade Utility has been split into 2 packages for Mellanox Ethernet Only NIC adapters, one supporting Synergy platforms and the other supporting ProLiant and Apollo platforms. This package supports Mellanox Ethernet Only NIC adapters on ProLiant and Apollo servers.

Prerequisites

Use iLO5 firmware version 2.30 or higher with ConnectX4-Lx/ConnectX5 firmware version 14.32.1010/16.32.1010 (or later) respectively. Thermal sensor reporting on the adapter will not be functional with older versions of iLO5 firmware.

Fixes

No fixes are included in version 14.32.1912.

No fixes are included in version 16.35.8008.

Enhancements

Firmware for the following devices has been updated to 14.32.1912:

- 817749-B21 (HPE Ethernet 25Gb 2-port 640FLR-SFP28 Adapter)
- 817753-B21 (HPE Ethernet 25Gb 2-port 640SFP28 Adapter)

Firmware for the following device has been updated to 16.35.8008:

- 874253-B21 (HPE Ethernet 100Gb 1-port 842QSFP28 Adapter)

New features and changes included in version 14.32.1912:

- To align with updated Microsoft UEFI Secure Boot requirements and the upcoming end-of-life of the 2011 Certificate Authority (CA), a transition to the 2023 CA has been done.

New features and changes included in version 16.35.8008:

- To align with updated Microsoft UEFI Secure Boot requirements and the upcoming end-of-life of the 2011 Certificate Authority (CA), a transition to the 2023 CA has been done.

Please also refer to the HPE advisory on Microsoft Windows UEFI CA 2023 certificate update: https://support.hpe.com/hpesc/public/docDisplay?docId=a00156355en_us&docLocale=en_US

Supported Devices and Features

HPE Part Number	Mellanox Ethernet Only Adapters	PSID
-----------------	---------------------------------	------

817749-B21	HPE Ethernet 25Gb 2-port 640FLR-SFP28 Adapter	HP_2690110034
817753-B21	HPE Ethernet 25Gb 2-port 640SFP28 Adapter	HP_2420110034
874253-B21	HPE Ethernet 100Gb 1-port 842QSFP28 Adapter	HPE0000000014

Online Firmware Upgrade Utility (ESXi 8.0) for HPE Mellanox VPI (Ethernet and Infiniband mode) ConnectX4 and ConnectX5 devices on VMware ESXi 8.0
Version: 1.0.7 **(Recommended)**
Filename: CP072401.compsig; CP072401.zip

Fixes

No fixes are included in version 12.28.4706.

No fixes are included in version 16.35.8008.

Enhancements

Firmware for the following devices has been updated to 12.28.4706:

- o 825110-B21 (HPE InfiniBand EDR/Ethernet 100Gb 1-port 840QSFP28 Adapter)
- o 825111-B21 (HPE InfiniBand EDR/Ethernet 100Gb 2-port 840QSFP28 Adapter)

Firmware for the following devices has been updated to 16.35.8008:

- o 879482-B21 (HPE InfiniBand FDR/Ethernet 40/50Gb 2-port 547FLR-QSFP Adapter)
- o 872726-B21 (HPE InfiniBand EDR/Ethernet 100Gb 2-port 841QSFP28 Adapter)

New features and changes included in version 12.28.4706:

- o To align with updated Microsoft UEFI Secure Boot requirements and the upcoming end-of-life of the 2011 Certificate Authority (CA), a transition to the 2023 CA has been done.

New features and changes included in version 16.35.8008:

- o To align with updated Microsoft UEFI Secure Boot requirements and the upcoming end-of-life of the 2011 Certificate Authority (CA), a transition to the 2023 CA has been done.

Please also refer to the HPE advisory on Microsoft Windows UEFI CA 2023 certificate update: https://support.hpe.com/hpsc/public/docDisplay?docId=a00156355en_us&docLocale=en_US

Supported Devices and Features

HPE Part Number	Device Name	PSID
825110-B21	HPE InfiniBand EDR/Ethernet 100Gb 1-port 840QSFP28 Adapter	HP_2180110032
825111-B21	HPE InfiniBand EDR/Ethernet 100Gb 2-port 840QSFP28 Adapter	HP_2190110032
872726-B21	HPE InfiniBand EDR/Ethernet 100Gb 2-port 841QSFP28 Adapter	HPE0000000009
879482-B21	HPE InfiniBand FDR/Ethernet 40/50Gb 2-port 547FLR-QSFP Adapter	HPE0000000022

Online Firmware Upgrade Utility (ESXi 8.0) for HPE NVIDIA VPI (Ethernet and Infiniband mode) ConnectX6 devices on VMware ESXi 8.0
Version: 1.0.10 **(Recommended)**
Filename: CP071677.compsig; CP071677.zip

Important Note!

ConnectX-6 VPI supports having one port as InfiniBand and the other port as Ethernet according to the following matrix of combinations.

Port #2 - InfiniBand				
Port #1 - Ethernet	HDR/HDR100	EDR	FDR	QDR
200GbE/50GbE	supported	not supported	not supported	supported
100GbE/25GbE	supported	not supported	not supported	supported
40GbE/10GbE	supported	not supported	not supported	supported
1GbE	supported	not supported	not supported	supported

Port #2 - Ethernet				
Port #1 - InfiniBand	200GbE/50GbE	100GbE/25GbE	40GbE/10GbE	1GbE
HDR / HDR100	supported	supported	not supported	supported
EDR	supported	supported	not supported	supported
FDR	not supported	not supported	not supported	not supported
QDR/SDR	supported	supported	not supported	supported

Prerequisites

Use iLO5 firmware version 2.30 or higher with ConnectX6 firmware version 20.32.1010. Thermal sensor reporting on the adapter will not be functional with older versions of iLO5 firmware.

Fixes

No new fixes have been included in version 20.43.8004.

Enhancements

New features and changes included in version 20.43.8004:

- To align with updated Microsoft UEFI Secure Boot requirements and the upcoming end-of-life of the 2011 Certificate Authority (CA), a transition to the 2023 CA has been done. To ensure successful loading of the Expansion ROM (ExpROM) during the UEFI Secure Boot process, system BIOS and operating system trust stores must be updated to include the 2023 CA.

Note: When performing a firmware update of ConnectX and BlueField devices the new certificate is required for Secure Boot. To continue supporting Secure Boot, systems must be updated to recognize the "Microsoft Option ROM UEFI CA 2023".

Supported Devices and Features

HPE Part Number	Device Name	PSID
P06154-B21	HPE InfiniBand HDR/Ethernet 200Gb 1-port QSFP56 PCIe3 x16 MCX653105A-HDAT Adapter	HPE0000000034
P06250-B21	HPE InfiniBand HDR100/Ethernet 100Gb 1-port QSFP56 PCIe3 x16 MCX653105A-ECAT Adapter	HPE0000000035
P06251-B21	HPE InfiniBand HDR100/Ethernet 100Gb 2-port QSFP56 PCIe3 x16 MCX653106A-ECAT Adapter	HPE0000000036

Online Firmware Upgrade Utility (ESXi 8.0) for Mellanox Open Ethernet cards

Version: 1.0.8 (**Recommended**)

Filename: CP072375.comsig; CP072375.zip

Important Note!

On Adapter Firmware rewrite scenario, SUM will always discover the Mellanox Open adapter firmware smart component as applicable and select it for deployment If the server iLO5 firmware version is older than 2.30.

Prerequisites

Use iLO5 firmware version 2.30 or higher with ConnectX4-Lx/ConnectX5 firmware version 14.32.1010/16.32.1010 respectively. Thermal sensor reporting on the adapter will not be functional with older versions of iLO5 firmware.

Fixes

No fixes are included in version 14.32.1912.

No fixes are included in version 16.35.8008.

Enhancements

Firmware for the following devices has been updated to 14.32.1912:

- P21930-B21 (HPE Ethernet 10Gb 2-port SFP+ MCX4121A-XCAT Adapter)
- P11341-B21 (HPE Ethernet 10Gb 2-port SFP+ MCX4621A-ACAB OCP3 Adapter)

Firmware for the following device has been updated to 16.35.8008:

- P21927-B21 (HPE Ethernet 100Gb 2-Port QSFP28 MCX516A-CCHT Adapter)

New features and changes included in version 14.32.1912:

- To align with updated Microsoft UEFI Secure Boot requirements and the upcoming end-of-life of the 2011 Certificate Authority (CA), a transition to the 2023 CA has been done.

New features and changes included in version 16.35.8008:

- To align with updated Microsoft UEFI Secure Boot requirements and the upcoming end-of-life of the 2011 Certificate Authority (CA), a transition to the 2023 CA has been done.

Please also refer to the HPE advisory on Microsoft Windows UEFI CA 2023 certificate update: https://support.hpe.com/hpesc/public/docDisplay?docId=a00156355en_us&docLocale=en_US

Supported Devices and Features

HPE Part Number	Mellanox Ethernet Only Adapters	PSID
P21930-B21	HPE Ethernet 10Gb 2-port SFP+ MCX4121A-XCHT Adapter	MT_0000000414
P11341-B21	HPE Ethernet 10Gb/25Gb 2-port SFP28 MCX4621A-ACAB OCP3 Adapter	MT_0000000238
P21927-B21	HPE Ethernet 100Gb 2-port QSFP28 MCX516A-CCHT Adapter	MT_0000000417

Firmware - Storage Controller

[Top](#)

Controller Firmware Flash for ESXi8.0 and 9.0 - HPE MR216i-a Gen10 Plus Tri Mode Controller
Version: 52.26.3.5487 (C) **(Recommended)**
Filename: CP070859.compsig; CP070859.zip

Enhancements

- o ESXi9.1 support.

Controller Firmware Flash for ESXi8.0 and 9.0 - HPE MR216i-p Gen10 Plus Tri Mode Controller
Version: 52.26.3.5487 (C) **(Recommended)**
Filename: CP070860.compsig; CP070860.zip

Enhancements

- o ESXi9.1 support.

Controller Firmware Flash for ESXi8.0 and 9.0 - HPE MR416i-a Gen10 Plus Tri Mode Controller
Version: 52.26.3.5487 (C) **(Recommended)**
Filename: CP070861.compsig; CP070861.zip

Enhancements

- o ESXi9.1 support.

Controller Firmware Flash for ESXi8.0 and 9.0 - HPE MR416i-p Gen10 Plus Tri Mode Controller
Version: 52.26.3.5487 (C) **(Recommended)**
Filename: CP070862.compsig; CP070862.zip

Enhancements

- o ESXi9.1 support.

Firmware Package - HPE Smart Array P408i-p, P408e-p, P408i-a, P408i-c, E208i-p, E208e-p, E208i-c, E208i-a, P204i-c, P416ie-m and P816i-a SR Gen10 and SR308i-o, SR308i-p Gen11 controllers
Version: 8.23 **(Recommended)**
Filename: HPE_SR_Gen10_8.23_A.fwpkg

Important Note!

- o HPE Service Pack for ProLiant (SPP) provides a fully qualified recipe for specific firmware and drivers released within the same cycle, making it the primary recommended choice.
- o It is strongly recommended to use controller firmware version 8.23 for SR SAS/SATA controllers and firmware version 03.01.47.052 for SR tri-mode controllers, along with Windows 2022/2025 driver version 1016.38.0.1003, Linux driver version 2.1.40-020, and VMware ESXi driver
- o **For Windows 2016 driver, please use 1010.84.0.1012 in below link:**
<https://www.hpe.com/global/swpublishing/MTX-c523e081ab344bc4b4bc9d5686>
- o **For Windows 2019 driver, please use 1016.10.0.1004 in below link:**
<https://www.hpe.com/global/swpublishing/MTX-29e86213c3ab4e94b0b54906f7>

Fixes

- o Fixed an issue where the system could lock up with controller lockup code 0x27006 during heavy I/O when a drive reported a predictive failure, by ensuring failure handling does not block critical system monitoring operations.
- o Fixed an issue where volume creation could fail when using mixed OPAL V1 and OPAL V2 self-encrypting drives (SEDs), ensuring consistent validation and successful configuration.
- o Fixed an issue that could cause reduced 4K random write performance in degraded RAID 60 configurations.
- o Fixed an issue where the system could crash when hot-adding drives to failed RAID 50/60 volumes, improving stability during recovery operations.
- o Fixed an issue where CBE remote encryption could remain enabled after being disabled in UEFI HII, ensuring settings are applied correctly.
- o Fixed an issue where the system could fail to boot during device discovery due to invalid device identification data, improving boot reliability.
- o Fixed an issue where encryption key mismatches could occur during master key updates, ensuring consistent and reliable encryption operations.
- o Fixed an issue where a drive could be incorrectly marked as failed during boot when a sanitize operation was in progress, preventing false drive failures.
- o Fixed an issue where secure erase operations using ATA passthrough could fail to start, ensuring successful execution of secure erase commands.
- o Fixed an issue where sanitize operations did not resume after a controller reboot, ensuring proper continuation of secure erase processes.
- o Added support to display drive depopulation and restoration status in UEFI HII, providing better visibility into ongoing drive operations.
- o Added support to display the remaining duration of array drive identification in UEFI HII, improving visibility into ongoing LED identification activity.

Adding the CA detail as below:

- o For E208e-p A new Microsoft Option ROM UEFI CA 2023 certificate has been added to replace the expired CA 2011 one. To prevent Secure Boot issues, please update BIOS and "Reset All Keys to Platform Defaults" following the instructions in Advisory: (Revision) Microsoft Windows - Information About Windows UEFI CA 2023 Certificate

CA: https://support.hpe.com/hpesc/public/docDisplay?docId=emr_na-a00157968en_us

Enhancements

- o Added HDD Power-On Hours reporting based on the PowerOnHours property in Drive Metrics, with periodic updates to improve drive usage visibility and indicate whether the attribute is supported by the drive.

Firmware Package - HPE Gen12 Boot Controller NS204i-u, HPE Gen11 Boot Controller NS204i-u, NS204i-d and HPE Gen10 Plus Boot Controller NS204i-p, NS204i-d, NS204i-t, NS204i-r
Version: 1.2.14.1031 **(Recommended)**

Important Note!

1.2.14.1018 is the minimum firmware requirement for AMD Turin DL365/385 and Intel Gen12 platforms. Downgrading NS204i firmware to version lower than 1018 will lead to MCTP failure.

- <https://www.hpe.com/global/swpublishing/MTX-c75706b8a59d4d8aabc4e4cc30>

For Gen10 plus server users, the NS204i firmware has to be 1.2.14.1018 or later in order to enable PLDM firmware update functionality for the controller. Please find the smart component versions of 1.2.14.1018 in below link:

- Windows: <https://www.hpe.com/global/swpublishing/MTX-84a4e0bb354f48ead65cf9451>
- Linux: <https://www.hpe.com/global/swpublishing/MTX-b6448d485ca64fd7a5d0d5f75e>
- VMware: <https://www.hpe.com/global/swpublishing/MTX-ad49b1acb0d4455c86460c727a>

Prerequisites

- iLO 6 version 1.10 or later is required for Gen11 and Gen12 servers.
- iLO 5 version 2.81 or later is required for Gen10/Gen10 Plus servers

Enhancements

- Aligning OCP specification to enhance stability with particular SSDs.

Firmware Package - HPE MR216i-a Gen10 Plus Tri Mode Controller

Version: 52.36.3-6584 (**Recommended**)

Filename: HPE_MR216i-a_Gen10P_52.36.3-6584_A.fwpkg; HPE_MR216i-a_Gen10P_52.36.3-6584_A.json

Important Note!

- This firmware version to be used on HPE MR216i-a Gen10 Plus Controller.
- The minimum iLO versions required to support 52.36.3-6584 are iLO 7 1.20, iLO 6 1.74, and iLO 5 3.18.

Prerequisites

iLO5 version should be at least 2.98 is required for **chassis&Fabric support**.

Fixes

- Fix an issue that Backup Exec doesn't work with LTO drives in Linux systems
- Fix a rare issue that controller VM fails to bootup after a host reboot on Linux hypervisor
- Fix an issue that poor performance is observed during small-range writes
- Fix an issue that storcli show /cx/ex/sx poh (power on hour) command report error on NVMe drives
- Fix a rare issue that PL fault 0x4318 is observed during the IPMI power-cycle test
- Fix a rare issue that cache restore failure observed after firmware update followed by a server UMCE (unrecoverable machine check error)
- Fix an issue that firmware may assert when NVME drives take long time for Task Management
- Fix a rare issue that PL fault 0x6054 observed during patrol read in progress
- Fix a rare issue that firmware may assert during firmware update with IOs and task managements on JBOD drives.
- Fix an issue that foreign drive is shown in HotspareType@Redfish.AllowableValues
- Fix an issue that SATA LFF drives list the "DriveFormFactor" as "2_5" under the Storage tab and in Redfish
- Fix an issue that Server health shows Warning when a degraded volume is present
- Fix a rare issue that GET operation on Redfish Drive URI occasionally return 404 Not Found
- Fix an issue that rebuild does not start on an SED drive when inserted in the missing slot of a R1 drive
- Fix an issue that NVME drive undergoing sanitize is not detected after server reboot
- Fix a rare issue that Redfish Chassis properties are not properly displayed for UBM10 backplane
- Fix an issue that PCIconfiglink page events may come continuously in snapdump log
- Fix a rare issue that firmware may assert when user starts crypto erase and removed the drive
- Fix an issue that the sanitize percentage does not progress when monitoring drive's sanitize state
- Fix a rare issue that PLDM Fault 0x5: Command abort failed observed when doing backplane firmware update
- Fix a rare firmware crash that may occur during concurrent Virtual Machine clone operations and JBOD creation
- Fix an issue that firmware may assert if drive goes through shield recovery and is subsequently removed
- Fix a rare issue that firmware may assert while running IO's and Task Management

Enhancements

- Add additional escape sequences for special characters when encoding BEJString to comply with the DMTF specification. iLO 7 1.20, iLO6 1.74 and iLO5 3.18 are required to support this change.
- DMTF PLDM Redfish Device Enablement enhancements
 - Add support for Redfish Conditions (GET)
 - Each resource contains a conditions table that lists the appropriate MessageId and MessageSeverity. Redfish messages impact the Redfish

resource Status object. Any outstanding message will appear in the Redfish Status[Conditions] array. The highest Status[Conditions][Severity] sets the overall Status[Health] of the resource. When the Status[Conditions] array is empty the Status[Health] shall be OK.

- Port Conditions do not display any condition other than OK
- In scenarios where ControllerPreviousError condition happens, the same is listed under StorageController.Status. Usually after iLO acknowledges ControllerPreviousError event, FW clears the condition from the StorageController.Status.Conditions[] list.
- Redfish Metrics GET Support for DriveMetrics, EnvironmentMetrics and VolumeMetrics
 - DriveMetrics: BadBlockCount, ReadIOPiBytes, WriteIOPiBytes, PowerOnHours, NVMeSMART (MVMESMART attributes are supported for NVMe drive only)
 - EnvironmentMetrics for Drive Resource: TemperatureCelsius.Reading
 - VolumeMetrics: ConsistencyCheckCount, ConsistencyCheckErrorCount, RebuildErrorCount
 - Each counter can hold a value up to 65535. Once the counter reaches the maximum value the value is not reset.
 - Metrics are cleared when user performs Controller NVRAM clear or Redfish ResetToDefaults.ResetAll.
- Add support for Redfish Parallel Resource PDR. The feature reduce iLO resource required to support controller related Metrics.
- Add support for UBM11 backplane
- Enhanced the UBM backplane firmware update process to eliminate the risk of firmware corruption when transferred data becomes corrupted
- Refine the message on HII prereview configuration for the foreign import
- Removed the Sanitize Secure Erase option from MRSA for SED drives, as SEDs support only Cryptographic Erase
- Return error when enabling encryption with 256 characters in the "EncryptionKeyIdentifier" property through Redfish

Firmware Package - HPE MR216i-p Gen10 Plus Tri Mode Controller

Version: 52.36.3-6584 **(Recommended)**

Filename: HPE_MR216i-p_Gen10P_52.36.3-6584_A.fwpkg; HPE_MR216i-p_Gen10P_52.36.3-6584_A.json

Important Note!

- This firmware version to be used on HPE MR216i-p Gen10 Plus Controller.
- The minimum iLO versions required to support 52.36.3-6584 are iLO 7 1.20, iLO 6 1.74, and iLO 5 3.18.

Prerequisites

iLO5 version should be at least 2.98 is required for **chassis&Fabric support**.

Fixes

- Fix an issue that Backup Exec doesn't work with LTO drives in Linux systems
- Fix a rare issue that controller VM fails to bootup after a host reboot on Linux hypervisor
- Fix an issue that poor performance is observed during small-range writes
- Fix an issue that storcli show /cx/ex/sx poh (power on hour) command report error on NVMe drives
- Fix a rare issue that PL fault 0x4318 is observed during the IPMI power-cycle test
- Fix a rare issue that cache restore failure observed after firmware update followed by a server UMCE (unrecoverable machine check error)
- Fix an issue that firmware may assert when NVMe drives take long time for Task Management
- Fix a rare issue that PL fault 0x6054 observed during patrol read in progress
- Fix a rare issue that firmware may assert during firmware update with IOs and task managements on JBOD drives.
- Fix an issue that foreign drive is shown in HotspareType@Redfish.AllowableValues
- Fix an issue that SATA LFF drives list the "DriveFormFactor" as "2_5" under the Storage tab and in Redfish
- Fix an issue that Server health shows Warning when a degraded volume is present
- Fix a rare issue that GET operation on Redfish Drive URI occasionally return 404 Not Found
- Fix an issue that rebuild does not start on an SED drive when inserted in the missing slot of a R1 drive
- Fix an issue that NVMe drive undergoing sanitize is not detected after server reboot
- Fix a rare issue that Redfish Chassis properties are not properly displayed for UBM10 backplane
- Fix an issue that PCIconfiglink page events may come continuously in snapdump log
- Fix a rare issue that firmware may assert when user starts crypto erase and removed the drive
- Fix an issue that the sanitize percentage does not progress when monitoring drive's sanitize state
- Fix a rare issue that PLDM Fault 0x5: Command abort failed observed when doing backplane firmware update
- Fix a rare firmware crash that may occur during concurrent Virtual Machine clone operations and JBOD creation
- Fix an issue that firmware may assert if drive goes through shield recovery and is subsequently removed
- Fix a rare issue that firmware may assert while running IO's and Task Management

Enhancements

- Add additional escape sequences for special characters when encoding BEJString to comply with the DMTF specification. iLO 7 1.20, iLO6 1.74 and iLO5 3.18 are required to support this change.
- DMTF PLDM Redfish Device Enablement enhancements
 - Add support for Redfish Conditions (GET)

- Each resource contains a conditions table that lists the appropriate MessageId and MessageSeverity. Redfish messages impact the Redfish resource Status object. Any outstanding message will appear in the Redfish Status[Conditions] array. The highest Status[Conditions][Severity] sets the overall Status[Health] of the resource. When the Status[Conditions] array is empty the Status[Health] shall be OK.
- Port Conditions do not display any condition other than OK
- In scenarios where ControllerPreviousError condition happens, the same is listed under StorageController.Status. Usually after iLO acknowledges ControllerPreviousError event, FW clears the condition from the StorageController.Status.Conditions[] list.
- Redfish Metrics GET Support for DriveMetrics, EnvironmentMetrics and VolumeMetrics
 - DriveMetrics: BadBlockCount, ReadIOPiBytes, WriteIOPiBytes, PowerOnHours, NVMeSMART (MVeSMART attributes are supported for NVMe drive only)
 - EnvironmentMetrics for Drive Resource: TemperatureCelsius.Reading
 - VolumeMetrics: ConsistencyCheckCount, ConsistencyCheckErrorCount, RebuildErrorCount
 - Each counter can hold a value up to 65535. Once the counter reaches the maximum value the value is not reset.
 - Metrics are cleared when user performs Controller NVRAM clear or Redfish ResetToDefaults.ResetAll.
- Add support for Redfish Parallel Resource PDR. The feature reduce iLO resource required to support controller related Metrics.
- Add support for UBM11 backplane
- Enhanced the UBM backplane firmware update process to eliminate the risk of firmware corruption when transferred data becomes corrupted
- Refine the message on HII prereview configuration for the foreign import
- Removed the Sanitize Secure Erase option from MRSA for SED drives, as SEDs support only Cryptographic Erase
- Return error when enabling encryption with 256 characters in the "EncryptionKeyIdentifier" property through Redfish

Firmware Package - HPE MR416i-a Gen10 Plus Tri Mode Controller

Version: 52.36.3-6584 (**Recommended**)

Filename: HPE_MR416i-a_Gen10P_52.36.3-6584_A.fwpkg; HPE_MR416i-a_Gen10P_52.36.3-6584_A.json

Important Note!

- This firmware version to be used on HPE MR416i-a Gen10 Plus Controller.
- The minimum iLO versions required to support 52.36.3-6584 are iLO 7 1.20, iLO 6 1.74, and iLO 5 3.18.

Prerequisites

iLO5 version should be at least 2.98 is required for **chassis&Fabric support**.

Fixes

- Fix an issue that Backup Exec doesn't work with LTO drives in Linux systems
- Fix a rare issue that controller VM fails to bootup after a host reboot on Linux hypervisor
- Fix an issue that poor performance is observed during small-range writes
- Fix an issue that storcli show /cx/ex/sx poh (power on hour) command report error on NVMe drives
- Fix a rare issue that PL fault 0x4318 is observed during the IPMI power-cycle test
- Fix a rare issue that cache restore failure observed after firmware update followed by a server UMCE (unrecoverable machine check error)
- Fix an issue that firmware may assert when NVME drives take long time for Task Management
- Fix a rare issue that PL fault 0x6054 observed during patrol read in progress
- Fix a rare issue that firmware may assert during firmware update with IOs and task managements on JBOD drives.
- Fix an issue that foreign drive is shown in HotspareType@Redfish.AllowableValues
- Fix an issue that SATA LFF drives list the "DriveFormFactor" as "2_5" under the Storage tab and in Redfish
- Fix an issue that Server health shows Warning when a degraded volume is present
- Fix a rare issue that GET operation on Redfish Drive URI occasionally return 404 Not Found
- Fix an issue that rebuild does not start on an SED drive when inserted in the missing slot of a R1 drive
- Fix an issue that NVME drive undergoing sanitize is not detected after server reboot
- Fix a rare issue that Redfish Chassis properties are not properly displayed for UBM10 backplane
- Fix an issue that PCIconfiglink page events may come continuously in snapdump log
- Fix a rare issue that firmware may assert when user starts crypto erase and removed the drive
- Fix an issue that the sanitize percentage does not progress when monitoring drive's sanitize state
- Fix a rare issue that PLDM Fault 0x5: Command abort failed observed when doing backplane firmware update
- Fix a rare firmware crash that may occur during concurrent Virtual Machine clone operations and JBOD creation
- Fix an issue that firmware may assert if drive goes through shield recovery and is subsequently removed
- Fix a rare issue that firmware may assert while running IO's and Task Management

Enhancements

- Add additional escape sequences for special characters when encoding BEJString to comply with the DMTF specification. iLO 7 1.20, iLO6 1.74 and iLO5 3.18 are required to support this change.
- DMTF PLDM Redfish Device Enablement enhancements

- Add support for Redfish Conditions (GET)
 - Each resource contains a conditions table that lists the appropriate MessageId and MessageSeverity. Redfish messages impact the Redfish resource Status object. Any outstanding message will appear in the Redfish Status[Conditions] array. The highest Status[Conditions][Severity] sets the overall Status[Health] of the resource. When the Status[Conditions] array is empty the Status[Health] shall be OK.
 - Port Conditions do not display any condition other than OK
 - In scenarios where ControllerPreviousError condition happens, the same is listed under StorageController.Status. Usually after iLO acknowledges ControllerPreviousError event, FW clears the condition from the StorageController.Status.Conditions[] list.
- Redfish Metrics GET Support for DriveMetrics, EnvironmentMetrics and VolumeMetrics
 - DriveMetrics: BadBlockCount, ReadIOPKiBytes, WriteIOPKiBytes, PowerOnHours, NVMeSMART (MVMesSMART attributes are supported for NVMe drive only)
 - EnvironmentMetrics for Drive Resource: TemperatureCelsius.Reading
 - VolumeMetrics: ConsistencyCheckCount, ConsistencyCheckErrorCount, RebuildErrorCount
 - Each counter can hold a value up to 65535. Once the counter reaches the maximum value the value is not reset.
 - Metrics are cleared when user performs Controller NVRAM clear or Redfish ResetToDefaults.ResetAll.
- Add support for Redfish Parallel Resource PDR. The feature reduce iLO resource required to support controller related Metrics.
- Add support for UBM11 backplane
- Enhanced the UBM backplane firmware update process to eliminate the risk of firmware corruption when transferred data becomes corrupted
- Refine the message on HII prereview configuration for the foreign import
- Removed the Sanitize Secure Erase option from MRSA for SED drives, as SEDs support only Cryptographic Erase
- Return error when enabling encryption with 256 characters in the "EncryptionKeyIdentifier" property through Redfish

Firmware Package - HPE MR416i-p Gen10 Plus Tri Mode Controller

Version: 52.36.3-6584 (**Recommended**)

Filename: HPE_MR416i-p_Gen10P_52.36.3-6584_A.fwpkg; HPE_MR416i-p_Gen10P_52.36.3-6584_A.json

Important Note!

- This firmware version to be used on HPE MR416i-p Gen10 Plus Controller.
- The minimum iLO versions required to support 52.36.3-6584 are iLO 7 1.20, iLO 6 1.74, and iLO 5 3.18.

Prerequisites

iLO5 version should be at least 2.98 is required for **chassis&Fabric support**.

Fixes

- Fix an issue that Backup Exec doesn't work with LTO drives in Linux systems
- Fix a rare issue that controller VM fails to bootup after a host reboot on Linux hypervisor
- Fix an issue that poor performance is observed during small-range writes
- Fix an issue that storcli show /cx/ex/sx poh (power on hour) command report error on NVMe drives
- Fix a rare issue that PL fault 0x4318 is observed during the IPMI power-cycle test
- Fix a rare issue that cache restore failure observed after firmware update followed by a server UMCE (unrecoverable machine check error)
- Fix an issue that firmware may assert when NVMe drives take long time for Task Management
- Fix a rare issue that PL fault 0x6054 observed during patrol read in progress
- Fix a rare issue that firmware may assert during firmware update with IOs and task managements on JBOD drives.
- Fix an issue that foreign drive is shown in HotspareType@Redfish.AllowableValues
- Fix an issue that SATA LFF drives list the "DriveFormFactor" as "2_5" under the Storage tab and in Redfish
- Fix an issue that Server health shows Warning when a degraded volume is present
- Fix a rare issue that GET operation on Redfish Drive URI occasionally return 404 Not Found
- Fix an issue that rebuild does not start on an SED drive when inserted in the missing slot of a R1 drive
- Fix an issue that NVMe drive undergoing sanitize is not detected after server reboot
- Fix a rare issue that Redfish Chassis properties are not properly displayed for UBM10 backplane
- Fix an issue that PCIconfiglink page events may come continuously in snapdump log
- Fix a rare issue that firmware may assert when user starts crypto erase and removed the drive
- Fix an issue that the sanitize percentage does not progress when monitoring drive's sanitize state
- Fix a rare issue that PLDM Fault 0x5: Command abort failed observed when doing backplane firmware update
- Fix a rare firmware crash that may occur during concurrent Virtual Machine clone operations and JBOD creation
- Fix an issue that firmware may assert if drive goes through shield recovery and is subsequently removed
- Fix a rare issue that firmware may assert while running IO's and Task Management

Enhancements

- Add additional escape sequences for special characters when encoding BEJString to comply with the DMTF specification. iLO 7 1.20, iLO6 1.74 and iLO5 3.18 are required to support this change.

- DMTF PLDM Redfish Device Enablement enhancements
 - Add support for Redfish Conditions (GET)
 - Each resource contains a conditions table that lists the appropriate MessageId and MessageSeverity. Redfish messages impact the Redfish resource Status object. Any outstanding message will appear in the Redfish Status[Conditions] array. The highest Status[Conditions][Severity] sets the overall Status[Health] of the resource. When the Status[Conditions] array is empty the Status[Health] shall be OK.
 - Port Conditions do not display any condition other than OK
 - In scenarios where ControllerPreviousError condition happens, the same is listed under StorageController.Status. Usually after iLO acknowledges ControllerPreviousError event, FW clears the condition from the StorageController.Status.Conditions[] list.
 - Redfish Metrics GET Support for DriveMetrics, EnvironmentMetrics and VolumeMetrics
 - DriveMetrics: BadBlockCount, ReadIOPKiBytes, WriteIOPKiBytes, PowerOnHours, NVMeSMART (MVMESMART attributes are supported for NVMe drive only)
 - EnvironmentMetrics for Drive Resource: TemperatureCelsius.Reading
 - VolumeMetrics: ConsistencyCheckCount, ConsistencyCheckErrorCount, RebuildErrorCount
 - Each counter can hold a value up to 65535. Once the counter reaches the maximum value the value is not reset.
 - Metrics are cleared when user performs Controller NVRAM clear or Redfish ResetToDefaults.ResetAll.
- Add support for Redfish Parallel Resource PDR. The feature reduce iLO resource required to support controller related Metrics.
- Add support for UBM11 backplane
- Enhanced the UBM backplane firmware update process to eliminate the risk of firmware corruption when transferred data becomes corrupted
- Refine the message on HII prereview configuration for the foreign import
- Removed the Sanitize Secure Erase option from MRSA for SED drives, as SEDs support only Cryptographic Erase
- Return error when enabling encryption with 256 characters in the "EncryptionKeyIdentifier" property through Redfish

Firmware Package - HPE SR932i-p Gen10 Plus /SR416i-a Gen10 Plus/SR932i-p Gen11/SR416ie-m Gen11 Controllers
 Version: 03.01.47.052 (**Recommended**)
 Filename: HPE_SR416_SR932_Gen10P_Gen11_03.01.47.052_A.fwpgk

Important Note!

- HPE Service Pack for ProLiant (SPP) provides a fully qualified recipe for specific firmware and drivers released within the same cycle, making it the primary recommended choice.
- It is strongly recommended to use controller firmware version 8.23 for SR SAS/SATA controllers and firmware version 03.01.47.052 for SR tri-mode controllers, along with Windows 2022/2025 driver version 1016.38.0.1003, Linux driver version 2.1.40-020, and VMware ESXi driver version 80.4902.0.103/90.4902.0.103, as this combination has been fully qualified.
- For Windows 2016 driver, please use 1010.84.0.1012 in below link:**
<https://www.hpe.com/global/swpublishing/MTX-c523e081ab344bc4b4bc9d5686>
- For Windows 2019 driver, please use 1016.10.0.1004 in below link:**
<https://www.hpe.com/global/swpublishing/MTX-29e86213c3ab4e94b0b54906f7>

Fixes

- Fixed an issue where logical drives could become stuck in a queued state after deleting an in-progress RPI operation, ensuring pending operations resume correctly.
- Fixed an issue to improve RAID 6 migration reliability, ensuring volumes remain operational even if two drives are removed during migration.
- Fixed an issue where the system could lock up with controller lockup code 0x27006 during heavy I/O when a drive reported a predictive failure, by ensuring failure handling does not block critical system monitoring operations.
- Fixed an issue where volume creation could fail when using mixed OPAL V1 and OPAL V2 self-encrypting drives (SEDs), ensuring consistent validation and successful configuration.
- Fixed an issue that could cause reduced 4K random write performance in degraded RAID 60 configurations.
- Fixed an issue where a drive could be incorrectly marked as failed during boot while a sanitize operation was in progress, preventing unintended drive failures during initialization.
- Fixed an issue where the system could crash when hot-adding drives to failed RAID 50/60 volumes, improving stability during recovery operations.
- Fixed an issue where CBE remote encryption could remain enabled after being disabled in UEFI HII, ensuring settings are applied correctly.
- Fixed an issue where the system could fail to boot during device discovery due to invalid device identification data, improving boot reliability.
- Fixed an issue where encryption key mismatches could occur during master key updates, ensuring consistent and reliable encryption operations.
- Fixed an issue where repeated LUN reset requests to NVMe drives could cause a controller lockup with code 0x1ABD, ensuring stable handling of reset operations.
- Fixed an issue where RPI operations could take longer than expected on certain HPE drives, improving performance consistency.

Adding the CA notes as below:

- A new Microsoft Option ROM UEFI CA 2023 certificate has been added to replace the expired CA 2011 one. To prevent Secure Boot issues, please update BIOS and "Reset All Keys to Platform Defaults" following the instructions in Advisory: (Revision) Microsoft Windows - Information About Windows UEFI CA 2023 Certificate.
https://support.hpe.com/hpesc/public/docDisplay?docId=a00156355en_us

Enhancements

- Added HDD Power-On Hours reporting based on the PowerOnHours property in Drive Metrics, with periodic updates to improve drive usage visibility and indicate whether the attribute is supported by the drive.
- Added support to display drive depopulation and restoration status in UEFI HII, providing better visibility into ongoing drive operations.
- Added support to display the remaining duration of array drive identification in UEFI HII, improving visibility into ongoing LED identification activity.
- Enhanced management of drives undergoing depopulation or restoration operations:
 - Drives are reported as StandbyOffline during these operations
 - System generates Redfish alerts when operations start (DriveOffline) and complete (DriveOfflineCleared)

- o Certain operations (e.g., firmware update, secure erase, configuration changes) are temporarily blocked
- o Management interfaces (Redfish/PLDM) provide consistent status and controlled responses

HPE D3600/D3700/D3610/D3710 12Gb SAS Disk Enclosure ROM Flash Component for VMware (ESXi)

Version: 5.04 (P) **(Recommended)**

Filename: CP072199.compsig; CP072199.md5; CP072199.zip

Important Note!

IMPORTANT: Firmware updates must be performed during a system maintenance window, with all I/O to the system halted. In single domain configuration, if user hosts an OS in D3000(or any storage box) and flash the SEPs, it will hang/crash everytime as SmartComponent will reset the SEPs after flash/codeload.

WARNING! Do not power cycle or restart during the firmware update as this can result in loss of capabilities for this unit. It typically takes several minutes for the firmware to load.

NOTE: All firmware flash progress messages are logged to /var/cpq/D3000.log and flash summary is logged to /var/cpq/Component.log.

Prerequisites

IMPORTANT: Firmware updates must be performed during a system maintenance window, with all I/O to the system halted.

WARNING! Do not power cycle or restart during the firmware update as this can result in loss of capabilities for this unit. It typically takes several minutes for the firmware to load.

NOTE: All firmware flash progress messages are logged to /var/cpq/D3000.log and flash summary is logged to /var/cpq/Component.log.

Fixes

The following fixes were incorporated in this version:

- o The Enabled-ClusterS2D command now completes successfully when executed on a SATA drive within a D3610 disk enclosure for a NonStop solution.
- o The smart carrier, which is the drive case for SAS drives, now authenticates in the D3610/D3710 drive enclosure.
- o Added new 7-segment error codes E0 and E1 to report issues with Fan modules A and B, respectively. These new codes only apply to the D3610/D3710 and only display when running firmware 5.04.
- o If the storage enclosure processor within the I/O module fails, a hard reset (power down and then power up) is executed to ensure the processor comes back online.

Please refer to the [Release Notes](#) for the complete listing of fixes, enhancements, known issues and work-arounds corresponding to this firmware.

Enhancements

Added support of ESXi 9.0

Removed support of ESXi 7.0

Supported Devices and Features

The D3600 / D3700 / D3610 / D3710 Enclosure can be attached to any of the following HPE Storage Controllers and Host Bus Adapters :

- o Smart Array P408e-p Controller
- o Smart Array E208e-p Controller

HPE D3610B/D3710B 12Gb SAS Disk Enclosure ROM Flash Component for VMware (ESXi)

Version: 6.00 (J) **(Recommended)**

Filename: CP072200.compsig; CP072200.md5; CP072200.zip

Important Note!

IMPORTANT: Firmware updates must be performed during a system maintenance window, with all I/O to the system halted. In single domain configuration, if user hosts an OS in D3000B(or any storage box) and flash the SEPs, it will hang/crash everytime as SmartComponent will reset the SEPs after flash/codeload.

WARNING! Do not power cycle or restart during the firmware update as this can result in loss of capabilities for this unit. It typically takes several minutes for the firmware to load.

NOTE: All firmware flash progress messages are logged to /var/cpq/D3000B.log and flash summary is logged to /var/cpq/Component.log.

Prerequisites

IMPORTANT: Firmware updates must be performed during a system maintenance window, with all I/O to the system halted.

WARNING! Do not power cycle or restart during the firmware update as this can result in loss of capabilities for this unit. It typically takes several minutes for the firmware to load.

NOTE: All firmware flash progress messages are logged to /var/cpq/D3000B.log and flash summary is logged to /var/cpq/Component.log.

Fixes

The following fixes were incorporated in this version:

- o Code optimization to save memory repo.
- o TLB exception seen while doing esp reset when expander reset was in progress.

- Added the psoc 8.93 binary in peripheral images, updated the reveille version numbers.
- Added whole new Delta PS-pmbus code , Updated the ESP version number.

Please refer to the [Release Notes](#) for the complete listing of fixes, enhancements, known issues and work-arounds corresponding to this firmware.

Enhancements

Added support of ESXi 9.0
Removed support of ESXi 7.0

Supported Devices and Features

The D3610B / D3710B Enclosure can be attached to any of the following HPE Storage Controllers and Host Bus Adapters :

- Smart Array P408e-p Controller
- Smart Array E208e-p Controller

HPE D6020 12Gb SAS Disk Enclosure ROM Flash Component for VMware (ESXi)

Version: 2.74 (W) (**Recommended**)

Filename: CP072201.compsig; CP072201.md5; CP072201.zip

Important Note!

IMPORTANT: Firmware updates must be performed during a system maintenance window, with all I/O to the system halted. In single domain configuration, if user hosts an OS in D6020(or any storage box) and flash the SEPs, it will hang/crash everytime as SmartComponent will reset the SEPs after flash/codeload.

WARNING! Do not power cycle or restart during the firmware update as this can result in loss of capabilities for this unit. It typically takes several minutes for the firmware to load.

NOTE: All firmware flash progress messages are logged to /var/cpq/D6020.log and flash summary is logged to /var/cpq/Component.log.

Prerequisites

IMPORTANT: Firmware updates must be performed during a system maintenance window, with all I/O to the system halted.

WARNING! Do not power cycle or restart during the firmware update as this can result in loss of capabilities for this unit. It typically takes several minutes for the firmware to load.

NOTE: All firmware flash progress messages are logged to /var/cpq/D6020.log and flash summary is logged to /var/cpq/Component.log.

Fixes

The following fixes were incorporated in this version:

- Temperature sensors logic inside gSEP model and SES database
- When an IOM is pulled the surviving IOM reports false critical temperatures

Please refer to the [Release Notes](#) for the complete listing of fixes, enhancements, known issues and work-arounds corresponding to this firmware.

Enhancements

Added support of ESXi 9.0
Removed support of ESXi 7.0

Supported Devices and Features

The D6020 Enclosure can be attached to any of the following HPE Storage Controllers and Host Bus Adapters :

- Smart Array P408e-p Controller
- Smart Array E208e-p Controller

HPE D8000 12Gb SAS Disk Enclosure ROM Flash Component for VMware (ESXi)

Version: 0130 (K) (**Recommended**)

Filename: CP072202.compsig; CP072202.md5; CP072202.zip

Important Note!

IMPORTANT: Firmware updates must be performed during a system maintenance window, with all I/O to the system halted. In single domain configuration, if user hosts an OS in D8000(or any storage box) and flash the SEPs, it will hang/crash everytime as SmartComponent will reset the SEPs after flash/codeload.

WARNING! Do not power cycle or restart during the firmware update as this can result in loss of capabilities for this unit. It typically takes several minutes for the firmware to load.

NOTE: All firmware flash progress messages are logged to /var/cpq/D8000.log and flash summary is logged to /var/cpq/Component.log.

Prerequisites

IMPORTANT: Firmware updates must be performed during a system maintenance window, with all I/O to the system halted.

WARNING! Do not power cycle or restart during the firmware update as this can result in loss of capabilities for this unit. It typically takes several minutes for the firmware to load.

NOTE: All firmware flash progress messages are logged to /var/cpq/D8000.log and flash summary is logged to /var/cpq/Component.log.

Fixes

The following fixes were incorporated in this version:

- o Smart Array reporting "Storage Enclosure FW upgrade Problem Detected".
- o PSU version is showing as "No Ver" after inserted the New bel power PSU.
- o GEM_5_2 Coverity defect fix.

Please refer to the [Release Notes](#) for the complete listing of fixes, enhancements, known issues and work-arounds corresponding to this firmware.

Enhancements

Added support of ESXi 9.0

Removed support of ESXi 7.0

Supported Devices and Features

The D8000 Enclosure can be attached to any of the following HPE Storage Controllers and Host Bus Adapters :

- o HPE Smart Array P408e-p Controller
- o HPE Smart Array E208e-p Controller

Online Firmware Flash for ESXi - HPE Gen11 Boot Controller NS204i-u, NS204i-d and HPE Gen10 Plus Boot Controller NS204i-p, NS204i-d
Version: 1.2.14.1018 (D) **(Recommended)**
Filename: CP070870.compsig; CP070870.zip

Enhancements

- o ESXi9.1 support.

Online ROM Flash Component for VMware ESXi - HPE 12Gb/s SAS Expander Firmware for HPE Smart Array Controllers and HPE HBA Controllers
Version: 1.2.15 (D) **(Recommended)**
Filename: CP070868.compsig; CP070868.zip

Important Note!

- o **Do NOT downgrade FW to previous version if your current expander is 5.10; please upgrade to 5.15 immediately.**

Enhancements

- o ESXi 9.1 support

Online ROM Flash Component for VMware ESXi - HPE Apollo 2000 Gen10 Plus Backplane Expander FW
Version: 1.27 (D) **(Recommended)**
Filename: CP070857.compsig; CP070857.zip

Enhancements

- o ESXi 9.1 support

Online ROM Flash Component for VMware ESXi - HPE Apollo 4200 Gen10 Plus Backplane Expander Firmware
Version: 0.39 (E) **(Recommended)**
Filename: CP070858.compsig; CP070858.zip

Prerequisites

- o Before upgrading to 0.39(D) and above, please flash to the transition version 0.39 first by standalone update approach to activate the new PID naming.
- o 0.39(B) is the minimum version for Gen10plus 4200 expander FW.
- o **0.39 transition version link:** <https://www.hpe.com/global/swpublishing/MTX-baec686eb389427aa933bbf9f0>

Enhancements

- o ESXi9.1 support.

Online ROM Flash Component for VMware ESXi - HPE Smart Array P408i-p, P408e-p, P408i-a, E208i-p, E208e-p, E208i-a, P816i-a SR Gen10 Controllers
Version: 8.23 **(Recommended)**
Filename: CP071763.compsig; CP071763.zip

Important Note!

- o HPE Service Pack for ProLiant (SPP) provides a fully qualified recipe for specific firmware and drivers released within the same cycle, making it the primary recommended choice.
- o It is strongly recommended to use controller firmware version 8.23 for SR SAS/SATA controllers and firmware version 03.01.47.052 for SR tri-mode controllers, along with Windows 2022/2025 driver version 1016.38.0.1003, Linux driver version 2.1.40-020, and VMware ESXi driver version 80.4902.0.103/90.4902.0.103, as this combination has been fully qualified.
- o For Windows 2016 driver, please use 1010.84.0.1012 in below link: <https://www.hpe.com/global/swpublishing/MTX-c523e081ab344bc4b4bc9d5686>
- o For Windows 2019 driver, please use 1016.10.0.1004 in below link: <https://www.hpe.com/global/swpublishing/MTX-29e86213c3ab4e94b0b54906f7>
- o FWPKG support for PLDM firmware upgrades was introduced. As a transition point, both OS-dependent, offline smart components and OS-independent FWPKG for PLDM firmware package updates were made available. From firmware versions later than 5.61, OS-dependent smart and offline components can only be used on DL325 and DL385 Gen10 with AMD EPYC 7xx2 Series Processors servers due to limitations associated with the PLDM Firmware Package Upgrade. Ref customer advisory [a00119198en-us](#). For servers other than DL325 and DL385 Gen10 with AMD EPYC 7xx2 Series Processors, please use OS-independent FWPKG for PLDM firmware package updates after firmware version 5.61.

Fixes

- Fixed an issue where the system could lock up with controller lockup code 0x27006 during heavy I/O when a drive reported a predictive failure, by ensuring failure handling does not block critical system monitoring operations.
- Fixed an issue where volume creation could fail when using mixed OPAL V1 and OPAL V2 self-encrypting drives (SEDs), ensuring consistent validation and successful configuration.
- Fixed an issue that could cause reduced 4K random write performance in degraded RAID 60 configurations.
- Fixed an issue where the system could crash when hot-adding drives to failed RAID 50/60 volumes, improving stability during recovery operations.
- Fixed an issue where CBE remote encryption could remain enabled after being disabled in UEFI HII, ensuring settings are applied correctly.
- Fixed an issue where the system could fail to boot during device discovery due to invalid device identification data, improving boot reliability.
- Fixed an issue where encryption key mismatches could occur during master key updates, ensuring consistent and reliable encryption operations.
- Fixed an issue where a drive could be incorrectly marked as failed during boot when a sanitize operation was in progress, preventing false drive failures.
- Fixed an issue where secure erase operations using ATA passthrough could fail to start, ensuring successful execution of secure erase commands.
- Fixed an issue where sanitize operations did not resume after a controller reboot, ensuring proper continuation of secure erase processes.
- Added support to display drive depopulation and restoration status in UEFI HII, providing better visibility into ongoing drive operations.
- Added support to display the remaining duration of array drive identification in UEFI HII, improving visibility into ongoing LED identification activity.

Adding the CA detail as below:

- For E208e-p A new Microsoft Option ROM UEFI CA 2023 certificate has been added to replace the expired CA 2011 one. To prevent Secure Boot issues, please update BIOS and "Reset All Keys to Platform Defaults" following the instructions in Advisory: (Revision) Microsoft Windows - Information About Windows UEFI CA 2023 Certificate

CA: https://support.hpe.com/hpesc/public/docDisplay?docId=emr_na-a00157968en_us

Enhancements

- Added HDD Power-On Hours reporting based on the PowerOnHours property in Drive Metrics, with periodic updates to improve drive usage visibility and indicate whether the attribute is supported by the drive.

Online ROM Flash Component for VMware ESXi - HPE Smart Array P816i-a,P416ie-m,P408i-p, P408e-p, P408i-a,P408i-c,P204i-c,E208i-p, E208e-p, E208i-a, P208i-c SR Gen10
Version: 5.61 (F) **(Recommended)**
Filename: CP070871.compsig; CP070871.zip

Important Note!

- FWPKG support for PLDM firmware upgrades was introduced. As a transition point, both OS-dependent, offline smart components and OS-independent FWPKG for PLDM firmware package updates were made available. From firmware versions later than 5.61, OS-dependent smart and offline components can only be used on DL325 and DL385 Gen10 with AMD EPYC 7xx2 Series Processors servers due to limitations associated with the PLDM Firmware Package Upgrade. Ref customer advisory [a00119198en_us](#). For servers other than DL325 and DL385 Gen10 with AMD EPYC 7xx2 Series Processors, please use OS-independent FWPKG for PLDM firmware package updates after firmware version 5.61.

Enhancements

- ESXi9.1 support.

Firmware - Storage Fibre Channel [Top](#)
HPE Firmware Flash for Emulex Fibre Channel Host Bus Adapters for VMware vSphere 8.0
Version: 2026.06.01 **(Recommended)**
Filename: CP071317.compsig; CP071317.zip

Important Note!

Release notes:

[Broadcom Release notes](#)

This Firmware package contains following firmware versions:

Adapter	Speed	Universal Boot Image	Firmware	UEFI	Boot Bios
HPE SN1200E 16Gb Dual Port Fibre Channel Host Bus Adapter	16Gb	14.4.731.21	14.4.731.21	14.4.731.20	14.4.718.0
HPE SN1200E 16Gb Single Port Fibre Channel Host Bus Adapter	16Gb	14.4.731.21	14.4.731.21	14.4.731.20	14.4.718.0
HPE SN1600E 32Gb Dual Port Fibre Channel Host Bus Adapter	32Gb	14.4.731.21	14.4.731.21	14.4.731.20	14.4.718.0
HPE SN1600E 32Gb Single Port Fibre Channel Host Bus Adapter	32Gb	14.4.731.21	14.4.731.21	14.4.731.20	14.4.718.0
HPE SN1610E 32Gb Single Port Fibre Channel Host Bus Adapter	32Gb	14.4.731.21	14.4.731.21	14.4.731.20	14.4.718.0
HPE SN1610E 32Gb Dual Port Fibre Channel Host Bus Adapter	32Gb	14.4.731.21	14.4.731.21	14.4.731.20	14.4.718.0
HPE SN1700E 64Gb Single Port Fibre Channel Host Bus Adapter	64Gb	14.4.731.21	14.4.731.21	14.4.731.20	14.4.718.0
HPE SN1700E 64Gb Dual Port Fibre Channel Host Bus Adapter	64Gb	14.4.731.21	14.4.731.21	14.4.731.20	14.4.718.0

Fixed the following:

Garbled characters are observed in the System Utilities(F9) configuration screens with Japanese Environment when HPE Emulex Fibre Channel Host Bus Adapter is installed on ProLiant Gen11 and ProLiant Gen12 servers

Added Following Enhancements:

Add logic to detect Small Form-Factor Pluggable (SFP) is non-responsive
Return a new state in Acquisition and Control Query Executive (ACQE) to indicate Small Form-Factor Pluggable(SFP) is non-responsive

These are applicable for :

- HPE SN1610E 32Gb Dual port Fibre Channel Host Bus Adapter
- HPE SN1610E 32Gb Single port Fibre Channel Host Bus Adapter
- HPE SN1700E 64Gb Dual Port Fibre Channel Host Bus Adapter

- o HPE SN1700E 64Gb Single Port Fibre Channel Host Bus Adapter

Prerequisites

Please consult SPOCK for a list of supported configurations available at the following link:

<http://www.hpe.com/storage/spock/>

Fixes

Fixed the following:

Garbled characters are observed in the System Utilities(F9) configuration screens with Japanese Environment when HPE Emulex Fibre Channel Host Bus Adapter is installed on ProLiant Gen11 and ProLiant Gen12 servers, applicable for:

- o HPE SN1610E 32Gb Dual port Fibre Channel Host Bus Adapter
- o HPE SN1610E 32Gb Single port Fibre Channel Host Bus Adapter
- o HPE SN1700E 64Gb Dual Port Fibre Channel Host Bus Adapter
- o HPE SN1700E 64Gb Single Port Fibre Channel Host Bus Adapter

Enhancements

This Firmware package contains following firmware versions:

Adapter	Speed	Universal Boot Image	Firmware	UEFI	Boot Bios
HPE SN1200E 16Gb Dual Port Fibre Channel Host Bus Adapter	16Gb	14.4.731.21	14.4.731.21	14.4.731.20	14.4.718.0
HPE SN1200E 16Gb Single Port Fibre Channel Host Bus Adapter	16Gb	14.4.731.21	14.4.731.21	14.4.731.20	14.4.718.0
HPE SN1600E 32Gb Dual Port Fibre Channel Host Bus Adapter	32Gb	14.4.731.21	14.4.731.21	14.4.731.20	14.4.718.0
HPE SN1600E 32Gb Single Port Fibre Channel Host Bus Adapter	32Gb	14.4.731.21	14.4.731.21	14.4.731.20	14.4.718.0
HPE SN1610E 32Gb Single Port Fibre Channel Host Bus Adapter	32Gb	14.4.731.21	14.4.731.21	14.4.731.20	14.4.718.0
HPE SN1610E 32Gb Dual Port Fibre Channel Host Bus Adapter	32Gb	14.4.731.21	14.4.731.21	14.4.731.20	14.4.718.0
HPE SN1700E 64Gb Single Port Fibre Channel Host Bus Adapter	64Gb	14.4.731.21	14.4.731.21	14.4.731.20	14.4.718.0
HPE SN1700E 64Gb Dual Port Fibre Channel Host Bus Adapter	64Gb	14.4.731.21	14.4.731.21	14.4.731.20	14.4.718.0

Added Following Enhancements:

- o Add logic to detect Small Form-Factor Pluggable (SFP) is non-responsive
- o Return a new state in Acquisition and Control Query Executive (ACQE) to indicate Small Form-Factor Pluggable(SFP) is non-responsive

These are applicable for :

- o HPE SN1610E 32Gb Dual port Fibre Channel Host Bus Adapter
- o HPE SN1610E 32Gb Single port Fibre Channel Host Bus Adapter
- o HPE SN1700E 64Gb Dual Port Fibre Channel Host Bus Adapter
- o HPE SN1700E 64Gb Single Port Fibre Channel Host Bus Adapter

Supported Devices and Features

This component is supported on following Emulex Fibre Channel Host Bus adapters:

16Gb FC Adapter:

- HPE SN1200E 16Gb Dual Port Fibre Channel Host Bus Adapter
- HPE SN1200E 16Gb Single Port Fibre Channel Host Bus Adapter

32Gb FC Adapter:

- HPE SN1600E 32Gb Dual Port Fibre Channel Host Bus Adapter
- HPE SN1600E 32Gb Single Port Fibre Channel Host Bus Adapter
- HPE SN1610E 32Gb Dual port Fibre Channel Host Bus Adapter
- HPE SN1610E 32Gb Single port Fibre Channel Host Bus Adapter

64Gb FC Adapter:

- HPE SN1700E 64Gb Dual Port Fibre Channel Host Bus Adapter
- HPE SN1700E 64Gb Single Port Fibre Channel Host Bus Adapter

HPE Firmware Flash for QLogic Fibre Channel Host Bus Adapters for VMware vSphere 8.0

Version: 2026.06.02 **(Recommended)**

Filename: CP072107.compsig; CP072107.zip

Important Note!

Release Notes:

[HPE QLogic Adapters Release Notes](#)

This Firmware package contains following firmware versions:

Adapter	Speed	MBI	Firmware	UEFI	BIOS	MPI FW	PEP FW	PEP SoftROM	PEP Brd Cfg 2P	PEP Brd Cfg 1P	FC Brd Cfg 2P	FC Brd Cfg 1P	PCIe Serdes	Preload FWA 2P	Preload FWA 1P
HPE SN1100Q 16GB Dual Port PCIe Fibre	16Gb	02.05.02	9.15.05	7.28	3.68	3.03.16	2.01.33	2.00.11	2.00.1	NA	2.02.7	NA	NA	2.1.9	NA

Channel Host Bus Adapter															
HPE SN1100Q 16GB Single Port PCIe Fibre Channel Host Bus Adapter	16Gb	02.05.02	9.15.05	7.28	3.68	3.03.16	2.01.33	2.00.11	NA	2.01.1	NA	2.02.7	NA	NA	2.1.9
HPE SN1600Q 32Gb Single Port Fibre Channel Host Bus Adapter	32Gb	02.05.02	9.15.05	7.28	3.68	3.03.16	2.01.33	2.00.11	NA	2.01.1	NA	2.02.7	NA	NA	2.1.9
HPE SN1600Q 32Gb Dual Port Fibre Channel Host Bus Adapter	32Gb	02.05.02	9.15.05	7.28	3.68	3.03.16	2.01.33	2.00.11	2.00.1	NA	2.02.7	Na	NA	2.1.9	NA
HPE SN1610Q 32Gb Dual Port Fibre Channel Host Bus Adapter	32Gb	02.11.14	09.15.19	7.39	NA	3.04.21	3.01.41	3.00.13	3.01.00	NA	3.07.02	NA	3.00.07	4.01.16	NA
HPE SN1610Q 32Gb Single Port Fibre Channel Host Bus Adapter	32Gb	02.11.14	09.15.19	7.39	NA	3.04.21	3.01.41	3.00.13	NA	3.02.00	NA	3.07.02	3.00.07	NA	4.05.07
HPE SN1700Q 64Gb Dual Port Fibre Channel Host Bus Adapter	64Gb	02.11.14	09.15.19	7.39	NA	3.04.21	3.01.41	3.00.13	3.01.00	NA	3.07.02	NA	3.00.07	4.01.16	NA
HPE SN1700Q 64Gb Single Port Fibre Channel Host Bus Adapter	64Gb	02.11.14	09.15.19	7.39	NA	3.04.21	3.01.41	3.00.13	NA	3.02.00	NA	3.07.02	3.00.07	NA	4.05.07

Updated UEFI signature validity

Prerequisites

Please consult SPOCK for a list of supported configurations available at the following link:

<http://www.hpe.com/storage/spock/>

Fixes

Updated UEFI signature Validity

Enhancements

This Firmware package contains following firmware versions:

Adapter	Speed	MBI	Firmware	UEFI	BIOS	MPI FW	PEP FW	PEP SoftROM	PEP Brd Cfg 2P	PEP Brd Cfg 1P	FC Brd Cfg 2P	FC Brd Cfg 1P	PCIe Serdes	Preload FWA 2P	Preload FWA 1P
HPE SN1100Q 16GB Dual Port PCIe Fibre Channel Host Bus Adapter	16Gb	02.05.02	9.15.05	7.28	3.68	3.03.16	2.01.33	2.00.11	2.00.1	NA	2.02.7	NA	NA	2.1.9	NA
HPE SN1100Q 16GB Single Port PCIe Fibre Channel Host Bus Adapter	16Gb	02.05.02	9.15.05	7.28	3.68	3.03.16	2.01.33	2.00.11	NA	2.01.1	NA	2.02.7	NA	NA	2.1.9
HPE SN1600Q 32Gb Single Port Fibre Channel Host Bus Adapter	32Gb	02.05.02	9.15.05	7.28	3.68	3.03.16	2.01.33	2.00.11	NA	2.01.1	NA	2.02.7	NA	NA	2.1.9
HPE SN1600Q 32Gb Dual Port Fibre Channel Host Bus Adapter	32Gb	02.05.02	9.15.05	7.28	3.68	3.03.16	2.01.33	2.00.11	2.00.1	NA	2.02.7	Na	NA	2.1.9	NA
HPE SN1610Q 32Gb Dual Port Fibre Channel Host Bus Adapter	32Gb	02.11.14	09.15.19	7.39	NA	3.04.21	3.01.41	3.00.13	3.01.00	NA	3.07.02	NA	3.00.07	4.01.16	NA
HPE SN1610Q 32Gb Single Port Fibre Channel Host Bus Adapter	32Gb	02.11.14	09.15.19	7.39	NA	3.04.21	3.01.41	3.00.13	NA	3.02.00	NA	3.07.02	3.00.07	NA	4.05.07
HPE SN1700Q 64Gb Dual Port Fibre Channel Host Bus Adapter	64Gb	02.11.14	09.15.19	7.39	NA	3.04.21	3.01.41	3.00.13	3.01.00	NA	3.07.02	NA	3.00.07	4.01.16	NA
HPE SN1700Q 64Gb Single Port Fibre Channel Host Bus Adapter	64Gb	02.11.14	09.15.19	7.39	NA	3.04.21	3.01.41	3.00.13	NA	3.02.00	NA	3.07.02	3.00.07	NA	4.05.07

Supported Devices and Features

This component is supported on following Qlogic Fibre Channel Host Bus adapters:

16Gb Fibre Channel Host Bus Adapter:

- HPE SN1100Q 16GB Dual Port PCIe Fibre Channel Host Bus Adapter
- HPE SN1100Q 16GB Single Port PCIe Fibre Channel Host Bus Adapter

32Gb Fibre Channel Host Bus Adapter:

- HPE SN1600Q 32Gb Single Port Fibre Channel Host Bus Adapter
- HPE SN1600Q 32Gb Dual Port Fibre Channel Host Bus Adapter
- HPE SN1610Q 32Gb Dual Port Fibre Channel Host Bus Adapter
- HPE SN1610Q 32Gb Single Port Fibre Channel Host Bus Adapter

64Gb Fibre Channel Host Bus Adapter:

- HPE SN1700Q 64Gb Dual Port Fibre Channel Host Bus Adapter
- HPE SN1700Q 64Gb Single Port Fibre Channel Host Bus Adapter

Software - Management

[Top](#)

HPE iLO Driver Bundle Smart Component for ESXi 8.0 and ESXi 9.0

Version: 2026.03.00 (**Recommended**)

Filename: cp070019.compsig; cp070019.zip

Enhancements

Added support for vSphere 9.1 OS

Smart Storage Administrator (SSA) CLI Smart Component for ESXi 8.0 for Gen10/Gen10 Plus/Gen11 Controllers

Version: 2026.07.01 (**Recommended**)

Filename: cp072100.compsig; cp072100.zip

Important Note!

- [Actual ESXi8.0 ssaccli version is 6.65.9.0](#)
- [Actual ESXi9.0 ssaccli version is 6.65.11.0](#)
- To support upgrades from ESXi 8.0 to ESXi 9.0, VMware requires the SSA CLI package version for ESXi 9.0 to be higher than the package version installed on ESXi 8.0. Therefore, the ESXi 9.0 package version is 6.65.11, while the internal SSA CLI version remains 6.65.9. This is expected behavior.

Enhancements

- Added a new reboot reason indicator when a debug token is invalidated

Software - Storage Controller

[Top](#)

HPE MegaRAID Storage Administrator StorCLI for VMware8.0 (For Gen10P and Gen11 Controllers)

Version: 2026.03.01 (**Recommended**)

Filename: cp068889.compsig; cp068889.zip

Important Note!

- Actual ESXi Version is 007.3604.0000.0000

Fixes

- Fix an issue that storcli show /cx/ex/sx poh (power on hour) command report error on NVMe drives
- Fix an issue that PSOC update is not allowing when the part number is beyond 65535

Enhancements

- Return error when enabling encryption with 256 characters for keyid in Drive Security command
- Display the controller serial number as "NA" when not programmed

Software - Storage Fibre Channel

[Top](#)

HPE QLogic Fibre Channel driver component for VMware vSphere 8.0

Version: 2026.04.01 (**Recommended**)

Filename: cp070510.compsig; cp070510.zip

Important Note!

Release Notes:

[HPE QLogic Adapters Release Notes](#)

This component is intended to be used by HPE applications. It is a zip that contains the same driver deliverable available from the vmware.com and the HPE vib depot.hpe.com webpages, plus an HPE specific CPXXXX.xml file.

This driver is only supported on VMware ESXi 8.0u3

Prerequisites

Please consult SPOCK for a list of supported configurations available at the following link:

Enhancements

Driver version 5.4.86.0-1
This driver is only supported on VMware ESXi 8.0u3

Supported Devices and Features

This component is supported on following Qlogic Fibre Channel Host Bus adapters:

16Gb Fibre Channel Host Bus Adapter:

- HPE SN1100Q 16GB Dual Port PCIe Fibre Channel Host Bus Adapter
- HPE SN1100Q 16GB Single Port PCIe Fibre Channel Host Bus Adapter

32Gb Fibre Channel Host Bus Adapter:

- HPE SN1600Q 32Gb Single Port Fibre Channel Host Bus Adapter
- HPE SN1600Q 32Gb Dual Port Fibre Channel Host Bus Adapter
- HPE SN1610Q 32Gb Dual Port Fibre Channel Host Bus Adapter
- HPE SN1610Q 32Gb Single Port Fibre Channel Host Bus Adapter

64Gb Fibre Channel Host Bus Adapter:

- HPE SN1700Q 64Gb Dual Port Fibre Channel Host Bus Adapter
- HPE SN1700Q 64Gb Single Port Fibre Channel Host Bus Adapter

Software - System Management

[Top](#)

HPE Agentless Management Bundle for ESXi for HPE Gen10 and Gen10 Plus Servers
Version: 802.11.13.0 (**Recommended**)
Filename: amsdComponent_802.11.13.0.1-1.zip

Fixes

See the [AMS Release Notes](#) for information about the issues resolved in this release.

Enhancements

See the [AMS Release Notes](#) for information about the enhancements in this release.

HPE Agentless Management Bundle Smart Component on ESXi for Gen10 and Gen10 Plus Servers
Version: 2026.03.01 (**Recommended**)
Filename: cp070839.compsig; cp070839.zip

Fixes

See the [AMS Release Notes](#) for information about the issues resolved in this release.

Enhancements

See the [AMS Release Notes](#) for information about the enhancements in this release.

Get connected

hpe.com/info/getconnected

Current HPE driver, support, and security alerts delivered directly to your desktop

© Copyright 2023 Hewlett Packard Enterprise Development Company, L.P.

The information contained herein is subject to change without notice. The only warranties for HPE products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HPE shall not be liable for technical or editorial errors or omissions contained herein.

Trademark acknowledgments, if needed.

Update August 07 2026

